



BSI Standards Publication

## 13 A plugs, socket-outlets, adaptors and connection units

Part 3: Adaptors – Specification

# Contents

	Page
<b>Foreword</b>	<b>IV</b>
1 Scope	1
2 Normative references	1
3 Terms and definitions	3
4 Conditions of use	7
5 General	7
6 General conditions for type testing	7
<i>Table 1 — Schedule of tests</i>	8
<i>Figure 5 — Gauge for plug pins</i>	9
<i>Figure 11 — GO gauge for socket-outlet</i>	10
<i>Figure 12 — Contact test gauge</i>	11
<i>Figure 14 — Non-contact test gauge</i>	12
<i>Figure 16a) — Withdrawal pull gauges for effectiveness of contact: Gauge for earthing socket contact</i>	13
7 Classification and rating	13
7.1 Classifications	13
7.2 Rating	14
8 Marking and labelling	14
<i>Table 2 — Rated current and maximum fuse rating in normal use, and load for flexing and cable grip tests related to size of flexible cable</i>	15
9 Clearances, creepage distances and solid insulation	16
9.1 Clearances	17
<i>Table 3 — Minimum clearances for basic insulation</i>	18
9.2 Creepage distances	18
<i>Table 4 — Minimum creepage distances (mm) for basic insulation</i>	19
9.3 Solid insulation	19
<i>Table 5 — Withstand voltages for insulation types</i>	19
9.4 Requirements for printed wiring boards and equivalent construction	20
10 Accessibility of live parts	20
<i>Figure 1 — Test pin</i>	20
<i>Figure 2a) — Apparatus for mechanical strength test on resilient covers</i>	21
<i>Figure 2b) — Hardware block for Figure 2a)</i>	22
11 Provision for earthing	23
12 Terminals and terminations of intermediate adaptors and adaptor plugs	24
<i>Table 6 — Torque values for screws and nuts</i>	25
13 Construction of adaptors (plug portion)	26
<i>Figure 3a) — Dimensions and disposition of pins</i>	26
<i>Figure 4b) — Concave shrinkage allowance for ISODs</i>	29
<i>Figure 6 — Apparatus for testing plug cover fixing screws</i>	32
<i>Figure 32a) — Apparatus for tests on adaptor pins</i>	34
<i>Figure 32b) — Apparatus for tests on adaptor plug pins</i>	34
<i>Figure 33 — Apparatus for torsion test on pins</i>	37
<i>Figure 7 — Mounting plate</i>	38
<i>Figure 8 — Plug pin deflection test apparatus for resilient adaptors</i>	39
<i>Figure 9 — Apparatus for abrasion test on insulating sleeves of plug pins</i>	41
<i>Figure 10 — Apparatus for pressure test at high temperature</i>	42
14 Construction of adaptors (adaptor socket-outlet portion)	43
<i>Figure 3 — Disposition of socket contacts</i>	43

	<i>Figure 13 — Test apparatus and circuit for use with contact and non contact gauges</i>	44
	<i>Figure 16b) — Withdrawal pull gauges for effectiveness of contact: Gauge for line and neutral current carrying socket contacts</i>	46
	<i>Figure 35 — Simulated plug and cable devices</i>	48
	<i>Figure 36 — Apparatus for calibration of turning moment of simulated plug</i>	50
	<i>Figure 37a) — Turning moment apparatus: Front view and side view</i>	50
	<i>Figure 37b) — Turning moment apparatus: Top view and pictorial overview</i>	51
	<i>Table 7 — Actuator test force</i>	53
15	Resistance to ageing and to humidity	53
15.1	Resistance to ageing	53
15.2	Resistance to humidity	53
16	Insulation resistance and electric strength	54
17	Temperature rise	55
	<i>Figure 34 — Test plug</i>	55
	<i>Table 8 — Permitted temperature rises</i>	57
	<i>Figure 17a) — Test apparatus for temperature rise test</i>	58
	<i>Figure 17b) — Dummy front plate for temperature rise test</i>	60
18	Breaking capacity of adaptors	61
19	Normal operation of adaptors	61
20	Connection of flexible cables and cable anchorage in intermediate adaptors and adaptor plugs	62
	<i>Figure 18 — Apparatus for flexing test</i>	65
	<i>Table 9 — Connection of flexible cables</i>	66
21	Mechanical strength	66
	<i>Figure 19 — Solid link for test on fuse clips</i>	66
	<i>Figure 38 — Solid links for test on fuse clips</i>	67
	<i>Figure 21a) — Pendulum impact test: General view of apparatus</i>	68
	<i>Figure 21b) — Pendulum impact test: Constructional details of striking elements</i>	69
	<i>Figure 21c) — Pendulum impact test: Constructional details of mounting support for test samples</i>	70
	<i>Figure 20 — Tumbling barrel</i>	71
22	Screws, current carrying parts and connections	72
23	Resistance to heat	73
	<i>Figure 23 — Apparatus for pressure test</i>	74
24	Resistance to abnormal heat and fire	75
24.1	General	75
24.2	Glow wire test	75
	<i>Table 10 — Application of glow wire test</i>	75
25	Resistance to excessive residual stresses and to rusting	76
26	(Not used)	77
27	General tests	77
<b>Annex A</b>	<b>(normative) Requirements for incorporated electronic components</b>	<b>79</b>
<b>Annex B</b>	<b>(normative) Pollution degree</b>	<b>84</b>
<b>Annex C</b>	<b>(normative) Relation between rated impulse withstand voltage, rated voltage and Overvoltage Category</b>	<b>85</b>
	<i>Table C.1 — Rated impulse withstand voltage for adaptors energized directly from the low voltage mains</i>	85
<b>Annex D</b>	<b>(normative) Determination of the Comparative Tracking Index and Proof Tracking Index</b>	<b>86</b>
<b>Annex E</b>	<b>(normative) Impulse voltage test</b>	<b>86</b>
	<i>Table E.1 — Test voltages for verifying clearances at sea level</i>	87

<b>Annex F</b>	(normative) <b>Measurement of clearances and creepage distances</b>	<b>87</b>
	<i>Table F.1 — Minimum values of width, X</i>	87
	<i>Figure F.1 — Example 1</i>	88
	<i>Figure F.2 — Example 2</i>	88
	<i>Figure F.3 — Example 3</i>	88
	<i>Figure F.4 — Example 4</i>	89
	<i>Figure F.5 — Example 5</i>	89
	<i>Figure F.6 — Example 6</i>	89
	<i>Figure F.7 — Example 7</i>	90
	<i>Figure F.8 — Example 8</i>	90
	<i>Figure F.9 — Example 9</i>	90
	<i>Figure F.10 — Example 10</i>	91
	<i>Figure F.11 — Example 11</i>	91
<b>Annex G</b>	(normative) <b>Test plug for temperature rise test</b>	<b>91</b>
	<i>Figure 30 — Test plug for temperature rise</i>	92
<b>Annex H</b>	(normative) <b>The construction and calibration of a calibrated link</b>	<b>93</b>
	<i>Figure 28 — Calibrated link</i>	94
	<i>Figure 29 — Calibration jig for calibrated link</i>	96
<b>Annex I</b>	(informative) <b>Annex identification migration from 2016 edition to 2023 edition</b>	<b>97</b>
	<i>Table I.1 — BS 1363 annex identification migration from 2016 to 2023</i>	98
	<b>Bibliography</b>	<b>100</b>

### Summary of pages

This document comprises a front cover, an inside front cover, pages I to VI, pages 1 to 100, an inside back cover and a back cover.

# Foreword

## Publishing information

This part of [BS 1363](#) is published by BSI Standards Limited, under licence from The British Standards Institution, and came into effect on 30 June 2023. It was prepared by Technical Committee PEL/23, *Electrical accessories*. A list of organizations represented on this committee can be obtained on request to the committee manager.

## Supersession

This part of [BS 1363](#) supersedes [BS 1363-3:2016+A1:2018](#) which remains current and will be withdrawn on 30 June 2026.

## Relationship with other publications

[BS 1363](#) is published in the following parts:

- *Part 1: Rewirable and non-rewirable 13 A fused plugs – Specification,*
- *Part 2: 13 A switched and unswitched socket-outlets – Specification,*
- *Part 3: Adaptors – Specification;*
- *Part 4: 13 A fused connection units: switched and unswitched – Specification;*
- *Part 5: Fused conversion plugs – Specification.*

## Information about this document

This is a full revision of the document, and introduces the following principal changes:

- the Scope now covers operating frequencies from 50 Hz to 60 Hz;
- current carrying parts made of brass are required to have a minimum content of 58% copper;
- the requirements governing voltage and current ratings of adaptors incorporating electronic components have changed;
- new adaptor requirements have been added for the maximum number of socket-outlets on the same plane;
- Annex requirements for incorporated electronic components have been modified, specifically, USB circuits intended for charging portable devices with the addition of the abnormal condition.

The numbering of figures within this standard remains as in the previous version; however, future revisions will implement consecutive numbering throughout.

[Annex A](#) gives details of the annex renumbering from the 2016 editions of [BS 1363](#), Part 1 to Part 5 to the 2023 editions.

This publication can be withdrawn, revised, partially superseded or superseded. Information regarding the status of this publication can be found in the Standards Catalogue on the BSI website at [bsigroup.com/standards](https://bsigroup.com/standards), or by contacting the Customer Services team.

Where websites and webpages have been cited, they are provided for ease of reference and are correct at the time of publication. The location of a webpage or website, or its contents, cannot be guaranteed.

### **Presentational conventions**

The provisions of this standard are presented in roman (i.e. upright) type. Its requirements are expressed in sentences in which the principal auxiliary verb is “shall”.

*Commentary, explanation and general informative material is presented in smaller italic type, and does not constitute a normative element.*

Requirements in this standard are drafted in accordance with the *Rules for the structure and drafting of UK standards:2022*, subclause **G.1.1**, which states, “Requirements should be expressed using wording such as: ‘When tested as described in Annex A, the product shall ...’”. This means that only those products that are capable of passing the specified test will be deemed to conform to this standard.

Where words have alternative spellings, the preferred spelling of the Shorter Oxford English Dictionary is used (e.g. “organization” rather than “organisation”).

### **Contractual and legal considerations**

This publication has been prepared in good faith, however no representation, warranty, assurance or undertaking (express or implied) is or will be made, and no responsibility or liability is or will be accepted by BSI in relation to the adequacy, accuracy, completeness or reasonableness of this publication. All and any such responsibility and liability is expressly disclaimed to the full extent permitted by the law.

This publication is provided as is, and is to be used at the recipient's own risk.

The recipient is advised to consider seeking professional guidance with respect to its use of this publication.

This publication is not intended to constitute a contract. Users are responsible for its correct application.

### **Compliance with a British Standard cannot confer immunity from legal obligations.**

In particular, attention is drawn to the following specific regulations:

- The Plugs and Sockets etc. (Safety) Regulations 1994. SI No. 1768 [1].

## 1 Scope

This part of [BS 1363](#) specifies requirements for adaptors having insulating sleeves on the line and neutral plug pins and suitable for use with socket-outlets conforming to BS 1363-2:2023, with particular reference to safety in normal use. Adaptors specified in this part of [BS 1363](#) are intended for household, commercial and light industrial purposes. The adaptors are suitable for the connection of portable appliances, sound vision equipment, luminaires, etc., in a.c. circuits only, operating at voltages not exceeding 250 V r.m.s. and frequencies from 50 Hz to 60 Hz. Adaptors incorporating electronic components detailed in [Annex A](#) are included within this part of [BS 1363](#).

This standard also applies to shaver adaptors which have the earth pin replaced with a similarly dimensioned protrusion made of insulating material designated as an insulated shutter opening device (ISOD) designed to operate the shutter mechanism of a socket-outlet conforming to BS 1363-2:2023.

Adaptors conforming to this standard are shuttered and therefore do not require the use of additional means to shield the current carrying contacts when no plug is present in the adaptor socket-outlets.

Assemblies comprising a plug and one or more portable socket-outlets connected together by a flexible cable are not considered to be adaptors according to this part of [BS 1363](#).

An adaptor is mechanical by nature of construction. The product is therefore immune from electromagnetic interference.

An adaptor that does not incorporate electronic devices does not emit intolerable electromagnetic interference, since significant electromagnetic disturbances are only generated during insertion and withdrawal which are not continuous.

This British Standard does not cover devices within the scope of the following standards:

- a) BS EN IEC 62368 series (direct plug-in devices);
- b) BS EN IEC 60730 series; or
- c) [BS 8546](#).

*NOTE* In order to maintain safety and interchangeability with plugs and socket-outlets, it is necessary that these products conform to the requirements of [Clause 10](#), [Clause 13](#) and [Clause 14](#), however their body outline need not be limited at a distance of 6,25 mm from the plug engagement surface.

## 2 Normative references

The following documents are referred to in the text in such a way that some or all of their content constitutes provisions, or limits the application, of this document<sup>1)</sup>. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

[BS 46:1950](#), *Specification – Two-pole and earthing-pin plugs, socket-outlets and socket-outlet adaptors*

[BS 646:1958+A2:2013](#), *Specification for cartridge fuse-links (rated up to 5 amperes) for a.c. and d.c. service*

[BS 1362:1973+A3:2021](#), *General purpose fuse links for domestic and similar purposes (primarily for use in plugs) – Specification*

[BS 1363-1:2023](#), *13 A plugs, socket-outlets, adaptors and connection units – Part 1: Rewirable and non-rewirable 13 A fused plugs – Specification*

<sup>1)</sup> Documents that are referred to solely in an informative manner are listed in the Bibliography.