

IEEE Standard for Information Technology—
Telecommunications and Information Exchange between Systems
Local and Metropolitan Area Networks—
Specific Requirements

**Part 11: Wireless LAN Medium Access Control
(MAC) and Physical Layer (PHY) Specifications**

**Amendment 1:
Enhancements for High-Efficiency WLAN**

IEEE Computer Society

Developed by the
LAN/MAN Standards Committee

IEEE Std 802.11ax™-2021
(Amendment to IEEE Std 802.11-2020)

**IEEE Standard for Information Technology—
Telecommunications and Information Exchange between Systems
Local and Metropolitan Area Networks—
Specific Requirements**

**Part 11: Wireless LAN Medium Access Control
(MAC) and Physical Layer (PHY) Specifications**

**Amendment 1:
Enhancements for High-Efficiency WLAN**

Developed by the
LAN/MAN Standards Committee
of the
IEEE Computer Society

Approved 9 February 2021
IEEE SA Standards Board

Abstract: Modifications to both the IEEE 802.11 physical layer (PHY) and medium access control (MAC) sublayer for high-efficiency operation in frequency bands between 1 GHz and 7.125 GHz are defined in this amendment to IEEE Std 802.11-2020.

Keywords: dense deployment, high efficiency, IEEE 802.11™, IEEE 802.11ax™, MAC, medium access control, OFDMA, orthogonal frequency division multiple access, PHY, physical layer, wireless local area network, WLAN

The Institute of Electrical and Electronics Engineers, Inc.
3 Park Avenue, New York, NY 10016-5997, USA

Copyright © 2021 by The Institute of Electrical and Electronics Engineers, Inc.
All rights reserved. Published 19 May 2021. Printed in the United States of America.

IEEE and 802 are registered trademarks in the U.S. Patent & Trademark Office, owned by The Institute of Electrical and Electronics Engineers, Incorporated.

Print: ISBN 978-1-5044-7389-7 STD24607
PDF: ISBN 978-1-5044-7390-3 STDPD24607

IEEE prohibits discrimination, harassment and bullying.

For more information, visit <http://www.ieee.org/web/aboutus/whatis/policies/p9-26.html>.

No part of this publication may be reproduced in any form, in an electronic retrieval system or otherwise, without the prior written permission of the publisher.

Important Notices and Disclaimers Concerning IEEE Standards Documents

IEEE Standards documents are made available for use subject to important notices and legal disclaimers. These notices and disclaimers, or a reference to this page (<https://standards.ieee.org/ipr/disclaimers.html>), appear in all standards and may be found under the heading “Important Notices and Disclaimers Concerning IEEE Standards Documents.”

Notice and Disclaimer of Liability Concerning the Use of IEEE Standards Documents

IEEE Standards documents are developed within the IEEE Societies and the Standards Coordinating Committees of the IEEE Standards Association (IEEE SA) Standards Board. IEEE develops its standards through an accredited consensus development process, which brings together volunteers representing varied viewpoints and interests to achieve the final product. IEEE Standards are documents developed by volunteers with scientific, academic, and industry-based expertise in technical working groups. Volunteers are not necessarily members of IEEE or IEEE SA, and participate without compensation from IEEE. While IEEE administers the process and establishes rules to promote fairness in the consensus development process, IEEE does not independently evaluate, test, or verify the accuracy of any of the information or the soundness of any judgments contained in its standards.

IEEE makes no warranties or representations concerning its standards, and expressly disclaims all warranties, express or implied, concerning this standard, including but not limited to the warranties of merchantability, fitness for a particular purpose and non-infringement. In addition, IEEE does not warrant or represent that the use of the material contained in its standards is free from patent infringement. IEEE Standards documents are supplied “AS IS” and “WITH ALL FAULTS.”

Use of an IEEE standard is wholly voluntary. The existence of an IEEE Standard does not imply that there are no other ways to produce, test, measure, purchase, market, or provide other goods and services related to the scope of the IEEE standard. Furthermore, the viewpoint expressed at the time a standard is approved and issued is subject to change brought about through developments in the state of the art and comments received from users of the standard.

In publishing and making its standards available, IEEE is not suggesting or rendering professional or other services for, or on behalf of, any person or entity, nor is IEEE undertaking to perform any duty owed by any other person or entity to another. Any person utilizing any IEEE Standards document, should rely upon his or her own independent judgment in the exercise of reasonable care in any given circumstances or, as appropriate, seek the advice of a competent professional in determining the appropriateness of a given IEEE standard.

IN NO EVENT SHALL IEEE BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO: THE NEED TO PROCURE SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE PUBLICATION, USE OF, OR RELIANCE UPON ANY STANDARD, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE AND REGARDLESS OF WHETHER SUCH DAMAGE WAS FORESEEABLE.

Translations

The IEEE consensus development process involves the review of documents in English only. In the event that an IEEE standard is translated, only the English version published by IEEE is the approved IEEE standard.

Official statements

A statement, written or oral, that is not processed in accordance with the IEEE SA Standards Board Operations Manual shall not be considered or inferred to be the official position of IEEE or any of its committees and shall not be considered to be, nor be relied upon as, a formal position of IEEE. At lectures, symposia, seminars, or educational courses, an individual presenting information on IEEE standards shall make it clear that the presenter's views should be considered the personal views of that individual rather than the formal position of IEEE, IEEE SA, the Standards Committee, or the Working Group.

Comments on standards

Comments for revision of IEEE Standards documents are welcome from any interested party, regardless of membership affiliation with IEEE or IEEE SA. However, **IEEE does not provide interpretation, consulting information, or advice pertaining to IEEE Standards documents.**

Suggestions for changes in documents should be in the form of a proposed change of text, together with appropriate supporting comments. Since IEEE standards represent a consensus of concerned interests, it is important that any responses to comments and questions also receive the concurrence of a balance of interests. For this reason, IEEE and the members of its Societies and Standards Coordinating Committees are not able to provide an instant response to comments, or questions except in those cases where the matter has previously been addressed. For the same reason, IEEE does not respond to interpretation requests. Any person who would like to participate in evaluating comments or in revisions to an IEEE standard is encouraged to join the relevant IEEE working group. You can indicate interest in a working group using the Interests tab in the Manage Profile & Interests area of the [IEEE SA myProject system](#). An IEEE Account is needed to access the application.

Comments on standards should be submitted using the [Contact Us](#) form.

Laws and regulations

Users of IEEE Standards documents should consult all applicable laws and regulations. Compliance with the provisions of any IEEE Standards document does not constitute compliance to any applicable regulatory requirements. Implementers of the standard are responsible for observing or referring to the applicable regulatory requirements. IEEE does not, by the publication of its standards, intend to urge action that is not in compliance with applicable laws, and these documents may not be construed as doing so.

Data privacy

Users of IEEE Standards documents should evaluate the standards for considerations of data privacy and data ownership in the context of assessing and using the standards in compliance with applicable laws and regulations.

Copyrights

IEEE draft and approved standards are copyrighted by IEEE under US and international copyright laws. They are made available by IEEE and are adopted for a wide variety of both public and private uses. These include both use, by reference, in laws and regulations, and use in private self-regulation, standardization, and the promotion of engineering practices and methods. By making these documents available for use and adoption by public authorities and private users, IEEE does not waive any rights in copyright to the documents.

Photocopies

Subject to payment of the appropriate licensing fees, IEEE will grant users a limited, non-exclusive license to photocopy portions of any individual standard for company or organizational internal use or individual, non-commercial use only. To arrange for payment of licensing fees, please contact Copyright Clearance Center, Customer Service, 222 Rosewood Drive, Danvers, MA 01923 USA; +1 978 750 8400; <https://www.copyright.com/>. Permission to photocopy portions of any individual standard for educational classroom use can also be obtained through the Copyright Clearance Center.

Updating of IEEE Standards documents

Users of IEEE Standards documents should be aware that these documents may be superseded at any time by the issuance of new editions or may be amended from time to time through the issuance of amendments, corrigenda, or errata. An official IEEE document at any point in time consists of the current edition of the document together with any amendments, corrigenda, or errata then in effect.

Every IEEE standard is subjected to review at least every 10 years. When a document is more than 10 years old and has not undergone a revision process, it is reasonable to conclude that its contents, although still of some value, do not wholly reflect the present state of the art. Users are cautioned to check to determine that they have the latest edition of any IEEE standard.

In order to determine whether a given document is the current edition and whether it has been amended through the issuance of amendments, corrigenda, or errata, visit [IEEE Xplore](#) or [contact IEEE](#). For more information about the IEEE SA or IEEE's standards development process, visit the IEEE SA Website.

Errata

Errata, if any, for all IEEE standards can be accessed on the [IEEE SA Website](#). Search for standard number and year of approval to access the web page of the published standard. Errata links are located under the Additional Resources Details section. Errata are also available in [IEEE Xplore](#). Users are encouraged to periodically check for errata.

Patents

IEEE Standards are developed in compliance with the [IEEE SA Patent Policy](#).

Attention is called to the possibility that implementation of this standard may require use of subject matter covered by patent rights. By publication of this standard, no position is taken by the IEEE with respect to the existence or validity of any patent rights in connection therewith. If a patent holder or patent applicant has filed a statement of assurance via an Accepted Letter of Assurance, then the statement is listed on the IEEE SA Website at <https://standards.ieee.org/about/submit/atl/patents.html>. Letters of Assurance may indicate whether the Submitter is willing or unwilling to grant licenses under patent rights without compensation or under reasonable rates, with reasonable terms and conditions that are demonstrably free of any unfair discrimination to applicants desiring to obtain such licenses.

Essential Patent Claims may exist for which a Letter of Assurance has not been received. The IEEE is not responsible for identifying Essential Patent Claims for which a license may be required, for conducting inquiries into the legal validity or scope of Patents Claims, or determining whether any licensing terms or conditions provided in connection with submission of a Letter of Assurance, if any, or in any licensing agreements are reasonable or non-discriminatory. Users of this standard are expressly advised that determination of the validity of any patent rights, and the risk of infringement of such rights, is entirely their own responsibility. Further information may be obtained from the IEEE Standards Association.

IMPORTANT NOTICE

IEEE Standards do not guarantee or ensure safety, security, health, or environmental protection, or ensure against interference with or from other devices or networks. IEEE Standards development activities consider research and information presented to the standards development group in developing any safety recommendations. Other information about safety practices, changes in technology or technology implementation, or impact by peripheral systems also may be pertinent to safety considerations during implementation of the standard. Implementers and users of IEEE Standards documents are responsible for determining and complying with all appropriate safety, security, environmental, health, and interference protection practices and all applicable laws and regulations.

Participants

At the time this amendment was sent to the IEEE SA Board for approval, the IEEE 802.11 Working Group had the following officers:

Dorothy Stanley, Chair
Jon W. Rosdahl, 1st Vice Chair
Robert Stacey, 2nd Vice Chair
Stephen McCann, Secretary

Osama Aboul-Magd, IEEE 802.11ax Task Group Chair
Ron Porat, IEEE 802.11ax Task Group 1st Vice Chair
Alfred Asterjadhi, IEEE 802.11ax Task Group 2nd Vice Chair
Yasuhiko Inoue, IEEE 802.11ax Task Group Secretary
Robert Stacey, IEEE 802.11ax Task Group Technical Editor

Tomoko Adachi	Peter Ecclesine	Vincent Knowles Jones
Jinsoo Ahn	Richard Edgar	Volker Jungnickel
Woojin Ahn	Marc Emmelmann	Christoph Jurczyk
Kosuke Aio	Vinko Erceg	Carl Kopp
Carlos H. Aldana	Andrew Estrada	Muhammad Kakani
Yaron Alpert	Ping Fang	Mirza Mehmedovic
Song-Haur An	Yonggang Fang	Alfonsina Kapetanovic
Carol Ansley	Xiang Feng	Amir Y. Kasher
Lee R. Armstrong	Norman Finn	Oren Kedem
Yusuke Asai	Matthew J. Fischer	Richard H. Kennedy
Kwok Shum S. Au	Michael Fischer	Stuart J. Kerry
Vijay Auluck	Shunsuke Fujio	Evgeny Khorov
Geert A. Awater	Sho Furuichi	Jeongki Kim
Shahrnaz Azizi	Ming Gan	Jin Min Kim
Robert Baeten	Eduard Garcia Villanova	Sang Gook Kim
Eugene Baik	Chittabrata Ghosh	Suhwook Kim
Stephane Baron	James P. Gilb	Yongho Kim
Anuj Batra	Tim Gilmer	Youhan Kim
Friedbert Berens	Niranjana Grandhe	Jarkko Knecht
Christian Berger	Michael Grigat	Geonjung Ko
Nehru Bhandaru	Yan Guo	Fumihide Kojima
John Buffington	Yuchen Guo	Bruce P. Kraemer
George Calcev	Robert Hall	Manish Kumar
Rui Cao	Xiao Han	Rajesh Kumar
Laurent Cariou	Thomas Handte	Massinissa Lalam
William Carney	Christopher J. Hansen	Zhou Lan
Ricky Chair	Chris Hartman	Leonardo Lanante
Clint F. Chaplin	Victor Hayes	James Lansford
Jiamin Chen	Allen D. Heberling	Jae Seung S. Lee
Xiaogang Chen	Ahmadreza Hedayat	Sungeun Lee
George Chen	Robert F. Heile	Suzanne Leicht
Dmitry Cherniack	Guido R. Hiertz	James Lepp
Rojan Chitrakar	Duncan Ho	Joseph Levy
Hangyu Cho	Hanseul Hong	Dejian Li
Jinsoo Choi	Koji Horisaki	Guoqing Li
Yongbin Chu	Chunyu Hu	Huan-Bang Li
Jinyoung Chun	Lei Huang	Qiang Li
Jana Ciochina	Po-Kai Huang	Yanchun Li
Sean Coffey	Zhiyong Huang	Yunbo Li
Carlos Cordeiro	Sung Hyun H. Hwang	Dong Guk Lim
Claudio da Silva	Timothy Jeffries	Yingpei Lin
Subir Das	Jia Jia	Erik Lindskog
Rolf J. de Vegt	Jinjing Jiang	Der-Zheng Liu
Pierre Debergh	Liang Jin	Jianhan Liu
Donald E. Eastlake	Allan Jones	Yong Liu
		Peter Loc

Artyom Lomayev
Hui-Ling Lou
Kaiying Lv
Lily Lv
Jing Ma
Narendar Madhavan
Jouni K. Malinen
Alexander Maltsev
Hiroshi Mano
Roger Marks
Simone Merlin
Apurva Mody
Bibhu Mohanty
Hitoshi Morioka
Yuichi Morioka
Hiroyuki Motozuka
Robert Mueller
Yutaka Murakami
Andrew Myles
Patrice Nezou
Paul Nikolich
Yujin Noh
John Notor
Minseok Oh
Oghenekome Oteri
Kazuyuki Ozaki
Stephen Palm
Eunsung Park
Minyoung Park
Sung-jin Park
Glenn Parsons
Abhishek Patil
Hakan Persson
James E. Petranovich
Albert Petrick
Rethnakaran Pulikkoonattu
Dengyu Qiao
Demir Rakanovic
Enrico-Henrik Rantala
Maximilian Riegel

Mark Rison
Zhigang Rong
Kiseon Ryu
Bahareh Sadeghi
Takenori Sakamoto
Kazuyuki Sakoda
Sam Sambasivan
Hemanth Sampath
Naotaka Sato
Sigurd Schelstraete
Andy Scott
Yongho Seok
Stephen J. Shellhammer
Ian Sherlock
Shimi Shilo
Graham K. Smith
Ju-Hyung Son
Sudhir Srinivasa
Adrian P. Stephens
Noel Stott
Jung Hoon H. Suh
Takenori Sumi
Bo Sun
Chen Sun
Li-Hsiang Sun
Sheng Sun
YanJun Sun
Dennis Sundman
Minco Takai
Sagar Tamhane
Yusuke Tanaka
Kentaro Taniguchi
Wu Tao
Bin Tian
Fei Tong
Solomon A. Trainin
Yoshio Ueda
Richard D. Van Nee
Robert Van Zelst
Roberto Vangelista

Jerome Vanthournout
Prabodh Varshney
Ganesh Venkatesan
Lochan Verma
Sameer Vermani
Pascal Viger
George A. Vlantis
Chao Chun Wang
Haiming Wang
Huizhao Wang
James June J. Wang
Lei Wang
Xiaofei Wang
Xuechuan Wang
Lisa Ward
Julian Webber
Menzo M. Wentink
Leif Wilhelmsson
Eric Wong
Tianyu Wu
Yan Xin
Qi Xue
Rui Yang
Jun Yang
Eunsung Yang
Kei-Itto Yano
James Yee
Peter Yee
Su Khiong K. Yong
Christopher Young
Heejung Yu
Jian Yu
Mao Yu
SunWoong Yun
Alan Zeleznikar
Hongyuan Zhang
Xingxin Zhang
Yan Zhang
Xiayu Zheng
Lan Zhuo

The following members of the individual balloting committee voted on this amendment. Balloters may have voted for approval, disapproval, or abstention.

Osama Aboul-Magd	Ryuichi Hirata	Walter Pienciak
Tomoko Adachi	Werner Hoelzl	Clinton Powell
Robert Aiello	Oliver Holland	Venkatesha Prasad
Kosuke Aio	Glenn Hu	Emily Qi
Thomas Alexander	Yasuhiko Inoue	Demir Rakanovic
Nobumitsu Amachi	Atsushi Ito	R. K. Rannow
Carol Ansley	Raj Jain	Ranga Reddy
Butch Anton	SangKwon Jeong	Alon Regev
Alfred Asterjadhi	Joe Natharaj Juisai	Maximilian Riegel
Kwok Shum Au	Lokesh Kabra	Mark Rison
Madhusudan Banavara	Srinivas Kandala	Robert Robinson
Harry Bims	Piotr Karocki	Benjamin Rolfe
Nancy Bravin	Ruediger Kays	Jon W. Rosdahl
Jason Brent	Stuart Kerry	Kazuyuki Sakon
Vern Brethour	Evgeny Khorov	Naotaka Sato
Demetrio Bucaneg	Yongbum Kim	Sigurd Schelstraete
William Byrd	Youhan Kim	Andy Scott
Paul Cardinal	Ryota Kimura	Yongho Scott
William Carney	Patrick Kinney	Kunal Shah
Juan Carreon	Shoichi Kitazawa	Ian Sherlock
Pin Chang	Jarkko Knecht	Dieter Smely
Cheng Chen	Jan Kruys	Gram Smith
George Cherian	Yasushi Kudoh	Robert Stacey
Rojan Chitrakar	Thomas Kurihara	Dorothy Stanley
Paul Chiuchiolo	Massinissa Lalam	Thomas Starai
Charles Cook	Hyeong Ho Lee	Noel Stott
Diana Cortes	Kang Lee	Walter Struppler
Michael Cowan	Wookbong Lee	Mark Sturza
Steven Crowley	Frank Leong	Bo Sun
Claudio Da Silva	James Lepp	Li-Hsiang Sun
Hendricus De Ruijter	Joseph Levy	Yusuke Tanaka
Antonio De La Oliva Delgado	Yong Liu	Payam Torab Jahromi
Peter Ecclesine	Kaiying Liu	Solomon Trainin
Richard Edgar	Javier Lopez	Mark-Rene Uchida
Aleksander Eitan	John Mackay	Allert Van Zelst
Marc Emmelmann	Vieric Maguire	Prabodh Varshney
Yonggang Fang	Jouko Malinen	John Vergis
Xiang Feng	Jeffery Masters	Lochan Verma
Matthew Fischer	Stephen McCann	George Vlantis
Michael Fischer	Brett McClellan	Lei Wang
Avraham Freedman	Michael Montemurro	Xiaofei Wang
Sho Furuichi	Jose Morales	Lisa Ward
Devon Gayle	Ronald Murias	Hung-Yu Wei
Mariana Goldhar	Rick Murphy	Matthias Wendt
David Goodall	Andrew Myles	Menzo Wentink
Scott Griffiths	Paul Neveux	Leif Wilhelmsson
Randall Groves	Nick S. A. Nikjoo	Scott Willy
Michael Gundlach	Paul Nikolich	Andreas Wolf
Mark Hanington	Robert O'Hara	Peter Wu
Christopher Hansen	Satoshi Obara	Tianyu Wu
Timothy Harrington	Bansi Patel	Rui Yang
Robert Heile	Abhishek Patil	Yunsong Yang
Marco Hernandez	Arumugam Paventhan	James Yee
Lin Hervieu	Albert Petrick	Yu Yuan
Guido Hiertz	Brian Petry	Oren Yuen
	David Pichler	

When the IEEE SA Standards Board approved this amendment on 9 February 2021, it had the following membership:

Gary Hoffman, *Chair*
Vacant Position, *Vice Chair*
John D. Kulick, *Past Chair*
Konstantinos Karachalios, *Secretary*

Ted Burse
Doug Edwards
J. Travis Griffith
Grace Gu
Guido R. Hiertz
Joseph L. Koepfinger*
David J. Law

Howard Li
Dong Liu
Kevin Lu
Paul Nikolich
Damir Novosel
Jon W. Rosdahl

Dorothy V. Stanley
Mehmet Ulema
Lei Wang
Sha Wei
Philip B. Winston
Daidi Zhong
Jingyi Zhou

*Member Emeritus

Introduction

This introduction is not part of IEEE Std 802.11ax-2021, IEEE Standard for Information Technology—Telecommunications and Information Exchange Between Systems—Local and Metropolitan Area Networks—Specific Requirements—Part 11: Wireless LAN Medium Access Control (MAC) and Physical Layer (PHY) Specifications—Amendment 1: Enhancements for High-Efficiency WLAN.

This amendment defines modifications to both the IEEE 802.11 physical layer (PHY) and medium access control (MAC) sublayer for high-efficiency operation in frequency bands between 1 GHz and 7.125 GHz.

Contents

1.	Overview.....	36
1.4	Word usage.....	36
1.5	Terminology for mathematical, logical, and bit operations.....	37
2.	Normative references.....	37
3.	Definitions, acronyms, and abbreviations.....	37
3.1	Definitions.....	37
3.2	Definitions specific to IEEE 802.11.....	38
3.4	Acronyms and abbreviations.....	46
4.	General description.....	47
4.3	Components of the IEEE Std 802.11 architecture.....	47
4.3.15a	High-efficiency (HE) STA.....	47
4.3.19	Wireless network management.....	48
4.3.19.8	Event reporting.....	48
6.	Layer management.....	49
6.3	MLME SAP interface.....	49
6.3.3	Scan.....	49
6.3.3.2	MLME-SCAN.request.....	49
6.3.3.3	MLME-SCAN.confirm.....	50
6.3.4	Synchronization.....	53
6.3.4.2	MLME-JOIN.request.....	53
6.3.7	Associate.....	53
6.3.7.2	MLME-ASSOCIATE.request.....	53
6.3.7.3	MLME-ASSOCIATE.confirm.....	54
6.3.7.4	MLME-ASSOCIATE.indication.....	56
6.3.7.5	MLME-ASSOCIATE.response.....	57
6.3.8	Reassociate.....	59
6.3.8.2	MLME-REASSOCIATE.request.....	59
6.3.8.3	MLME-REASSOCIATE.confirm.....	60
6.3.8.4	MLME-REASSOCIATE.indication.....	61
6.3.8.5	MLME-REASSOCIATE.response.....	62
6.3.11	Start.....	64
6.3.11.2	MLME-START.request.....	64
6.3.118	Quiet time period.....	65
6.3.118.1	Introduction.....	65
6.3.118.2	MLME-QTP.request.....	65
6.3.118.3	MLME-QTP.indication.....	66
6.3.118.4	MLME-QTP.response.....	67
6.3.118.5	MLME-QTP.confirm.....	68
6.5	PLME SAP interface.....	69
6.5.6	PLME-TXTIME.confirm.....	69
6.5.6.2	Semantics of the service primitive.....	69

8.	PHY service specification.....	71
8.3	Detailed PHY service specifications.....	71
8.3.4	Basic service and options.....	71
8.3.4.2	PHY-SAP inter-(sub)layer service primitives	71
8.3.4.3	PHY SAP service primitives parameters	71
8.3.4.4	Vector descriptions	71
8.3.5	PHY SAP detailed service specification.....	72
8.3.5.2	PHY-DATA.request	72
8.3.5.3	PHY-DATA.indication	72
8.3.5.10	PHY-CCARESET.request	73
8.3.5.12	PHY-CCA.indication	73
8.3.5.16	PHY-TRIGGER.request	74
9.	Frame formats	76
9.2	MAC frame formats.....	76
9.2.4	Frame fields	76
9.2.4.1	Frame Control field.....	76
9.2.4.3	Address fields	77
9.2.4.5	QoS Control field.....	78
9.2.4.6	HT Control field.....	80
9.2.4.6a	Control subfield variants of an A-Control subfield	83
9.2.4.7	Frame Body field	92
9.2.5	Duration/ID field (QoS STA)	93
9.2.5.2	Setting for single and multiple protection under enhanced distributed channel access (EDCA)	93
9.2.5.7	Setting for control response frames	95
9.2.5.8	Setting for other response frames	95
9.3	Format of individual frame types.....	95
9.3.1	Control frames	95
9.3.1.2	RTS frame format	95
9.3.1.3	CTS frame format	96
9.3.1.5	PS-Poll frame format	96
9.3.1.6	CF-End frame format.....	96
9.3.1.7	BlockAckReq frame format.....	96
9.3.1.8	BlockAck frame format	97
9.3.1.19	VHT/HE NDP Announcement frame format	104
9.3.1.22	Trigger frame format	107
9.3.2	Data frames	119
9.3.2.1	Format of Data frames	119
9.3.3	(PV0) Management frames.....	120
9.3.3.2	Beacon frame format	120
9.3.3.5	Association Request frame format.....	122
9.3.3.6	Association Response frame format	123
9.3.3.7	Reassociation Request frame format	124
9.3.3.8	Reassociation Response frame format	125
9.3.3.9	Probe Request frame format	126
9.3.3.10	Probe Response frame format.....	127
9.3.3.13	Action frame format.....	129
9.3.4	Extension frames.....	129
9.3.4.2	DMG Beacon	129
9.3.4.3	S1G Beacon frame format	129

9.4	Management and Extension frame body components	130
9.4.1	Fields that are not elements	130
9.4.1.7	Reason Code field	130
9.4.1.9	Status Code field	130
9.4.1.11	Action field	130
9.4.1.17	QoS Info field	131
9.4.1.45	Band ID field	131
9.4.1.53	Operating Mode field.....	132
9.4.1.60	TWT Information field	133
9.4.1.64	HE MIMO Control field	134
9.4.1.65	HE Compressed Beamforming Report field.....	136
9.4.1.66	HE MU Exclusive Beamforming Report field	143
9.4.1.67	HE CQI Report field	145
9.4.2	Elements.....	146
9.4.2.1	General.....	146
9.4.2.3	Supported Rates and BSS Membership Selectors element.....	147
9.4.2.5	TIM element	147
9.4.2.8	Country element.....	148
9.4.2.26	Extended Capabilities element.....	149
9.4.2.28	EDCA Parameter Set element.....	150
9.4.2.29	TSPEC element.....	151
9.4.2.36	Neighbor Report element.....	153
9.4.2.45	Multiple BSSID element.....	155
9.4.2.63	Channel Switch Timing element.....	156
9.4.2.66	Event Request element.....	157
9.4.2.67	Event Report element.....	157
9.4.2.73	Multiple BSSID-Index element	158
9.4.2.139	ADDBA Extension element.....	158
9.4.2.157	VHT Capabilities element	159
9.4.2.159	Extended BSS Load element	159
9.4.2.161	Transmit Power Envelope element.....	160
9.4.2.170	Reduced Neighbor Report element.....	164
9.4.2.177	FILS Request Parameters element.....	167
9.4.2.199	TWT element	167
9.4.2.248	HE Capabilities element	175
9.4.2.249	HE Operation element	197
9.4.2.250	UORA Parameter Set element	200
9.4.2.251	MU EDCA Parameter Set element	200
9.4.2.252	Spatial Reuse Parameter Set element.....	201
9.4.2.253	NDP Feedback Report Parameter Set element	203
9.4.2.254	BSS Color Change Announcement element.....	203
9.4.2.255	Quiet Time Period element	204
9.4.2.256	ESS Report element	207
9.4.2.257	OPS element	208
9.4.2.258	TWT Constraint Parameters element.....	208
9.4.2.259	HE BSS Load element	208
9.4.2.260	Multiple BSSID Configuration element	210
9.4.2.261	Known BSSID element.....	210
9.4.2.262	Short SSID List element	211
9.4.2.263	HE 6 GHz Band Capabilities element	211
9.4.2.264	UL MU Power Capabilities element.....	212
9.6	Action frame format details	213
9.6.1	Introduction General	213
9.6.7	Public Action details	213

9.6.7.16	TDLs Discovery Response frame format.....	213
9.6.7.36	FILS Discovery frame format.....	213
9.6.12	TDLs Action field formats	215
9.6.12.2	TDLs Setup Request Action field format.....	215
9.6.12.3	TDLs Setup Response Action field format	216
9.6.12.4	TDLs Setup Confirm Action field format.....	216
9.6.15	Self-protected Action frame details	217
9.6.15.2	Mesh Peering Open frame format.....	217
9.6.15.3	Mesh Peering Confirm frame format.....	217
9.6.24	Unprotected SIG Action frame details.....	217
9.6.24.1	Unprotected SIG Action field	217
9.6.24.8	TWT Setup frame format.....	218
9.6.24.9	TWT Teardown frame format.....	218
9.6.24.12	TWT Information frame format.....	219
9.6.31	HE Action frame details	220
9.6.31.1	HE Action field.....	220
9.6.31.2	HE Compressed Beamforming/CQI frame format	220
9.6.31.3	Quiet Time Period action frame format.....	221
9.6.31.4	OPS frame format	221
9.6.32	Protected HE Action frame details	221
9.6.32.1	Protected HE Action field.....	221
9.6.32.2	HE BSS Color Change Announcement frame format	222
9.6.32.3	MU EDCA Reset frame format	222
9.7	Aggregate MPDU (A-MPDU).....	223
9.7.1	A-MPDU format.....	223
9.7.3	A-MPDU contents	225
10.	MAC sublayer functional description.....	234
10.1	Introduction.....	234
10.2	MAC architecture	234
10.2.1	General.....	234
10.2.3	Hybrid coordination function (HCF)	235
10.2.3.2	HCF contention based channel access (EDCA)	235
10.2.4a	Triggered uplink access (TUA)	235
10.2.5	Combined use of DCF, and HCF, and TUA.....	235
10.3	DCF.....	236
10.3.1	General.....	236
10.3.2	Procedures common to the DCF and EDCAF	236
10.3.2.1	CS mechanism	236
10.3.2.3	IFS.....	237
10.3.2.4	Setting and resetting the NAV	237
10.3.2.6	RTS/CTS with fragmentation	239
10.3.2.13	MU acknowledgment procedure.....	239
10.3.3	Random backoff time.....	242
10.3.4	DCF access procedure	242
10.3.4.4	Recovery procedures and retransmit limits	242
10.3.5	Individually addressed MPDU transfer procedure	242
10.3.7	DCF timing relations	243
10.3.8	Signal extension.....	243
10.4	MSDU, A-MSDU, and MMPDU fragmentation.....	243
10.5	MSDU, A-MSDU, and MMPDU defragmentation	244
10.6	Multirate support.....	244
10.6.1	Overview.....	244

10.6.5	Rate selection for Data and Management frames	244
10.6.5.1	Rate selection for non-STBC Beacon and non-STBC PSMP frames.....	244
10.6.5.3	Rate selection for other group addressed Data and Management frames	245
10.6.6	Rate selection for Control frames	245
10.6.6.1	General rules for rate selection for Control frames	245
10.6.6.6	Channel Width selection for Control frames	245
10.6.10	Modulation classes.....	246
10.6.11	Non-HT basic rate calculation	247
10.6.12	Channel Width in non-HT and non-HT duplicate PPDU's	248
10.6.13	Rate selection constraints for VHT STAs.....	248
10.6.13.3	Additional rate selection constraints for VHT PPDU's	248
10.8	HT Control field operation	249
10.9	Control Wrapper operation	251
10.11	A-MSDU operation.....	251
10.12	A-MPDU operation.....	252
10.12.1	A-MPDU contents	252
10.12.2	A-MPDU length limit rules	252
10.12.3	Minimum MPDU Sstart Spacing field rules	254
10.12.4	A-MPDU aggregation of group addressed Data frames	254
10.12.6	A-MPDU padding for VHT PPDU, HE, or SIG PPDU.....	256
10.12.7	Setting the EOF/Tag field of the MPDU delimiter.....	256
10.13	PPDU duration constraint	256
10.15	Low-density parity check code (LDPC) operation	256
10.22	Operation across regulatory domains	257
10.22.3	Operation with operating classes	257
10.22.4	Operation with the Transmit Power Envelope element	258
10.23	HCF.....	259
10.23.1	General.....	259
10.23.2	HCF contention based channel access (EDCA)	259
10.23.2.2	EDCA backoff procedure	259
10.23.2.4	Obtaining an EDCA TXOP	260
10.23.2.5	EDCA channel access in a VHT, HE, or TVHT BSS	261
10.23.2.7	Sharing an EDCA TXOP	262
10.23.2.8	Multiple frame transmission in an EDCA TXOP	263
10.23.2.9	TXOP limits	265
10.23.2.10	Truncation of TXOP	267
10.23.2.11	Termination of TXOP	267
10.23.2.12	Retransmit procedures	267
10.23.3	HCF controlled channel access (HCCA)	268
10.23.3.5	HCCA transfer rules	268
10.25	Block acknowledgment (block ack)	268
10.25.2	Setup and modification of the block ack parameters.....	268
10.25.5	Selection of BlockAck and BlockAckReq variants.....	268
10.25.6	HT-immediate block ack extensions.....	269
10.25.6.1	Introduction to HT-immediate block ack extensions.....	269
10.25.6.3	Scoreboard context control during full-state operation	270
10.25.6.5	Generation and transmission of BlockAck frames by an HT STA, DMG STA, or SIG STA.....	270
10.25.6.6	Receive reordering buffer control operation.....	270
10.25.8	GCR and GLK-GCR block ack	271
10.25.8.1	Introduction General	271
10.25.8.4	GCR block ack BlockAckReq and BlockAck frame exchanges	271
10.27	Protection mechanisms	273
10.27.6	Protection rules for HE STAs	273

10.29	Reverse direction protocol	273
10.29.1	General.....	273
10.29.2	Reverse direction (RD) exchange sequence	273
10.29.3	Rules for RD initiator	274
10.29.4	Rules for RD responder	275
10.36	Null data PDU (NDP) sounding	276
10.36.6	Transmission of a VHT NDP.....	276
10.47	Target wake time (TWT)	276
10.47.1	TWT overview.....	276
10.47.9	TWT parameter ranges	280
11.	MLME	281
11.1	Synchronization	281
11.1.3	Maintaining synchronization	281
11.1.3.8	Multiple BSSID procedure	281
11.1.4	Acquiring synchronization, scanning	286
11.1.4.3	Active scanning and probing procedures.....	286
11.2	Power management.....	287
11.2.3	Power management in a non-DMG infrastructure network.....	287
11.2.3.2	Non-AP STA power management modes.....	287
11.2.3.6	AP operation	288
11.2.3.7	Receive operation for STAs in PS mode	289
11.2.3.9	STAs operating in active mode.....	290
11.2.3.15	TIM Broadcast	290
11.2.6	SM power save.....	291
11.3	STA authentication and association.....	293
11.3.3	Frame filtering based on STA state	293
11.3.5	Association, reassociation, and disassociation	293
11.3.5.3	AP or PCP association receipt procedures.....	293
11.3.5.5	AP or PCP reassociation receipt procedures.....	293
11.3.8	Neighbor report information upon rejection with suggested BSS transition.....	293
11.4	TS operation.....	294
11.4.4	TS setup	294
11.4.4.4	TS setup procedures for both AP and non-AP STA initiation.....	294
11.7	TPC procedures.....	294
11.7.1	General.....	294
11.7.2	Association based on transmit power capability.....	294
11.7.3	Peering based on transmit power capability	294
11.7.5	Specification of regulatory and local maximum transmit power levels	295
11.7.6	Transmit power selection.....	297
11.10	Radio measurement procedures	297
11.10.14	Multiple BSSID set.....	297
11.20	Tunneled direct-link setup	298
11.20.1	General.....	298
11.21	Wireless network management procedures	298
11.21.2	Event request and report procedures.....	298
11.21.2.1	Event request and event report.....	298
11.21.2.7	BSS color collision event.....	298
11.21.2.8	BSS color in use event.....	299
11.21.6	Fine timing measurement (FTM) procedure.....	299
11.21.6.4	Measurement exchange.....	299
11.21.7	BSS transition management for network load balancing.....	299
11.21.7.1	BSS transition capability	299

11.21.7.4	BSS transition management response.....	299
11.21.7.5	Planned ESS.....	300
11.31	Multi-band operation	300
11.31.5	On-channel Tunneling (OCT) operation.....	300
11.45	Fast Initial Link Setup (FILS) procedures	301
11.45.2	FILS Discovery frame generation and usage.....	301
11.45.2.1	FILS Discovery frame transmission	301
11.49	Reduced neighbor report.....	302
11.53	Out-of-band discovery of a 6 GHz BSS	304
12.	Security	307
12.5	RSNA confidentiality and integrity protocols	307
12.5.3	CTR with CBC-MAC protocol (CCMP).....	307
12.5.3.3	CCMP cryptographic encapsulation	307
12.5.5	GCM protocol (GCMP).....	307
12.5.5.3	GCMP cryptographic encapsulation.....	307
12.12	Constraints on allowed security parameters	307
12.12.1	Introduction.....	307
12.12.2	Security constraints in the 6 GHz band	307
14.	MLME mesh procedures	309
14.2	Mesh discovery	309
14.2.4	Mesh STA configuration	309
14.2.7	Candidate peer mesh STA	309
18.	Extended Rate PHY (ERP) specification.....	310
18.2	PHY-specific service parameter list	310
26.	High-efficiency (HE) MAC specification.....	311
26.1	Introduction.....	311
26.2	HE channel access	311
26.2.1	TXOP duration-based RTS/CTS	311
26.2.2	Intra-BSS and inter-BSS PPDU classification.....	312
26.2.3	SRG PPDU identification	313
26.2.4	Updating two NAVs	314
26.2.5	Truncation of TXOP	315
26.2.6	MU-RTS Trigger/CTS frame exchange procedure	316
26.2.6.1	General.....	316
26.2.6.2	MU-RTS Trigger frame transmission.....	317
26.2.6.3	CTS frame response to an MU-RTS Trigger frame	318
26.2.7	EDCA operation using MU EDCA parameters	319
26.2.8	Multiple frame transmission in an EDCA TXOP in the 6 GHz band.....	321
26.3	Fragmentation and defragmentation	321
26.3.1	General.....	321
26.3.2	Dynamic fragmentation	323
26.3.2.1	General.....	323
26.3.2.2	Level 1 dynamic fragmentation	324
26.3.2.3	Level 2 dynamic fragmentation	324
26.3.2.4	Level 3 dynamic fragmentation	324

26.3.3	Dynamic defragmentation.....	325
26.3.3.1	General.....	325
26.3.3.2	Level 1 dynamic defragmentation	326
26.3.3.3	Level 2 dynamic defragmentation	326
26.3.3.4	Level 3 dynamic defragmentation	327
26.4	HE acknowledgment procedure.....	328
26.4.1	Overview.....	328
26.4.2	Acknowledgment context in a Multi-STA BlockAck frame	330
26.4.3	Negotiation of block ack bitmap lengths	332
26.4.4	Per-PPDU acknowledgment selection rules	333
26.4.4.1	General.....	333
26.4.4.2	Responding to an HE SU PPDU or HE ER SU PPDU with an SU PPDU	333
26.4.4.3	Responding to an HE MU PPDU with an SU PPDU	334
26.4.4.4	Responding to an HE MU PPDU, HE SU PPDU, or HE ER SU PPDU with an HE TB PPDU	334
26.4.4.5	Responding to an HE TB PPDU with an SU PPDU.....	335
26.4.4.6	Responding to an HE TB PPDU with an HE MU PPDU	336
26.4.5	HE block acknowledgment request and response rules.....	337
26.5	MU operation.....	338
26.5.1	HE DL MU operation	338
26.5.1.1	General.....	338
26.5.1.2	RU addressing in an HE MU PPDU	338
26.5.1.3	RU allocation in an HE MU PPDU	340
26.5.2	UL MU operation.....	341
26.5.2.1	General.....	341
26.5.2.2	Rules for soliciting UL MU frames	341
26.5.2.3	Non-AP STA behavior for UL MU operation	349
26.5.2.4	A-MPDU contents in an HE TB PPDU	353
26.5.2.5	UL MU CS mechanism.....	356
26.5.3	MU cascading sequence.....	357
26.5.4	UL OFDMA-based random access (UORA).....	358
26.5.4.1	General.....	358
26.5.4.2	Eligible RA-RUs.....	359
26.5.4.3	Transmission procedure for UORA	360
26.5.4.4	Retransmission procedure for UORA.....	362
26.5.4.5	Additional considerations for unassociated STAs	362
26.5.5	Buffer status report operation	363
26.5.6	Bandwidth query report operation	365
26.5.7	NDP feedback report procedure	366
26.5.7.1	General.....	366
26.5.7.2	STA behavior	366
26.5.7.3	AP behavior	368
26.5.7.4	NDP feedback report for a resource request.....	368
26.5.7.5	Power save operation with NDP feedback report procedure	369
26.5.8	Use of TSPEC by HE STAs	369
26.5.9	UL MU transmit power capabilities	369
26.6	A-MPDU operation in an HE PPDU	369
26.6.1	General.....	369
26.6.2	A-MPDU padding in an HE PPDU	371
26.6.2.1	General.....	371
26.6.2.2	A-MPDU padding in an HE SU PPDU, HE ER SU PPDU, and HE MU PPDU	371
26.6.2.3	A-MPDU padding in an HE TB PPDU	371

26.6.3	Multi-TID A-MPDU and ack-enabled single-TID A-MPDU	372
26.6.3.1	General.....	372
26.6.3.2	Ack-enabled single-TID A-MPDU operation.....	374
26.6.3.3	Non-ack-enabled multi-TID A-MPDU operation.....	374
26.6.3.4	Ack-enabled multi-TID A-MPDU operation.....	374
26.7	HE sounding protocol	375
26.7.1	General.....	375
26.7.2	HE sounding protocol	375
26.7.3	Rules for HE sounding protocol sequences	378
26.7.4	Rules for generating segmented feedback	384
26.7.5	HE sounding NDP transmission	385
26.8	TWT operation.....	385
26.8.1	General.....	385
26.8.2	Individual TWT agreements	386
26.8.3	Broadcast TWT operation.....	390
26.8.3.1	General.....	390
26.8.3.2	Rules for TWT scheduling AP.....	392
26.8.3.3	Rules for TWT scheduled STA	396
26.8.4	Use of TWT Information frames	400
26.8.4.1	General.....	400
26.8.4.2	TWT Information frame exchange for individual TWT.....	401
26.8.4.3	TWT Information frame exchange for broadcast TWT.....	402
26.8.4.4	TWT Information frame exchange for flexible wake time.....	403
26.8.5	Power save operation during TWT SPs.....	404
26.8.6	Negotiation of wake TBTT and wake interval	405
26.8.7	HE subchannel selective transmission.....	407
26.8.7.1	General.....	407
26.8.7.2	SST operation	407
26.9	Operating mode indication.....	408
26.9.1	General.....	408
26.9.2	Receive operating mode (ROM) indication.....	411
26.9.3	Transmit operating mode (TOM) indication	412
26.10	Spatial reuse operation.....	413
26.10.1	General.....	413
26.10.2	OBSS PD-based spatial reuse operation.....	414
26.10.2.1	General.....	414
26.10.2.2	General operation with non-SRG OBSS PD level.....	414
26.10.2.3	General operation with SRG OBSS PD level.....	416
26.10.2.4	Adjustment of OBSS PD and transmit power	417
26.10.2.5	OBSS PD SR transmit power restriction period.....	420
26.10.2.6	OBSS PD-based spatial reuse backoff procedure.....	421
26.10.3	PSR-based spatial reuse operation.....	422
26.10.3.1	General.....	422
26.10.3.2	PSR-based spatial reuse initiation.....	422
26.10.3.3	PSR-based spatial reuse backoff procedure.....	423
26.10.3.4	UL Spatial Reuse subfield of Trigger frame.....	423
26.10.3.5	PSRT PPDU transmission requirements.....	424
26.10.3.6	PSRT PPDU reception and response transmission requirements.....	424
26.10.4	Interaction of OBSS PD and PSR-based spatial reuse	424
26.11	Rules for setting some TXVECTOR parameters for PPDU transmitted by an HE STA.....	425
26.11.1	STA_ID.....	425
26.11.2	UPLINK_FLAG	426
26.11.3	BEAM_CHANGE	426
26.11.4	BSS_COLOR.....	426

26.11.5	TXOP_DURATION	427
26.11.6	SPATIAL_REUSE	428
26.11.7	INACTIVE_SUBCHANNELS and RU_ALLOCATION	430
26.11.8	TRIGGER_RESPONDING	431
26.11.9	STBC and DCM.....	431
26.12	HE PDU post-FEC padding and packet extension	432
26.13	Link adaptation using the HLA Control subfield	433
26.14	Power management.....	435
26.14.1	Intra-PPDU power save for non-AP HE STAs.....	435
26.14.2	Power save with UORA and TWT	436
26.14.3	Opportunistic power save	437
26.14.3.1	General.....	437
26.14.3.2	AP operation for opportunistic power save	437
26.14.3.3	STA operation for opportunistic power save	438
26.14.4	HE dynamic SM power save	438
26.15	PPDU format, BW, MCS, NSS, and DCM selection rules	439
26.15.1	General.....	439
26.15.2	PPDU format selection	439
26.15.3	MCS, NSS, BW, and DCM selection	441
26.15.4	Rate selection constraints for HE STAs	443
26.15.4.1	Receive HE-MCS and NSS Set	443
26.15.4.2	Transmit HE-MCS and NSS Set.....	444
26.15.4.3	Additional rate selection constraints for HE PDUs	444
26.15.4.4	Rx Supported VHT-MCS and NSS Set	445
26.15.5	Additional rules for ER beacons and group addressed frames	445
26.15.6	Additional rules for HE beacons and group addressed frames	445
26.15.7	Additional rules for group addressed frames in an HE MU PDU	446
26.15.8	Additional rules for PDUs sent in the 6 GHz band	447
26.16	Midamble parameter setting rules.....	448
26.17	HE BSS operation.....	449
26.17.1	Basic HE BSS operation	449
26.17.2	HE BSS operation in the 6 GHz band.....	452
26.17.2.1	General.....	452
26.17.2.2	Beacons in the 6 GHz band.....	454
26.17.2.3	Scanning in the 6 GHz band	455
26.17.2.4	HE STA antenna indication	458
26.17.3	BSS color	458
26.17.3.1	General.....	458
26.17.3.2	Initial BSS color.....	458
26.17.3.3	Disabling BSS color.....	458
26.17.3.4	Selecting and advertising a new BSS color	459
26.17.3.5	Detecting and reporting BSS color collision	460
26.17.4	AID assignment	461
26.17.5	Quiet HE STAs in an HE BSS.....	461
26.17.5.1	General.....	461
26.17.5.2	QTP Requesting STA procedure	462
26.17.5.3	Responding AP procedure	463
26.17.6	ER beacon generation in an ER BSS	463
26.17.7	Co-hosted BSSID set	464
27.	High-efficiency (HE) PHY specification.....	465
27.1	Introduction.....	465
27.1.1	Introduction to the HE PHY	465

27.1.2	Scope.....	470
27.1.3	HE PHY functions	470
27.1.3.1	General.....	470
27.1.3.2	PHY management entity (PLME).....	470
27.1.3.3	Service specification method	470
27.1.4	PPDU formats	470
27.2	HE PHY service interface.....	471
27.2.1	Introduction.....	471
27.2.2	TXVECTOR and RXVECTOR parameters	471
27.2.3	TRIGVECTOR parameters.....	488
27.2.4	PHYCONFIG_VECTOR parameters	489
27.2.5	Effects of CH_BANDWIDTH parameter on PPDU format.....	490
27.2.6	Support for non-HT, HT, and VHT formats	493
27.2.6.1	General.....	493
27.2.6.2	Support for non-HT format.....	494
27.2.6.3	Support for HT format	496
27.2.6.4	Support for VHT format	496
27.3	HE PHY	496
27.3.1	Introduction.....	496
27.3.1.1	MU transmission.....	497
27.3.1.2	OFDMA	497
27.3.2	Subcarrier and resource allocation.....	498
27.3.2.1	General.....	498
27.3.2.2	Resource unit, guard, and DC subcarriers	498
27.3.2.3	Null subcarriers.....	504
27.3.2.4	Pilot subcarriers	505
27.3.2.5	Resource indication and User identification in an HE MU PPDU	505
27.3.2.6	Resource allocation for an HE TB PPDU.....	506
27.3.2.7	20 MHz operating non-AP HE STAs	506
27.3.2.8	RU restrictions for 20 MHz operation	507
27.3.2.9	80 MHz operating non-AP HE STAs	508
27.3.3	MU-MIMO	508
27.3.3.1	DL MU-MIMO	508
27.3.3.2	UL MU-MIMO	509
27.3.4	HE PPDU formats.....	510
27.3.5	Transmitter block diagram.....	513
27.3.6	Overview of the PPDU encoding process.....	521
27.3.6.1	General.....	521
27.3.6.2	Construction of L-STF field	521
27.3.6.3	Construction of L-LTF field	522
27.3.6.4	Construction of L-SIG field.....	522
27.3.6.5	Construction of RL-SIG field	523
27.3.6.6	Construction of HE-SIG-A field.....	523
27.3.6.7	Construction of HE-SIG-B field	525
27.3.6.8	Construction of HE-STF field.....	525
27.3.6.9	Construction of HE-LTF field	525
27.3.6.10	Construction of the Data field in an HE SU PPDU, HE ER SU PPDU, and HE TB PPDU	526
27.3.6.11	Construction of the Data field in an HE MU PPDU.....	527
27.3.7	HE modulation and coding schemes (HE-MCSs)	528
27.3.8	HE-SIG-B modulation and coding schemes (HE-SIG-B-MCSs).....	528
27.3.9	Timing-related parameters	528
27.3.10	Mathematical description of signals	533
27.3.11	HE preamble	539

27.3.11.1	Introduction.....	539
27.3.11.2	Cyclic shift.....	539
27.3.11.3	L-STF field	540
27.3.11.4	L-LTF field	541
27.3.11.5	L-SIG field.....	542
27.3.11.6	RL-SIG field	544
27.3.11.7	HE-SIG-A field.....	545
27.3.11.8	HE-SIG-B field	559
27.3.11.9	HE-STF field.....	575
27.3.11.10	HE-LTF field	579
27.3.12	Data field.....	594
27.3.12.1	General.....	594
27.3.12.2	Pre-FEC padding process.....	595
27.3.12.3	SERVICE field	597
27.3.12.4	Scrambler	597
27.3.12.5	Coding.....	598
27.3.12.6	Stream parser	603
27.3.12.7	Segment parser.....	604
27.3.12.8	BCC interleavers.....	604
27.3.12.9	Constellation mapping	605
27.3.12.10	LDPC tone mapper	608
27.3.12.11	Segment deparser.....	610
27.3.12.12	Space-time block coding.....	611
27.3.12.13	Pilot subcarriers	611
27.3.12.14	OFDM modulation.....	616
27.3.12.15	Dual carrier modulation	617
27.3.12.16	Midambles	617
27.3.13	Packet extension	619
27.3.14	Non-HT duplicate transmission	623
27.3.15	Transmit requirements for PPDU sent in response to a triggering frame	624
27.3.15.1	Introduction.....	624
27.3.15.2	Power pre-correction.....	624
27.3.15.3	Pre-correction accuracy requirements	625
27.3.16	SU-MIMO and DL MU-MIMO beamforming.....	627
27.3.16.1	General.....	627
27.3.16.2	Beamforming feedback matrix V	627
27.3.16.3	CQI feedback	628
27.3.17	HE sounding NDP	628
27.3.18	HE TB feedback NDP.....	629
27.3.19	Transmit specification.....	629
27.3.19.1	Transmit spectral mask	629
27.3.19.2	Spectral flatness	634
27.3.19.3	Transmit center frequency and symbol clock frequency tolerance	635
27.3.19.4	Modulation accuracy.....	635
27.3.20	Receiver specification.....	642
27.3.20.1	General.....	642
27.3.20.2	Receiver minimum input sensitivity	642
27.3.20.3	Adjacent channel rejection.....	643
27.3.20.4	Nonadjacent channel rejection.....	644
27.3.20.5	Receiver maximum input level.....	644
27.3.20.6	CCA sensitivity.....	644
27.3.21	HE transmit procedure	647
27.3.22	HE receive procedure.....	652
27.3.23	Channel numbering.....	658

27.3.23.1	General.....	658
27.3.23.2	Channel allocation in the 6 GHz band.....	659
27.3.24	Regulatory requirements.....	659
27.4	HE PLME	659
27.4.1	PLME_SAP sublayer management primitives	659
27.4.2	PHY MIB.....	664
27.4.3	TXTIME and PSDU_LENGTH calculation.....	664
27.4.4	HE PHY	668
27.5	Parameters for HE-MCSs	669
27.5.1	General.....	669
27.5.2	HE-MCSs for 26-tone RU	669
27.5.3	HE-MCSs for 52-tone RU	674
27.5.4	HE-MCSs for 106-tone RU	679
27.5.5	HE-MCSs for 242-tone RU	684
27.5.6	HE-MCSs for 484-tone RU	689
27.5.7	HE-MCSs for 996-tone RU	694
27.5.8	HE-MCSs for 2×996-tone RU	699
27.6	Parameters for HE-SIG-B-MCSs.....	704
Annex B (normative) Protocol Implementation Conformance Statement (PICS) proforma.....		705
B.4	PICS proforma—IEEE Std 802.11-2020.....	705
B.4.3	IUT configuration.....	705
B.4.4	MAC protocol	706
B.4.4.1	MAC protocol capabilities	706
B.4.4.2	MAC frames.....	706
B.4.12	QoS base functionality	707
B.4.33	High-efficiency (HE) features.....	707
B.4.33.1	HE MAC features.....	707
B.4.33.2	HE PHY features.....	709
Annex C (normative) ASN.1 encoding of the MAC and PHY MIB.....		715
C.3	MIB detail	715
Annex D (normative) Regulatory references.....		750
D.1	External regulatory references	750
Annex E (normative) Country elements and operating classes		751
E.1	Country information and operating classes	751
E.2	Band-specific operating requirements	753
E.2.7	6 GHz band in the United States	753
Annex G (normative) Frame exchange sequences.....		755
G.1	General.....	755
G.4	HT, VHT, and SIG sequences.....	755
G.5	HE sequences	755

Annex T (informative) Overlapping BSS (OBSS) management.....	757
T.1 Introduction.....	757
T.6 BSS color and spatial reuse	757
Annex Z (informative) HE-SIG-B content examples	758
Z.1 General.....	758
Z.2 Example 1	758
Z.3 Example 2	760
Z.4 Example 3	761
Z.5 Example 4	762
Annex AA (informative) Multiple BSSID configuration examples	763
AA.1 Introduction.....	763
AA.2 Examples.....	763

Figures

Figure 9-11—Non-CMMG variant HT Control field format	81
Figure 9-16—VHT Control Middle subfield of the VHT variant HT Control field format.....	81
Figure 9-19a—A-Control subfield of the HE variant HT Control field format	82
Figure 9-19b—Control subfield format.....	82
Figure 9-22a—Control Information subfield format in a TRS Control subfield.....	83
Figure 9-22b—Control Information subfield format in an OM Control subfield	84
Figure 9-22c—Control Information subfield format in an HLA Control subfield.....	85
Figure 9-22d—MSI/Partial PPDU Parameters subfield format if the Unsolicited MFB subfield is 1.....	88
Figure 9-22e—Control Information subfield format in a BSR Control subfield	89
Figure 9-22g—Control Information subfield format in a BQR Control subfield.....	91
Figure 9-22h—Control Information subfield format in a CAS Control subfield	91
Figure 9-22f—Control Information subfield format in a UPH Control subfield	91
Figure 9-36—BAR Control field format	97
Figure 9-42—BA Control field format	98
Figure 9-43—BA Information field format (Compressed BlockAck)	99
Figure 9-47b—AID TID Info subfield format.....	101
Figure 9-47c—Per AID TID Info subfield format if the AID11 subfield is not 2045.....	101
Figure 9-47a—BA Information field format (Multi-STA BlockAck).....	101
Figure 9-47d—Per AID TID Info subfield format if the AID11 subfield is 2045	103
Figure 9-58—VHT NDP Announcement frame format	104
Figure 9-59—Sounding Dialog Token field format	104
Figure 9-61b—STA Info field format in an HE NDP Announcement frame if the AID11 subfield is not 2047.....	105
Figure 9-61c—Partial BW Info subfield format.....	105
Figure 9-61a—HE NDP Announcement frame format	105
Figure 9-61d—STA Info subfield format in an HE NDP Announcement frame if the AID11 subfield is 2047.....	107
Figure 9-64a—Trigger frame format.....	108
Figure 9-64b—Common Info field format	108
Figure 9-64c—UL Spatial Reuse subfield format	111
Figure 9-64d—User Info field format	112
Figure 9-64e—SS Allocation subfield format	114
Figure 9-64f—RA-RU Information subfield format	114
Figure 9-64g—Trigger Dependent User Info subfield format in the Basic Trigger frame	115
Figure 9-64h—Trigger Dependent User Info subfield format in the BFRP Trigger frame.....	116
Figure 9-64i—Trigger Dependent User Info subfield format in the MU-BAR Trigger frame	116
Figure 9-64j—UL BW subfield and B7–B1 of RU Allocation subfield in MU-RTS Trigger frame.....	117
Figure 9-64k—Trigger Dependent Common Info subfield format in the GCR MU-BAR Trigger frame..	118
Figure 9-64l—User Info field format in the NFRP Trigger frame	118
Figure 9-100—QoS Info field format when sent by an AP.....	131
Figure 9-142—TWT Information field format	133
Figure 9-144a—HE MIMO Control field format	134
Figure 9-337—BSSID Information field format	153
Figure 9-580—ADDBA Capabilities field format	158
Figure 9-616—Transmit Power Envelope element format.....	160
Figure 9-617—Transmit Power Information field format	160
Figure 9-617a—Maximum Transmit Power field format if the Maximum Transmit Power Interpretation subfield is 0 or 2.....	162
Figure 9-617b—Maximum Transmit Power field format if Maximum Transmit Power Interpretation subfield is 1 or 3.....	162
Figure 9-632—TBTT Information field format.....	165

Figure 9-632a—BSS Parameters subfield format	166
Figure 9-686—TWT element format.....	167
Figure 9-687—Control field format	167
Figure 9-688—Request Type field format in Individual TWT Parameter Set field.....	169
Figure 9-688a—Request Type field format in Broadcast TWT Parameter Set field.....	169
Figure 9-687a—Individual TWT Parameter Set field format	169
Figure 9-687b—Broadcast TWT Parameter Set field format.....	169
Figure 9-689a—Broadcast TWT Info subfield format	174
Figure 9-788a—HE Capabilities element format	175
Figure 9-788b—HE MAC Capabilities Information field format	176
Figure 9-788c—HE PHY Capabilities Information field format	183
Figure 9-788d—Supported HE-MCS And NSS Set field format.....	193
Figure 9-788e—Rx HE-MCS Map subfield, Tx HE-MCS Map subfield, and Basic HE-MCS And NSS Set field format	194
Figure 9-788f—PPE Thresholds field format.....	195
Figure 9-788g—PPE Thresholds Info field format	195
Figure 9-788h—HE Operation element format	197
Figure 9-788i—HE Operation Parameters field format	197
Figure 9-788j—BSS Color Information field format	198
Figure 9-788k—6 GHz Operation Information field format	199
Figure 9-788l—Control field format	199
Figure 9-788m—UORA Parameter Set element format.....	200
Figure 9-788n—OCW Range field format	200
Figure 9-788o—MU EDCA Parameter Set element format.....	201
Figure 9-788p—MU AC Parameter Record field format.....	201
Figure 9-788q—Spatial Reuse Parameter Set element format	201
Figure 9-788r—SR Control field format	202
Figure 9-788s—NDP Feedback Report Parameter Set element format	203
Figure 9-788t—BSS Color Change Announcement element format	203
Figure 9-788u—New BSS Color Information field format.....	204
Figure 9-788v—Quiet Time Period element format.....	204
Figure 9-788w—Quiet Time Content subfield format in Quiet Time Period Setup subtype.....	205
Figure 9-788x—Quiet Time Content subfield format in Quiet Time Period Request subtype.....	205
Figure 9-788y—Quiet Time Content subfield format in Quiet Time Period Response subtype	206
Figure 9-788z—ESS Report element format.....	207
Figure 9-788aa—ESS Information field format	207
Figure 9-788ab—OPS element format	208
Figure 9-788ac—TWT Constraint Parameters element format.....	208
Figure 9-788ad—HE BSS Load element format.....	208
Figure 9-788ae—Multiple BSSID Configuration element format	210
Figure 9-788af—Known BSSID element format	210
Figure 9-788ag—BSSID Bitmap field format.....	211
Figure 9-788ah—Short SSID List element format	211
Figure 9-788ai—HE 6 GHz Band Capabilities element format	211
Figure 9-788aj—Capabilities Information field format.....	212
Figure 9-788ak—UL MU Power Capabilities element format	212
Figure 9-965—TWT Flow field format if the Negotiation Type subfield is 0 or 1	218
Figure 9-965a—TWT Flow field format if the Negotiation Type subfield is 2	219
Figure 9-965b—TWT Flow field format if the Negotiation Type subfield is 3.....	219
Figure 9-970a—MU EDCA Control field format	223
Figure 10-1—Non-DMG non-CMMG non-SIG STA MAC architecture	234
Figure 10-14a—Example of HE MU PPDU transmission with immediate UL OFDMA acknowledgment	240

Figure 10-14b—Example of UL MU transmission with immediate DL MU transmission containing individually addressed BlockAck frames acknowledging frames received from respective STAs	241
Figure 10-14c—Example of UL MU transmissions with immediate Multi-STA BlockAck frame acknowledging MPDUs	241
Figure 10-14d—Example of UL MU transmissions with immediate DL non-HT duplicate PPDU containing Multi-STA BlockAck frame	242
Figure 10-37a—Example of a frame exchange with GCR MU-BAR Trigger frames	272
Figure 11-3a—Example of Multiple BSSID element carrying Nontransmitted BSSID Profile subelements	282
Figure 11-3b—Example of nontransmitted BSSID profile fragmented across multiple Multiple BSSID elements	283
Figure 26-1—Example of MU-RTS/CTS/DL MU PPDU/Acknowledgment Response and NAV setting	316
Figure 26-2—Example of MU-RTS/CTS/Trigger/HE TB PPDU/Multi-STA BlockAck and NAV setting	317
Figure 26-3—Example of MU-RTS Trigger frame soliciting CTS frame responses on primary 40 MHz channel	319
Figure 26-4—Example of User Info field ordering and RU location mapping	347
Figure 26-5—Example of MU cascading sequence	358
Figure 26-6—Illustration of UORA procedure	360
Figure 26-7—Example of HE non-TB sounding	378
Figure 26-8—Example of HE TB sounding	379
Figure 26-9—Example of individual TWT operation	387
Figure 26-10—Example of broadcast TWT operation with optional TBTT negotiation	391
Figure 26-11—Illustration of the adjustment rule for OBSS PD and TX_PWR	418
Figure 26-12—Example of OBSS PD SR operation	421
Figure 26-13—PSRR PPDU spatial reuse	423
Figure 26-14—Example of power save operation with UORA and TWT	436
Figure 26-15—Quiet time period operation	462
Figure 27-1—PHY interaction on transmit for various PPDU formats	493
Figure 27-2—PHY interaction on receive for various PPDU formats	494
Figure 27-3—PHY-CONFIG and CCA interaction with various PPDU formats	494
Figure 27-4—Illustration of OFDM and OFDMA concepts	497
Figure 27-5—RU locations in a 20 MHz HE PPDU	502
Figure 27-6—RU locations in a 40 MHz HE PPDU	502
Figure 27-7—RU locations in an 80 MHz HE PPDU	503
Figure 27-8—HE SU PPDU format	510
Figure 27-9—HE MU PPDU format	510
Figure 27-10—HE ER SU PPDU format	511
Figure 27-11—HE TB PPDU format	511
Figure 27-12—Number of 20 MHz channels that need to be modulated for the pre-HE modulated fields for each RU size and location in an HE TB PPDU	512
Figure 27-14—Transmitter block diagram for L-SIG, RL-SIG, and HE-SIG-A fields for an HE SU PPDU and HE ER SU PPDU if Beam Change subfield is 0	514
Figure 27-13—Transmitter block diagram for L-SIG, RL-SIG, and HE-SIG-A fields for an HE SU PPDU and HE ER SU PPDU if Beam Change subfield is 1	514
Figure 27-15—Transmitter block diagram for L-SIG, RL-SIG, and HE-SIG-A fields of an HE TB PPDU	515
Figure 27-16—Transmitter block diagram for HE-SIG-B field	515
Figure 27-17—Transmitter block diagram for UL transmission or DL non-MU-MIMO transmission of a Data field with BCC encoding on a 26-, 52-, 106- or 242-tone RU	516
Figure 27-18—Transmitter block diagram for UL transmission or DL non-MU-MIMO transmission of a Data field with LDPC encoding on a 26-, 52-, 106-, 242-, 484- or 996-tone RU	517

Figure 27-19—Transmitter block diagram for DL MU-MIMO transmission of a Data field with BCC encoding on a 106- or 242-tone RU.....	518
Figure 27-20—Transmitter block diagram for DL MU-MIMO transmission of a Data field with LDPC encoding on a 106-, 242-, 484- or 996-tone RU	519
Figure 27-21—Transmitter block diagram for the Data field of an HE SU PPDU in 160 MHz with LDPC encoding.....	520
Figure 27-22—Transmitter block diagram for the Data field of an HE SU PPDU in 80+80 MHz with LDPC encoding.....	521
Figure 27-23—Timing boundaries for HE PPDU fields if midamble is not present	534
Figure 27-24—CRC calculation	556
Figure 27-25—Data subcarrier constellation of HE-SIG-A symbols.....	558
Figure 27-26—HE-SIG-B content channel format.....	560
Figure 27-27—Example of the mapping of 8-bit RU Allocation subfield and the position of User field to user's assignment for one 20 MHz channel	569
Figure 27-28—HE-SIG-B content channel for a 20 MHz PPDU	573
Figure 27-29—HE-SIG-B content channel for a 40 MHz PPDU	573
Figure 27-30—HE-SIG-B content channels and their duplication in an 80 MHz PPDU	574
Figure 27-31—HE-SIG-B content channels and their duplication in a 160 MHz PPDU	574
Figure 27-32—Generation of HE-LTF symbols per frequency segment in an HE SU PPDU, HE MU PPDU, and HE ER SU PPDU	591
Figure 27-33—Generation of HE-LTF symbols per frequency segment in an HE TB PPDU for user u on RU r.....	592
Figure 27-34—Generation of 1x HE-LTF symbols per frequency segment.....	592
Figure 27-35—Generation of 2x HE-LTF symbols per frequency segment.....	593
Figure 27-36—HE PPDU padding process in the last OFDM symbol (non-STBC) if a = 1	595
Figure 27-37—Constellation bit encoding for 1024-QAM (1st quadrant).....	605
Figure 27-38—Constellation bit encoding for 1024-QAM (2nd quadrant)	606
Figure 27-39—Constellation bit encoding for 1024-QAM (3rd quadrant)	606
Figure 27-40—Constellation bit encoding for 1024-QAM (4th quadrant)	607
Figure 27-41—HE PPDU with midamble	618
Figure 27-42—Midamble at the end of an HE PPDU	618
Figure 27-43—PE field duration of an HE SU PPDU or HE ER SU PPDU without midambles if TXVECTOR parameter NOMINAL_PACKET_PADDING is 8 μ s and TPE = TPE,nominal..	620
Figure 27-44—PE field duration of an HE SU PPDU or HE ER SU PPDU without midambles if TXVECTOR parameter NOMINAL_PACKET_PADDING is 16 μ s and TPE = TPE,nominal	620
Figure 27-45—HE sounding NDP format	628
Figure 27-46—HE TB feedback NDP format	629
Figure 27-47—Example transmit spectral mask for a 20 MHz mask PPDU	630
Figure 27-48—Example transmit spectral mask for a 40 MHz mask PPDU	631
Figure 27-49—Example transmit spectral mask for an 80 MHz mask PPDU	631
Figure 27-50—Example transmit spectral mask for a 160 MHz mask PPDU	632
Figure 27-51—Example transmit spectral mask for an 80+80 MHz mask PPDU	633
Figure 27-52—Example transmit spectral mask for the N \times 20 MHz preamble punctured channel with transmissions on both upper and lower subchannels	633
Figure 27-53—Example transmit spectral mask for an 80 MHz HE PPDU with the highest 20 MHz subchannel punctured	634
Figure 27-54—PHY transmit procedure for an HE SU PPDU	648
Figure 27-55—PHY transmit procedure for an HE ER SU PPDU	648
Figure 27-56—PHY transmit procedure for an HE MU PPDU	649
Figure 27-57—PHY transmit procedure for an HE TB PPDU	649
Figure 27-58—PHY transmit state machine for an HE PPDU without midambles	651
Figure 27-59—PHY receive procedure for an HE SU PPDU	652
Figure 27-60—PHY receive procedure for an HE ER SU PPDU	652

Figure 27-61—PHY receive procedure for an HE MU PPDU.....	653
Figure 27-62—PHY receive procedure for an HE TB PPDU	653
Figure 27-63—PHY receive state machine if midambles are not present.....	654
Figure AA-1—Example of partial list of profiles with a profile periodicity of 4	763
Figure AA-2—Example of partial list of profiles with a profile periodicity of 3	764
Figure AA-3—Example of a BSSID being deactivated	764
Figure AA-4—Example of a BSSID being activated.....	765
Figure AA-5—Example of DTIM period being changed for a particular BSSID.....	765

Tables

Table 8-2—PHY SAP inter-(sub)layer service primitives	71
Table 8-3—PHY SAP service primitive parameters	71
Table 8-5—The channel-list parameter entries.....	73
Table 9-1—Valid type and subtype combinations	76
Table 9-13—Ack policy	78
Table 9-13a—Queue Size subfield encoding by a non-AP HE STA	80
Table 9-13b—HT Control field format	81
Table 9-22a—Control ID subfield values.....	82
Table 9-24a—UL Target Receive Power subfield in TRS Control field	83
Table 9-24b—UL MU Disable and UL MU Data Disable subfields encoding.....	85
Table 9-24c—HLA Control subfields	86
Table 9-24d—ACI Bitmap subfield encoding.....	89
Table 9-24e—Delta TID subfield encoding	89
Table 9-24f—Scaling Factor subfield encoding.....	90
Table 9-25—Maximum data unit sizes (in octets) and durations (in microseconds)	92
Table 9-27—BlockAckReq frame variant encoding	97
Table 9-28—BlockAck frame variant encoding.....	98
Table 9-28a—Fragment Number subfield encoding for the Compressed BlockAck variant.....	99
Table 9-28b—Context of the Per AID TID Info subfield and presence of optional subfields if the AID11 subfield is not 2045.....	101
Table 9-28c—Fragment Number subfield encoding for the Multi-STA BlockAck variant.....	102
Table 9-29a—Feedback Type And Ng subfield and Codebook Size subfield encoding for HE TB sounding.....	106
Table 9-29b—Feedback Type And Ng subfield and Codebook Size subfield encoding for HE non-TB sounding.....	106
Table 9-29c—Trigger Type subfield encoding	109
Table 9-29d—UL BW subfield encoding.....	109
Table 9-29e—GI And HE-LTF Type subfield encoding.....	110
Table 9-29f—MU-MIMO HE-LTF Mode subfield encoding.....	110
Table 9-29g—Pre-FEC Padding Factor and PE Disambiguity subfields	111
Table 9-29h—AID12 subfield encoding	112
Table 9-29i—B7–B1 of the RU Allocation subfield	113
Table 9-29j—UL Target Receive Power subfield in Trigger frame.....	115
Table 9-29k—Feedback Type subfield encoding.....	119
Table 9-32—Beacon frame body.....	120
Table 9-34—Association Request frame body	122
Table 9-35—Association Response frame body	123
Table 9-36—Reassociation Request frame body.....	124
Table 9-37—Reassociation Response frame body	125
Table 9-38—Probe Request frame body	126
Table 9-39—Probe Response frame body	127
Table 9-43—Action frame body and Action No Ack frame body	129
Table 9-45—DMG Beacon frame body	129
Table 9-46—Minimum and full set of optional elements.....	129
Table 9-49—Reason codes	130
Table 9-50—Status codes	130
Table 9-51—Category values	130
Table 9-67—Band ID field	131
Table 9-80—Subfield values of the Operating Mode field	132
Table 9-91a—HE MIMO Control field encoding	134
Table 9-91c—Subcarrier indices scidx(0) and scidx(Ns – 1) for Ng = 4	137

Table 9-91b—HE Compressed Beamforming Report information	137
Table 9-91d—Subcarrier indices $scidx(0)$ and $scidx(N_s - 1)$ for $N_g = 16$	140
Table 9-91e—Subcarrier indices for compressed beamforming feedback matrix	142
Table 9-91f—HE MU Exclusive Beamforming Report information	144
Table 9-91g—HE CQI Report information	145
Table 9-92—Element IDs	146
Table 9-91h—Average SNR of RU index k for space-time stream i subfield	146
Table 9-93—BSS membership selector value encoding	147
Table 9-153—Extended Capabilities element	149
Table 9-158—Direction subfield encoding	151
Table 9-160—TS Info Ack Policy subfield encoding	152
Table 9-161—Setting of Schedule subfield	152
Table 9-159—Access Policy subfield	152
Table 9-173—Optional subelement IDs for Neighbor Report	154
Table 9-193—Event Type field definitions for event requests and reports	157
Table 9-265a—HE Fragmentation Operation subfield	158
Table 9-275a—Maximum Transmit Power Interpretation subfield encoding	160
Table 9-276—Meaning of Local Maximum Transmit Power Count subfield if the Maximum Transmit Power Interpretation subfield is 0 or 2	161
Table 9-277—Definition of Local Maximum Transmit Power Unit Interpretation subfield	161
Table 9-277—Meaning of Maximum Transmit Power Count subfield if Maximum Transmit Power Interpretation subfield is 1 or 3	163
Table 9-281—TBTT Information field contents	164
Table 9-288—PHY Support Criterion subfield	167
Table 9-296a—Interpretation of Negotiation Type subfield and of Target Wake Time, TWT Wake Interval Mantissa, and TWT Wake Interval Exponent subfields	168
Table 9-297—TWT Setup Command field values	170
Table 9-297a—Broadcast TWT Recommendation field for a broadcast TWT element	172
Table 9-322a—Subfields of the HE MAC Capabilities Information field	177
Table 9-322b—Subfields of the HE PHY Capabilities Information field	184
Table 9-322c—Subfields of the Supported HE-MCS And NSS Set field	193
Table 9-322d—Constellation index	196
Table 9-322e—RU allocation index	196
Table 9-322f—Quiet Time Period Subtype field encoding	204
Table 9-322g—Status codes	206
Table 9-322h—Recommended BSS Transition RSSI Threshold Within ESS subfield encoding	207
Table 9-374—TDLS Discovery Response frame Action field format	213
Table 9-383—FILS Discovery frame format	213
Table 9-384—BSS Operating Channel Width	214
Table 9-386—PHY Index subfield	214
Table 9-387—FILS Minimum Rate	214
Table 9-414—Information for TDLS Setup Request Action field	215
Table 9-415—Information for TDLS Setup Response Action field	216
Table 9-416—Information for TDLS Setup Confirm Action field	216
Table 9-436—Mesh Peering Open frame Action field format	217
Table 9-437—Mesh Peering Confirm frame Action field format	217
Table 9-501—TWT Setup frame Action field format	218
Table 9-526a—HE Action field values	220
Table 9-526b—HE Compressed Beamforming/CQI frame Action field format	220
Table 9-526c—Quiet Time Period frame body	221
Table 9-526d—OPS frame Action field format	221
Table 9-526f—HE BSS Color Change Announcement frame Action field format	222
Table 9-526g—MU EDCA Reset frame Action field format	222

Table 9-526e—Protected HE Action field values	222
Table 9-527—MPDU delimiter fields (non-DMG).....	224
Table 9-529—A-MPDU contexts	225
Table 9-530—A-MPDU contents in the non-HE data enabled immediate response context.....	227
Table 9-531—A-MPDU contents in the data enabled no immediate response context	227
Table 9-533—A-MPDU contents in the control response context.....	227
Table 9-534a—A-MPDU contents in the HE non-ack-enabled single-TID immediate response context..	228
Table 9-534b—A-MPDU contents in the HE ack-enabled single-TID immediate response context	230
Table 9-534c—A-MPDU contents in the HE non-ack-enabled multi-TID immediate response context ...	231
Table 9-534d—A-MPDU contents in the HE ack-enabled multi-TID immediate response context	232
Table 10-9—Modulation classes	246
Table 10-10—Non-HT reference rate.....	247
Table 10-11a—Conditions for including Control subfield variants	250
Table 10-19—Modulation classes eligible for TXOP termination.....	267
Table 10-20—Rate and modulation class of a final transmission in a TXOP	267
Table 10-32a—TWT setup exchange command interpretation.....	278
Table 18-1—TXVECTOR parameters	310
Table 18-3—RXVECTOR parameters	310
Table 26-1—Negotiated buffer size and Block Ack Bitmap subfield length.....	332
Table 26-2—Relation between TID Aggregation Limit field, Multi-TID Aggregation Tx Support field, and solicited immediate response	348
Table 26-3—FEEDBACK_STATUS description	368
Table 26-4—Settings for BW, RU Start Index, and RU End Index fields in HE NDP Announcement frame	382
Table 26-5—TWT setup exchange for unsolicited TWT and recommended broadcast TWT switch	388
Table 26-6—Broadcast TWT announcements	393
Table 26-7—Broadcast TWT membership exchanges	397
Table 26-8—Wake TBTT negotiation exchanges	406
Table 26-9—Setting of VHT Channel Width and VHT NSS at an HE STA transmitting the OM Control subfield	409
Table 26-10—PPDU_BW determination	417
Table 26-11—Non-SRG OBSS PD Min and Non-SRG OBSS PD Max values for non-AP STAs.....	419
Table 26-12—SRG OBSS PD Min and SRG OBSS PD Max values for non-AP STAs	419
Table 26-13—PPE thresholds per PPET8 and PPET16	433
Table 26-14—Example of rate selection for HE PPDU	444
Table 26-15—6 GHz BSS channel width.....	453
Table 27-1—TXVECTOR and RXVECTOR parameters.....	471
Table 27-2—TRIGVECTOR parameters	488
Table 27-3—Interpretation of FORMAT, NON_HT_MODULATION, CH_BANDWIDTH, and CH_OFFSET parameters.....	490
Table 27-4—Interpretation of CH_BANDWIDTH and INACTIVE_SUBCHANNELS parameters when FORMAT is equal to NON_HT and NON_HT_MODULATION is equal to NON_HT_DUP_OFDM.....	492
Table 27-5—Mapping of the HE PHY parameters for non-HT operation	495
Table 27-7—Data and pilot subcarrier indices for RUs in a 20 MHz HE PPDU and in a non-OFDMA 20 MHz HE PPDU.....	499
Table 27-6—Maximum number of RUs for each channel width	499
Table 27-8—Data and pilot subcarrier indices for RUs in a 40 MHz HE PPDU and in a non-OFDMA 40 MHz HE PPDU.....	500
Table 27-9—Data and pilot subcarrier indices for RUs in an 80 MHz HE PPDU and in a non-OFDMA 80 MHz HE PPDU.....	500
Table 27-10—Null subcarrier indices.....	504
Table 27-11—HE PPDU fields.....	511

Table 27-12—Timing-related constants	529
Table 27-13—Subcarrier allocation related constants for the HE-modulated fields in a non-OFDMA HE PPDU	530
Table 27-14—Subcarrier allocation related constants for RUs in an OFDMA HE PPDU	531
Table 27-15—Frequently used parameters	531
Table 27-16—Number of modulated subcarriers and guard interval duration values for HE PPDU fields.....	537
Table 27-17—CH_BANDWIDTH and for pre-HE modulated fields.....	538
Table 27-18—HE-SIG-A field of an HE SU PPDU and HE ER SU PPDU	545
Table 27-19—Interpretation of DCM, STBC, and GI+HE-LTF Size subfields	547
Table 27-20—HE-SIG-A field of an HE MU PPDU	548
Table 27-21—HE-SIG-A field of an HE TB PPDU.....	552
Table 27-22—Spatial Reuse field encoding for an HE SU PPDU, HE ER SU PPDU, and HE MU PPDU	555
Table 27-23—Spatial Reuse field encoding for an HE TB PPDU	555
Table 27-24—Common field.....	561
Table 27-25—RUs associated with each RU Allocation subfield for each HE-SIG-B content channel and PPDU bandwidth.....	562
Table 27-26—RU Allocation subfield.....	564
Table 27-27—User Block field.....	567
Table 27-28—User field format for non-MU-MIMO allocation.....	569
Table 27-29—User field format for MU-MIMO allocation	570
Table 27-30—Spatial Configuration subfield encoding.....	571
Table 27-31—HE-LTF type and GI duration combinations for various HE PPDU formats	580
Table 27-32—HE-LTF subcarrier mapping for the HE TB feedback NDP	590
Table 27-33—NSD,short values.....	596
Table 27-34—SERVICE field	597
Table 27-35—BCC interleaver parameters	605
Table 27-36—LDPC tone mapping distance for each RU size	608
Table 27-37—Pilot indices for a 26-tone RU	611
Table 27-38—The 2 pilot values for a 26-tone RU	612
Table 27-39—Pilot indices for 52-tone RU transmission	612
Table 27-40—The 4 pilot values in a 52- and 106-tone RU	612
Table 27-41—Pilot indices for 106-tone RU transmission	613
Table 27-42—Pilot indices for 242-tone RU transmission	613
Table 27-43—The 8 pilot values in a 242-tone RU.....	614
Table 27-44—Pilot indices for 484-tone RU transmission	614
Table 27-45—Pilot indices for 996-tone RU transmission	614
Table 27-46—Nominal TPE values.....	619
Table 27-47—Transmit power and RSSI measurement accuracy	626
Table 27-48—Maximum transmit spectral flatness deviations	635
Table 27-49—Allowed relative constellation error versus constellation size and coding rate.....	636
Table 27-50—iRU _{26,start} for RUs other than a 26-tone RU	640
Table 27-51—Receiver minimum input level sensitivity.....	642
Table 27-52—Minimum required adjacent and nonadjacent channel rejection levels.....	643
Table 27-53—HE PHY MIB attributes	659
Table 27-54—HE PHY characteristics.....	668
Table 27-55—HE-MCSs for 26-tone RU, NSS = 1	669
Table 27-56—HE-MCSs for 26-tone RU, NSS = 2	670
Table 27-57—HE-MCSs for 26-tone RU, NSS = 3	671
Table 27-58—HE-MCSs for 26-tone RU, NSS = 4	671
Table 27-59—HE-MCSs for 26-tone RU, NSS = 5	672
Table 27-60—HE-MCSs for 26-tone RU, NSS = 6	672

Table 27-61—HE-MCSs for 26-tone RU, NSS = 7	673
Table 27-62—HE-MCSs for 26-tone RU, NSS = 8	673
Table 27-63—HE-MCSs for 52-tone RU, NSS = 1	674
Table 27-64—HE-MCSs for 52-tone RU, NSS = 2	675
Table 27-65—HE-MCSs for 52-tone RU, NSS = 3	676
Table 27-66—HE-MCSs for 52-tone RU, NSS = 4	676
Table 27-67—HE-MCSs for 52-tone RU, NSS = 5	677
Table 27-68—HE-MCSs for 52-tone RU, NSS = 6	677
Table 27-69—HE-MCSs for 52-tone RU, NSS = 7	678
Table 27-70—HE-MCSs for 52-tone RU, NSS = 8	678
Table 27-71—HE-MCSs for 106-tone RU, NSS = 1	679
Table 27-72—HE-MCSs for 106-tone RU, NSS = 2	680
Table 27-73—HE-MCSs for 106-tone RU, NSS = 3	681
Table 27-74—HE-MCSs for 106-tone RU, NSS = 4	681
Table 27-75—HE-MCSs for 106-tone RU, NSS = 5	682
Table 27-76—HE-MCSs for 106-tone RU, NSS = 6	682
Table 27-77—HE-MCSs for 106-tone RU, NSS = 7	683
Table 27-78—HE-MCSs for 106-tone RU, NSS = 8	683
Table 27-79—HE-MCSs for 242-tone RU, NSS = 1	684
Table 27-80—HE-MCSs for 242-tone RU, NSS = 2	685
Table 27-82—HE-MCSs for 242-tone RU, NSS = 4	686
Table 27-81—HE-MCSs for 242-tone RU, NSS = 3	686
Table 27-83—HE-MCSs for 242-tone RU, NSS = 5	687
Table 27-84—HE-MCSs for 242-tone RU, NSS = 6	687
Table 27-85—HE-MCSs for 242-tone RU, NSS = 7	688
Table 27-86—HE-MCSs for 242-tone RU, NSS = 8	688
Table 27-87—HE-MCSs for 484-tone RU, NSS = 1	689
Table 27-88—HE-MCSs for 484-tone RU, NSS = 2	690
Table 27-89—HE-MCSs for 484-tone RU, NSS = 3	691
Table 27-90—HE-MCSs for 484-tone RU, NSS = 4	691
Table 27-91—HE-MCSs for 484-tone RU, NSS = 5	692
Table 27-92—HE-MCSs for 484-tone RU, NSS = 6	692
Table 27-93—HE-MCSs for 484-tone RU, NSS = 7	693
Table 27-94—HE-MCSs for 484-tone RU, NSS = 8	693
Table 27-95—HE-MCSs for 996-tone RU, NSS = 1	694
Table 27-96—HE-MCSs for 996-tone RU, NSS = 2	695
Table 27-97—HE-MCSs for 996-tone RU, NSS = 3	696
Table 27-98—HE-MCSs for 996-tone RU, NSS = 4	696
Table 27-99—HE-MCSs for 996-tone RU, NSS = 5	697
Table 27-100—HE-MCSs for 996-tone RU, NSS = 6	697
Table 27-101—HE-MCSs for 996-tone RU, NSS = 7	698
Table 27-102—HE-MCSs for 996-tone RU, NSS = 8	698
Table 27-103—HE-MCSs for 2×996-tone RU, NSS = 1	699
Table 27-104—HE-MCSs for 2×996-tone RU, NSS = 2	700
Table 27-105—HE-MCSs for 2×996-tone RU, NSS = 3	701
Table 27-106—HE-MCSs for 2×996-tone RU, NSS = 4	701
Table 27-107—HE-MCSs for 2×996-tone RU, NSS = 5	702
Table 27-108—HE-MCSs for 2×996-tone RU, NSS = 6	702
Table 27-109—HE-MCSs for 2×996-tone RU, NSS = 7	703
Table 27-110—HE-MCSs for 2×996-tone RU, NSS = 8	703
Table 27-111—HE-SIG-B-MCSs.....	704
Table G-1—Attributes applicable to frame exchange sequence definition	755
Table Z-1—Resource allocation signaling example 1	758

Table Z-2—HE-SIG-B field content for example 1	759
Table Z-3—Resource allocation signaling example 2.....	760
Table Z-4—HE-SIG-B field content for example 2	760
Table Z-5—Resource allocation signaling example 3.....	761
Table Z-6—HE-SIG-B field content for example 3	761
Table Z-7—RU Allocation subfields for different dynamic splits of User fields for the example of two MU-MIMO users in the lowest 484-tone RU of an 80 MHz or wider PPDU	762

**IEEE Standard for Information Technology—
Telecommunications and Information Exchange between Systems
Local and Metropolitan Area Networks—
Specific Requirements**

**Part 11: Wireless LAN Medium Access Control
(MAC) and Physical Layer (PHY) Specifications**

**Amendment 1:
Enhancements for High-Efficiency WLAN**

NOTE—The editing instructions contained in this amendment define how to merge the material contained therein into the existing base standard and its amendments to form the comprehensive standard.

The editing instructions are shown in *bold italic*. Four editing instructions are used: change, delete, insert, and replace. *Change* is used to make corrections in existing text or tables. The editing instruction specifies the location of the change and describes what is being changed by using ~~striketrough~~ (to remove old material) and underscore (to add new material). *Delete* removes existing material. *Insert* adds new material without disturbing the existing material. Insertions may require renumbering. If so, renumbering instructions are given in the editing instruction. *Replace* is used to make changes in tables, figures, or equations by removing the existing figure or equation and replacing it with a new one. Editorial instructions, change markings and this NOTE will not be carried over into future editions because the changes will be incorporated into the base standard.

1. Overview

1.4 Word usage

Change the second paragraph in 1.4 as follows:

The construction “between x and y ”, “ x to y ” or “ x - y ” represents an inclusive range (i.e., the range includes both values x and y). The construction “B x -B y ” represents bits x to y ; it is not the subtraction of bit y from bit x .