

Under revision DR 92049

Superseded by AS 3015-1993

AS 3015 (Int)—1991  
(Expires 4 March 1993)

Interim Australian Standard®

---

**Electrical installations—Extra low  
voltage (d.c.) power supplies in  
public telecommunications  
networks**

---



STANDARDS AUSTRALIA



This Interim Australian Standard was prepared by Committee EL/1, Wiring Rules. It was approved on behalf of the Council of Standards Australia on 25 January 1991 and published on 4 March 1991.

---

The following interests are represented on Committee EL/1:

Association of Consulting Engineers Australia  
Australian Consumers Association  
Australian Electrical and Electronic Manufacturers Association  
Confederation of Australian Industry  
Department of Administrative Services  
Electrical Contractors Associations of Australia  
Electrical Regulatory Authorities  
Electrical Trades Union of Australia  
Electricity Supply Association of Australia  
Institute of Electrical Inspectors  
Institution of Engineers Australia  
Insurance Council of Australia  
Telecom Australia

Additional interests participating in preparation of Standard:

Telecom Network Engineering, Structures and Telepower Branch

---

*Review of Australian Standards. To keep abreast of progress in industry, Australian Standards are subject to periodic review and are kept up-to-date by the issue of amendments or new editions as necessary. It is important therefore that Standards users ensure that they are in possession of the latest edition, and any amendments thereto.*

*All details of all Australian Standards and related publications will be found in the Standards Australia Catalogue of Publications; this information is supplemented each month by the magazine 'The Australian Standard', which subscribing members receive, and which gives details of new publications, new editions and amendments, and of withdrawn Standards.*

*Suggestions for improvements to Australian Standards, addressed to the head office of Standards Australia, are welcomed. Notification of any inaccuracy or ambiguity found in an Australian Standard should be made without delay in order that the matter may be investigated and appropriate action taken.*

---

Interim Australian Standard<sup>®</sup>

---

**Electrical installations—Extra low  
voltage (d.c.) power supplies in  
public telecommunications  
networks**

---

First published as AS 3015 (Int)—1991.

**PREFACE**

This Interim Standard was prepared by the Standards Australia Committee on Wiring Rules following a request from Telecom Australia.

The purpose of the Interim Standard is to establish safety requirements for the installation of extra-low voltage equipment and circuits in public telecommunications networks.

Standards Australia invites comment on this Interim Standard from persons and organizations concerned with this subject. The date of expiry for comment is 2 years after publication at which time this Interim Australian Standard will either be withdrawn or revised in the light of public comment, with the view to the preparation of an Australian Standard.

During the life of this document the Committee will monitor all comment as it is received.

Attention is drawn to the fact that this document is an Interim Australian Standard only and should be regarded as a Draft Standard and hence liable to alteration after the expiry date.

This document is not to be regarded as an Australian Standard until issued as such by Standards Australia.

**CONTENTS**

	<i>Page</i>
FOREWORD .....	3
SECTION 1 SCOPE AND GENERAL	
1.1 SCOPE .....	4
1.2 APPLICATION .....	4
1.3 REFERENCED DOCUMENTS .....	4
1.4 DEFINITIONS .....	4
SECTION 2 BATTERIES	
2.1 GENERAL .....	6
2.2 INTERMEDIATE VOLTAGES .....	6
2.3 BATTERY MOUNTING .....	6
2.4 VENTILATION .....	6
2.5 BATTERY ACCOMMODATION .....	6
2.6 ARRANGEMENT OF CELLS .....	7
2.7 BARRIERS AND SHROUDDING .....	7
SECTION 3 D.C. DISTRIBUTION AND PROTECTION	
3.1 GENERAL CIRCUIT ARRANGEMENT .....	8
3.2 DESIGN REQUIREMENTS .....	8
3.3 RATING OF CONDUCTORS .....	8
3.4 INSULATION RESISTANCE .....	8
3.5 OVERCURRENT PROTECTION .....	8
3.6 SWITCHGEAR AND CONTROLGEAR .....	8
3.7 TELECOMMUNICATIONS SERVICE EARTH CONDUCTOR .....	8
APPENDIX A SAMPLE VENTILATION RATE CALCULATION .....	10

© Copyright — STANDARDS AUSTRALIA

Users of Standards are reminded that copyright subsists in all Standards Australia publications and software. Except where the Copyright Act allows and except where provided for below no publications or software produced by Standards Australia may be reproduced, stored in a retrieval system in any form or transmitted by any means without prior permission in writing from Standards Australia. Permission may be conditional on an appropriate royalty payment. Requests for permission and information on commercial software royalties should be directed to the head office of Standards Australia.

Standards Australia will permit up to 10 percent of the technical content pages of a Standard to be copied for use exclusively in-house by purchasers of the Standard without payment of a royalty or advice to Standards Australia.

Standards Australia will also permit the inclusion of its copyright material in computer software programs for no royalty payment provided such programs are used exclusively in-house by the creators of the programs.

Care should be taken to ensure that material used is from the current edition of the Standard and that it is updated whenever the Standard is amended or revised. The number and date of the Standard should therefore be clearly identified.

The use of material in print form or in computer software programs to be used commercially, with or without payment, or in commercial contracts is subject to the payment of a royalty. This policy may be varied by Standards Australia at any time.

## FOREWORD

Most telecommunications equipment is powered from either a nominal 24 V or 48 V d.c. power supply. Consequently these supplies and their power distribution systems fall into the category of ELV as defined in AS 3000.

The power supplies form an integral part of a telecommunications facility and their proper function is vital to the continuation of such a facility. The ELV (d.c.) portion of the power supply is shown in Figure 1. The practices which are included in this Standard have been developed over many years of safe operation of the telecommunications network.

If this Standard conflicts with the ELV Section of AS 3000 or with any other Standard, then the provisions of this Standard apply to the ELV (d.c.) installations of telecommunications carriers.

## STANDARDS AUSTRALIA

## Interim Australian Standard

Electrical installations—Extra-low voltage (d.c.) power supplies  
in public telecommunications networks

## SECTION 1 SCOPE AND GENERAL

**1.1 SCOPE** This Standard sets out requirements for the design and installation of telecommunications ELV (d.c.) power supplies which are used by telecommunications carriers in the provision of public telecommunications networks.

**1.2 APPLICATION** This Standard applies to the installation of ELV (d.c.) power supplies in public telecommunications networks, e.g. telephone exchanges and mains or solar powered microwave repeaters and optical fibre regenerators, which are in restricted premises. Where there is conflict between this Standard and the telecommunications carrier's internal documents, this Standard shall apply.

The requirements of this Standard do not apply to power supplies installed in customer owned premises or other premises not owned or operated by the telecommunications carrier.

The appropriate requirements of AS 3000 and related Standards shall apply to power supplies which are not installed in restricted premises.

**1.3 REFERENCED DOCUMENTS** The following documents are referred to in this Standard:

AS

- 1939 Degrees of protection provided by enclosures for electrical equipment (IP Code)
- 1981 Stationary batteries of lead-acid pasted plate type
- 2430 Classification of hazardous areas
- 2430.1 Part 1: Explosive gas atmospheres
- 2676 Guide to the installation, maintenance, testing and replacement of secondary batteries in buildings
- 2676.1 Part 1: Vented cells
- 2676.2 Part 2: Sealed (valve-regulated) cells
- 2692 Busbar trunking systems (busways)
- 3000 SAA Wiring Rules
- 3008 Electrical installations—Selection of cables
- 3008.1 Part 1: Cables for alternating voltages up to and including 0.6/1 kV
- 3011 Electrical installations—Secondary batteries installed in buildings
- 3011.1 Part 1: Vented cells
- 3011.2 Part 2: Sealed (valve-regulated) cells

**1.4 DEFINITIONS** For the purpose of this Standard, the definitions below apply.

**1.4.1 Authorized personnel**—person or persons in charge of the restricted premises, or any other person duly authorized by the telecommunications carrier.

**1.4.2 Battery**—an electrochemical system capable of storing, in chemical form, the electrical energy received and which can reconvert it to electrical energy.

**1.4.3 Battery circuits**—the cable or busbar conductors connecting the battery to the point of common connection.

**1.4.4 Battery enclosure**—a cabinet or enclosed rack suitable for mounting of battery cells.

**1.4.5 Battery room**—a room containing batteries which normally have no other protective enclosure.

**1.4.6 Boost charge (boost)**—a partial charge at higher voltage for a short period. Typically, for lead-acid cells, the voltage is taken above 2.35 V per cell at 20°C.

**1.4.7 Cell**—an assembly of electrodes and electrolyte which constitutes the basic unit of a battery.

**1.4.8 Charge (of a cell, string or battery)**—an operation during which a cell, string or battery receives, from an external circuit, electrical energy which is converted into chemical energy.

**1.4.9 Equalizing charge**—an extended charge to ensure complete charging of all the cells in a string or battery. During equalizing, the applied voltage is above the float voltage but below the boost charge voltage.

**1.4.10 Float operation**—a method of maintaining a lead-acid secondary battery in a fully charged state by applying a steady voltage above the open circuit voltage of the cell, but below the boost charge voltage.