



Lamp controlgear

**Part 2.7: Particular requirements for
battery supplied electronic controlgear
for emergency lighting (self-contained)
(IEC 61347-2-7:2017 (ED. 3.1) MOD)**

STANDARDS
Australia



This Australian Standard® was prepared by Committee EL-041, Lamps and Related Equipment. It was approved on behalf of the Council of Standards Australia on 28 May 2019. This Standard was published on 18 June 2019.

The following are represented on Committee EL-041:

- Australian Industry Group
 - Consumers' Federation of Australia
 - Department of the Environment and Energy (Australian Government)
 - Electrical Compliance Testing Association of Australia
 - Electrical Regulatory Authorities Council
 - IES: The Lighting Society
 - Joint Accreditation System of Australia and New Zealand
 - Lighting Council Australia
 - Master Electricians Australia
 - NSW Fair Trading
-

This Standard was issued in draft form for comment as **DIS AS 61347.2.7:2019**.

Standards Australia wishes to acknowledge the participation of the expert individuals that contributed to the development of this Standard through their representation on the Committee and through the public comment period.

Keeping Standards up-to-date

Australian Standards® are living documents that reflect progress in science, technology and systems. To remain in their currency, all Standards are periodically reviewed, and new editions are published. Between editions, amendments may be issued.

Standards may also be withdrawn. It is important that readers assure themselves they are using a current Standard, which should include any amendments that may have been published since the Standard was published.

Detailed information about Australian Standards, drafts, amendments and new projects can be found by visiting **www.standards.org.au**

Standards Australia welcomes suggestions for improvements, and encourages readers to notify us immediately of any apparent inaccuracies or ambiguities. Contact us via email at **mail@standards.org.au**, or write to Standards Australia, GPO Box 476, Sydney, NSW 2001.

Australian Standard®

Lamp controlgear

**Part 2.7: Particular requirements for
battery supplied electronic controlgear
for emergency lighting (self-contained)
(IEC 61347-2-7:2017 (ED. 3.1) MOD)**

First published as AS 61347.2.7:2019

COPYRIGHT

© Standards Australia Limited

All rights are reserved. No part of this work may be reproduced or copied in any form or by any means, electronic or mechanical, including photocopying, without the written permission of the publisher, unless otherwise permitted under the Copyright Act 1968.

ISBN 978 1 76072 487 0

PREFACE

This Standard was prepared by the Australian members of Joint Standards Australia/Standards New Zealand Committee EL-041, Lamps and Related Equipment.

The objective of this Standard is to specify minimum safety requirements for battery supplied electronic controlgear for emergency lighting (self-contained), designed to be used with or incorporating electrical light sources on supply voltages not exceeding 250 V.

This Standard is an adoption with national modifications and has been reproduced from IEC 61347-2-7:2017 (ED. 3.1), *Lamp controlgear — Part 2-7: Particular requirements for battery supplied electronic controlgear for emergency lighting (self-contained)* and its Amendment 1 (2017). The modifications are additional requirements and are set out in Appendix ZZ, which has been added at the end of the source text.

Appendix ZZ lists the variations to IEC 61347-2-7 (ED. 3.1) for the application of this Standard in Australia.

This Standard is to be read in conjunction with AS/NZS 61347.1. This Part 2 supplements or modifies the corresponding clauses in AS/NZS 61347.1.

The essential safety requirements of AS/NZS 3820, *Essential safety requirements for electrical equipment*, which could be applicable to lighting products within the scope of AS 61347.2.7, are covered by AS 61347.2.7.

The IEC edition includes the following significant technical changes with respect to the previous edition:

- (a) Modification of IEC 61347-2-7 to become a standard exclusively for d.c. battery supplied electronic controlgear for emergency lighting (self-contained). IEC 61347-2-3 Annex J is intended to cover centrally supplied emergency controlgear.
- (b) Update of Clause 22 — Recharging devices.
- (c) Modification of Clause 20 battery voltage characterisation to support EBLF measurement.
NOTE: This to simplify and increase reproducibility of testing.
- (d) Rationalisation of requirements between IEC 61347-2-7 and IEC 60598-2-22 requirements of IEC 60598-2-22 being transferred to IEC 61347-2-7.

This Standard is structured as follows:

- (i) Preface.
- (ii) IEC 61347-2-7:2017 (ED. 3.1) unedited from the first clause to Bibliography.
- (iii) Appendix ZZ — Australian variations to the source document.

The variations listed in Appendix ZZ address issues including the following:

- (A) Modification of the requirements to include lithium battery technologies
- (B) Align requirements with AS/NZS 2293.3 and emergency lighting practices used in Australia and New Zealand.

As this Standard is reproduced from an International Standard, the following applies:

- (1) In the source text “this part of IEC 61347” should read “this Australian Standard”.
- (2) A full point substitutes for a comma when referring to a decimal marker.

Australian or Australian/New Zealand Standards that are identical adoptions of international normative references may be used interchangeably. Refer to the online catalogue for information on specific Standards.

The terms “normative” and “informative” are used in Standards to define the application of the annex or appendix to which they apply. A “normative” annex or appendix is an integral part of a Standard, whereas an “informative” annex or appendix is only for information and guidance.

Currently in preview, click buy full version

CONTENTS

FOREWORD.....	4
INTRODUCTION.....	6
INTRODUCTION to Amendment 1	6
1 Scope.....	7
2 Normative references	7
3 Terms and definitions	8
4 General requirements	10
5 General notes on tests	10
6 Classification.....	11
7 Marking.....	11
8 Protection against accidental contact with live parts	13
9 Terminals	13
10 Provisions for protective earthing	13
11 Moisture resistance and insulation.....	13
12 Electric strength	13
13 Thermal endurance test for windings of controlgear.....	13
14 Fault conditions	13
15 Starting conditions.....	13
16 Lamp current.....	14
17 Supply current.....	14
18 Maximum current in any lead (with cathode preheating)	14
19 Lamp operating current waveforms	14
20 Functional safety (EBLF, EOF _X)	15
21 Changeover operation	17
22 Recharging device.....	18
23 Protection against excessive discharge	20
24 Indicator	21
25 Remote control: rest mode, inhibition mode	21
26 Temperature cycling test and endurance test	22
27 Polarity reversal	22
28 Fault conditions	23
29 Construction.....	23
30 Creepage distances and clearances	23
31 Screws, current-carrying parts and connections.....	23
32 Resistance to heat, fire and tracking.....	23
33 Resistance to corrosion	23
34 Abnormal lamp conditions	23
35 Protection of associated components	28
Annex A (normative) Test to establish whether a conductive part is a live part, which may cause an electric shock	30
Annex B (normative) Particular requirements for thermally protected lamp controlgear	30

	<i>Page</i>
Annex C (normative) Particular requirements for electronic lamp controlgear with means of protection against overheating.....	30
Annex D (normative) Requirements for carrying out the heating test of thermally protected lamp controlgear	30
Annex E (normative) Use of constant S other than 4 500 in t_w tests.....	30
Annex F (normative) Draught-proof enclosure.....	30
Annex G (normative) Explanation of the derivation of the values of pulse voltages	31
Annex H (normative) Tests	31
Annex I (normative) Batteries for emergency lighting luminaires	31
Annex J (informative) Rest mode and inhibition mode facilities	31
Annex K (normative) Controlgear incorporating an automatic testing function for emergency lighting operation	32
Annex L (informative) Compatibility between normal mains operation electronic controlgear and battery-powered emergency operation controlgear	35
Bibliography.....	38
Figure 1 – Suitable circuit for the measurement of lamp current and luminous flux.....	16
Figure 2 – Circuit for testing rectifying effect.....	25
Figure 3 – Circuit to test whether a controlgear can withstand a leaking burner	27
Figure 4 – Circuit to test whether a controlgear can withstand rectification.....	28
Figure L.1 – Timing diagram: changeover operation.....	36
Figure L.2 – Supply voltage for the function test	37
Table 1 – Voltage per cell to which the battery is discharged	18
Table 2 – Relation between RMS working voltage and maximum peak voltage	29
Table K.1 – Relevant requirements of IEC 62034.....	32

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents, including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

DISCLAIMER

This Consolidated version is not an official IEC Standard and has been prepared for user convenience. Only the current versions of the standard and its amendment(s) are to be considered the official documents.

This Consolidated version of IEC 61347-2-7 bears the edition number 3.1. It consists of the third edition (2011-12) [documents 34C/995/FDIS and 34C/1002/RVD] and its amendment 1 (2015-11) [documents 34C/1354/FDIS and 34C/1359/RVD]. The technical content is identical to the base edition and its amendment.

This Final version does not show where the technical content is modified by amendment 1. A separate Redline version with all changes highlighted is available in this publication.

International Standard IEC 61347-2-7 has been prepared by subcommittee 34C: Auxiliaries for lamps, of IEC technical committee 34: Lamps and related equipment.

This third edition constitutes a technical revision.

Significant changes introduced into this third edition include:

- modification of IEC 61347-2-7 to become a standard exclusively for d.c. battery supplied electronic controlgear for emergency lighting (self-contained). IEC 61347-2-3 Annex J is intended to cover centrally supplied emergency controlgear;
- update of Clause 22 – Recharging devices;
- modification of Clause 20 battery voltage characterisation to support EBF measurement. This to simplify and increase reproducibility of testing;
- rationalisation of requirements between IEC 61347-2-7 and IEC 60598-2-22 requirements of IEC 60598-2-22 being transferred to IEC 61347-2-7.

This publication has been drafted in accordance with the ISO/IEC Directives Part 2.

This standard shall be used in conjunction with IEC 61347-1. This part supplements or modifies the corresponding clauses in IEC 61347-1.

NOTE In this standard, the following print types are used:

- requirements: in roman type;
- *test specifications: in italic type;*
- notes: in small roman type.

A list of all parts of the IEC 61347 series, published under the general title *Lamp controlgear*, can be found on the IEC website.

The committee has decided that the contents of the base publication and its amendment will remain unchanged until the stability date indicated on the IEC web site under "<http://webstore.iec.ch>" in the date related to the specific publication. At this date, the publication will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

IMPORTANT – The 'colour inside' logo on the cover page of this publication indicates that it contains colours which are considered to be useful for the correct understanding of its contents. Users should therefore print this document using a colour printer.

INTRODUCTION

The formatting into separately published parts provides for ease of future amendments and revisions. Additional requirements will be added as and when a need for them is recognized.

This standard, and the parts which make up IEC 61347-2, in referring to any of the clauses of IEC 61347-1, specify the extent to which such a clause is applicable and the order in which the tests are to be performed; they also include additional requirements, as necessary. All parts which make up IEC 61347-2 are self-contained and, therefore, do not include reference to each other.

Where the requirements of any of the clauses of IEC 61347-1 are referred to in this standard by the phrase "The requirements of Clause n of IEC 61347-1 apply", this phrase is interpreted as meaning that all requirements of the clause in question of Part 1 apply, except any which are clearly inapplicable to the specific type of lamp controlgear covered by this particular part of IEC 61347-2.

INTRODUCTION to Amendment 1

EBLF is the ratio of the light output of a light source in emergency mode to the rated light output under normal conditions. EBLF is controlled by the output characteristics (current, voltage, power) of the controlgear with which the light source is operated.

For conventional lamps like fluorescent lamps, the EBLF is defined by the light output ratio of the lamp operated at 100 % and in emergency mode.

$$\text{EBLF} = \Phi_{\text{emergency}} / \Phi_{100\%}$$

For this measurement no special lamp is required, it is expected that all lamps of the same type show a very similar light output ratio independent of its manufacturer. The measurement is done at an ambient temperature of 25 °C. Due to the same dimensions and the identical cooling system (free air) the thermal conditions are identical for all lamps. The result is fully reproducible without any additional condition.

Special requirements for LED light sources

The light output of LED light sources depends also on the temperature at which they are operated. Typically the temperature is controlled by a heat sink on which it is mounted (e.g. luminaire surface).

This amendment describes a test method to evaluate the EBLF via an output factor (EOF_X) taking into account that the ratio of the forward current of the LED controlgear is directly proportional to the LED light output. Any non-linearity due to the increased efficacy at lower operation temperature leads to an increased tolerance of the light output in the emergency mode but always positive.

Controlgear, which operates the LED light source in normal operation as well as in emergency operation can be marked directly with the output factor. Controlgear, operating the LED module in emergency mode only needs to be marked with the output value, for example the forward current $I_{\text{emergency}}$.

AUSTRALIAN STANDARD

Lamp controlgear

Part 2.7:

Particular requirements for battery supplied electronic controlgear for emergency lighting (self-contained) (IEC 61347-2-7:2017 (ED. 3.1) MOD)**1 Scope**

This part of IEC 61347 specifies particular safety requirements for battery supplied electronic controlgear for maintained and non-maintained emergency lighting purposes.

It includes specific requirements for electronic controlgear and control units for self-contained luminaires for emergency lighting as specified by IEC 60598-2-22.

It is intended for controlgear for fluorescent lamps, but it is also applicable to other lamp types e.g. incandescent, high pressure discharge lamps and LEDs.

This standard covers the emergency mode operation of a controlgear. For controlgear with a combination of normal and emergency lighting operation, the normal lighting operation aspects are covered by the appropriate part 2 of IEC 61347.

DC supplied electronic controlgear for emergency lighting may or may not include batteries.

This standard does not apply to d.c. supplied electronic controlgear for emergency lighting, which are intended for connection to a centralised emergency power supply system. A centralised emergency power system could be a central battery system.

NOTE Annex J of IEC 61347-2-3 applies to a.c., a.c./d.c. or d.c. supplied electronic controlgear for connection to centralised emergency power supply systems that are also intended for emergency lighting operations from a.c./d.c. supplies.

2 Normative references

For the purpose of this part of IEC 61347, the normative references given in Clause 2 of IEC 61347-1, which are mentioned in this standard, apply, together with the following normative references.

IEC 60081, *Double-capped fluorescent lamps – Performance specifications*

IEC 60598-2-22, *Luminaires – Part 2: Particular requirements – Luminaires for emergency lighting*

IEC 60901, *Single-capped fluorescent lamps – Performance specifications*

IEC 60921, *Ballasts for tubular fluorescent lamps – Performance requirements*

IEC 60929, *AC and/or DC-supplied electronic control gear for tubular fluorescent lamps – Performance requirements*

IEC 61347-1, *Lamp controlgear – Part 1: General and safety requirements*

IEC 61347-2-3, *Lamp control gear – Part 2-3: Particular requirements for a.c. and/or d.c. supplied electronic control gear for fluorescent lamps*