



BSI Standards Publication

**Low voltage switchgear and controlgear —
Partial discharge voltages and FO level in
low voltage switchgear and controlgear**

National foreword

This Published Document is the UK implementation of IEC TR 63434:2023.

The UK participation in its preparation was entrusted to Technical Committee PEL/121/1, Low voltage switchgear and controlgear.

A list of organizations represented on this committee can be obtained on request to its committee manager.

Contractual and legal considerations

This publication has been prepared in good faith, however no representation, warranty, assurance or undertaking (express or implied) is or will be made, and no responsibility or liability is or will be accepted by BSI in relation to the adequacy, accuracy, completeness or reasonableness of this publication. All and any such responsibility and liability is expressly disclaimed to the full extent permitted by the law.

This publication is provided as is, and is to be used at the recipient's own risk.

The recipient is advised to consider seeking professional guidance with respect to its use of this publication.

This publication is not intended to constitute a contract. Users are responsible for its correct application.

This publication is not to be regarded as a British Standard.

© The British Standards Institution 2023
Published by BSI Standards Limited 2023

ISBN 978 0 55 7 21292 1

ICS 29.30.20

Compliance with a Published Document cannot confer immunity from legal obligations.

This Published Document was published under the authority of the Standards Policy and Strategy Committee on 31 October 2023.

Amendments/corrigenda issued since publication

Date	Text affected
------	---------------



TECHNICAL REPORT

Low voltage switchgear and controlgear – Partial discharge voltages and PD-level in low voltage switchgear and controlgear

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

ICS 29.130.20

ISBN 978-2-8322-7573-3

Warning! Make sure that you obtained this publication from an authorized distributor.

CONTENTS

FOREWORD.....	4
INTRODUCTION.....	6
1 Scope.....	7
2 Normative references	7
3 Terms and definitions	7
4 Basic information (physics).....	10
4.1 Discharge phenomena	10
4.1.1 General	10
4.1.2 Homogeneous electric fields	11
4.1.3 Inhomogeneous electric fields.....	11
4.2 Dimensioning examples	14
4.2.1 General	14
4.2.2 Influence of design and temperature on a series connection of clearances and solid insulation for AC voltage	17
4.2.3 Series connection of clearances and solid insulation by design for DC voltage	24
4.2.4 Solid insulation – dimensioning – material characteristics	24
5 Application rules	29
5.1 General.....	29
5.2 Partial discharge considerations	30
5.3 Measures to prevent/reduce the probability of partial discharges	30
Annex A (informative) Research on partial discharge in low-voltage switchgear and controlgear	31
A.1 General.....	31
A.2 Investigations on switchgear	31
A.3 Reference to other products relevant for applications.....	35
Annex B (informative) Voltage factors when considering partial discharge effects	36
Bibliography.....	38
Figure 1 – Temperature dependent variation of the breakdown field strength \hat{E}_d of air per Equation (1), $\alpha = 0,2$, $\beta = 20 \text{ }^\circ\text{C}$, $p = p_0 = 1\,013 \text{ mbar}$	11
Figure 2 – Inception voltage $U_{i,RMS}$ depending on the electrode radius r , $R \gg r$	12
Figure 3 – Maximum electrical field strength \hat{E} depending on the electrode edge radius r	13
Figure 4 – Paschen curve $\hat{E}_d = f(p \times d)$ for air	13
Figure 5 – Principle terminal / contact arrangement of a 3-pole device, capacitive voltage divider	15
Figure 6 – Field strength in the air gap, inhomogeneous, $\eta = 0,5$, $\epsilon_{r2} = 4$, cold state	19
Figure 7 – Field strength in the solid insulation, inhomogeneous, $\eta = 0,5$, $\epsilon_{r2} = 4$, cold state	19
Figure 8 – Field strength in the air gap, inhomogeneous, $\eta = 0,5$, $\epsilon_{r2} = 12$ at $130 \text{ }^\circ\text{C}$ operational temperature	20
Figure 9 – Field strength in the solid insulation, inhomogeneous, $\eta = 0,5$, $\epsilon_{r2} = 12$ operational temperature	20
Figure 10 – Gaps and voids in a solid and combined solid / gaseous insulation [7]	21

Figure 11 – Model of a void of thickness t in an insulation wall of defined thickness d [20]	23
Figure 12 – Principle arrangement of electrodes and insulation walls of a 3-pole device	24
Figure 13 – Permissible field strength for dimensioning of solid insulation according to Equation (18).....	25
Figure 14 – Breakdown at high frequency, solid insulation; $d = 0,75$ mm [23]	26
Figure 15 – Breakdown at high frequency, solid insulation, influence of humidity; conditioning at 50 °C; 1: mica-filled phenolic, $d = 0,75$ mm; 2: glass-silicone laminate, $d = 1,5$ mm [24]	27
Figure 16 – Dielectric strength \hat{E}_d of different types of thermoplastic insulation material depending on the temperature	28
Figure 17 – Dielectric strength $E_{d,RMS}$ of PA6-GF30 in dry and moist condition (equilibrium moisture content at 23 °C/50 % RH) depending on the temperature θ (°C).....	29
Figure A.1 – Example of phase resolved partial discharge measurement on a MPSP at room temperature and at elevated operational temperatures.....	31
Figure A.2 – PD Testing (690 V, basic insulation, 20°C).....	32
Figure A.3 – Inception (U_i) and extinction (U_e) voltage during partial discharge measurements on motor protection switching devices (MPSD) at elevated temperatures	33
Table 1 – Relationship between electrode radius r and corona inception voltage $U_{i,RMS}$	12
Table 2 – Ranking of the internal field strength of different gap and void shapes [7]	22
Table A.1 – Inception U_i and extinction U_e voltage depending on the temperature as per Figure A.1 and Figure A.2.....	32
Table A.2 – Maximum discharge values and number of events observed at the test voltage as per Figure A.1 and Figure A.2.....	32
Table A.3 – Ratings and design parameters of the investigated motor protection switching devices (MPSD).....	34
Table A.4 – Partial Discharge (PD) acceptance levels in different IEC documents.....	35
Table B.1 – Coordination of rated RMS voltage with partial discharge voltage and extinction voltage.....	37

INTERNATIONAL ELECTROTECHNICAL COMMISSION

—

**LOW VOLTAGE SWITCHGEAR AND CONTROLGEAR –
PARTIAL DISCHARGE VOLTAGES AND PD-LEVEL IN
LOW VOLTAGE SWITCHGEAR AND CONTROLGEAR**

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use, and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, accept IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) IEC draws attention to the possibility that the implementation of this document may involve the use of (a) patent(s). IEC takes no position concerning the evidence, validity or applicability of any claimed patent rights in respect thereof. As of the date of publication of this document, IEC had not received notice of (a) patent(s), which may be required to implement this document. However, implementers are cautioned that this may not represent the latest information, which may be obtained from the patent database available at <https://patents.iec.ch>. IEC shall not be held responsible for identifying any or all such patent rights.

IEC TR 63434 has been prepared by subcommittee 121A: Low voltage switchgear and controlgear, of IEC technical committee 121: Switchgear and controlgear and their assemblies for low-voltage. It is a Technical Report.

The text of this Technical Report is based on the following documents:

Draft	Report on voting
121A/549/DTR	121A/556A/RVDTR

Full information on the voting for its approval can be found in the report on voting indicated in the above table.

The language used for the development of this Technical Report is English.

This document was drafted in accordance with ISO/IEC Directives, Part 2, and developed in accordance with ISO/IEC Directives, Part 1 and ISO/IEC Directives, IEC Supplement, available at www.iec.ch/members_experts/refdocs. The main document types developed by IEC are described in greater detail at www.iec.ch/publications.

The committee has decided that the contents of this document will remain unchanged until the stability date indicated on the IEC website under webstore.iec.ch in the data related to the specific document. At this date, the document will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

Currently in preview, click buy full version

INTRODUCTION

The application of this document is intended to provide awareness about partial discharge phenomena. Special emphasis is given to the electrical field stress through solid insulation as it relates to the risk of insulation failure.

IEC 60664-1[1]¹ is only providing requirements for partial discharge testing of solid insulation when the peak value of the operational voltage exceeds 700 V and the average field strength is higher than 1 kV/mm. However, in practice, partial discharge testing gives random results below 4 kV/mm, mainly because of the intrinsic fluctuation of PD inception voltage in gaps, the variations of the shape and size of the internal voids in solid materials, and the large influence of the temperature and humidity on the material characteristics. Therefore, this document is providing guidance related to the proper design of the insulation and the selection criteria of the material.

¹ Numbers in square brackets refer to the Bibliography.

LOW VOLTAGE SWITCHGEAR AND CONTROLGEAR –

PARTIAL DISCHARGE VOLTAGES AND PD-LEVEL IN LOW VOLTAGE SWITCHGEAR AND CONTROLGEAR

1 Scope

This document is intended to provide awareness about partial discharge phenomena. This document gives guidance for some conditions when partial discharge can occur in low voltage switchgear and controlgear connected to networks of up to 1 000 V AC. Internal operational voltages can exceed these values. This document gives guidance on the design of conductors and dimensioning of insulation exposed to electrical fields.

This document explains the partial discharge phenomena considering electrical field stress, type of insulation material and other construction parameters, such as the voltage, frequency, temperature, humidity and the distances within the device.

This document does not cover:

- phenomena associated with semiconductor power switching by effects on equipment placed downstream of semiconductor power switching systems;
- partial discharge test procedures (see IEC 60270) [2];
- pure DC systems which are under consideration;
- selection of solid insulation material.

2 Normative references

There are no normative references in this document.

3 Terms and definitions

For the purposes of this document, the following terms and definitions apply.

ISO and IEC maintain terminological databases for use in standardization at the following addresses:

- IEC Electropedia: available at <http://www.electropedia.org/>
- ISO Online browsing platform: available at <http://www.iso.org/obp>

3.1

homogeneous electric field

Electric field which has an essentially constant voltage gradient between electrodes, such as that between two spheres where the radius of each sphere is greater than the distance between them

Note 1 to entry: The homogeneous field condition is referred to as case B in IEC 60664-1[1].

[SOURCE: IEC 60050-442:2014[3], 442-09-02]

3.2

inhomogeneous electric field

electric field which does not have an essentially constant voltage gradient between electrodes