

INTERNATIONAL STANDARD

NORME INTERNATIONALE



Superconductivity –

Part 17: Electronic characteristic measurements of local critical current density and its distribution in large-area superconducting films

Supraconductivité –

Partie 17: Mesurages de caractéristiques électroniques – Densité de courant critique local et sa distribution dans les films supraconducteurs de grande surface



THIS PUBLICATION IS COPYRIGHT PROTECTED

Copyright © 2021 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester. If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

Droits de reproduction réservés. Sauf indication contraire, aucune partie de cette publication ne peut être reproduite ni utilisée sous quelque forme que ce soit et par aucun procédé, électronique ou mécanique, y compris la photocopie et les microfilms, sans l'accord écrit de l'IEC ou du Comité national de l'IEC du pays du demandeur. Si vous avez des questions sur le copyright de l'IEC ou si vous désirez obtenir des droits supplémentaires sur cette publication, utilisez les coordonnées ci-après ou contactez le Comité national de l'IEC de votre pays de résidence.

IEC Central Office
3, rue de Varembe
CH-1211 Geneva 20
Switzerland

Tel.: +41 22 919 02 11
info@iec.ch
www.iec.ch

About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigendum or an amendment might have been published.

IEC publications search - webstore.iec.ch/advsearchform

The advanced search enables to find IEC publications by a variety of criteria (reference number, text, technical committee, ...). It also gives information on projects, replaced and withdrawn publications.

IEC Just Published - webstore.iec.ch/justpublished

Stay up to date on all new IEC publications. Just Published details all new publications released. Available online and once a month by email.

IEC Customer Service Centre - webstore.iec.ch/csc

If you wish to give us your feedback on this publication or need further assistance, please contact the Customer Service Centre: sales@iec.ch.

IEC online collection - oc.iec.ch

Discover our powerful search engine and read freely all the publications previews. With a subscription you will always have access to up to date content tailored to your needs.

Electropedia - www.electropedia.org

The world's leading online dictionary on electrotechnology, containing more than 22 000 terminological entries in English and French, with equivalent terms in 18 additional languages. Also known as the International Electrotechnical Vocabulary (IEV) online.

A propos de l'IEC

La Commission Electrotechnique Internationale (IEC) est la première organisation mondiale qui élabore et publie des Normes internationales pour tout ce qui a trait à l'électricité, à l'électronique et aux technologies apparentées.

A propos des publications IEC

Le contenu technique des publications IEC est constamment revu. Veuillez vous assurer que vous possédez l'édition la plus récente, un corrigendum ou amendement peut avoir été publié.

Recherche de publications IEC -

webstore.iec.ch/advsearchform

La recherche avancée permet de trouver des publications IEC en utilisant différents critères (numéro de référence, texte, comité d'études, ...). Elle donne aussi des informations sur les projets et les publications remplacées ou retirées.

IEC Just Published - webstore.iec.ch/justpublished

Restez informé sur les nouvelles publications IEC. Just Published détaille les nouvelles publications parues. Disponible en ligne et une fois par mois par email.

Service Clients - webstore.iec.ch/csc

Si vous désirez nous donner des commentaires sur cette publication ou si vous avez des questions contactez-nous: sales@iec.ch.

IEC online collection - oc.iec.ch

Découvrez notre puissant moteur de recherche et consultez gratuitement tous les aperçus des publications. Avec un abonnement, vous aurez toujours accès à un contenu à jour adapté à vos besoins.

Electropedia - www.electropedia.org

Le premier dictionnaire d'électrotechnologie en ligne au monde, avec plus de 22 000 articles terminologiques en anglais et en français, ainsi que les termes équivalents dans 16 langues additionnelles. Egalement appelé Vocabulaire Electrotechnique International (IEV) en ligne.

INTERNATIONAL STANDARD

NORME INTERNATIONALE



Superconductivity –

Part 17: Electronic characteristic measurements – Local critical current density and its distribution in large-area superconducting films

Supraconductivité –

Partie 17: Mesurages de caractéristiques électroniques – Densité de courant critique local et sa distribution dans les films supraconducteurs de grande surface

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

COMMISSION
ELECTROTECHNIQUE
INTERNATIONALE

ICS 17.220.20; 29.050

ISBN 978-2-8322-1022-0

Warning! Make sure that you obtained this publication from an authorized distributor.

Attention! Veuillez vous assurer que vous avez obtenu cette publication via un distributeur agréé.

CONTENTS

FOREWORD	4
INTRODUCTION	6
1 Scope	8
2 Normative references	8
3 Terms and definitions	8
4 Requirements	9
5 Apparatus	10
5.1 Measurement equipment	10
5.2 Components for inductive measurements	11
6 Measurement procedure	12
6.1 General	12
6.2 Determination of the experimental coil coefficient	12
6.3 Measurement of J_C in sample films	16
6.4 Measurement of J_C with only one frequency	16
6.5 Examples of the theoretical and experimental coil coefficients	17
7 Uncertainty in the test method	18
7.1 Major sources of systematic effects that affect the U_3 measurement	18
7.2 Effect of deviation from the prescribed value for the coil-to-film distance	19
7.3 Uncertainty in the experimental coil coefficient and the obtained J_C	20
7.4 Effects of the film edge	20
7.5 Specimen protection	20
8 Test report	21
8.1 Identification of test specimen	21
8.2 Report of J_C values	21
8.3 Report of test conditions	21
Annex A (informative) Additional information relating to Clauses 1 to 8	22
A.1 Comments on other methods for measuring the local J_C of large-area HTS films	22
A.2 Requirements	22
A.3 Theory of the third-harmonic voltage generation	23
A.4 Calculation of the induced electric fields	24
A.5 Theoretical coil coefficient k and experimental coil coefficient k'	25
A.6 Scaling of the U_3 – I_0 curves and the constant-inductance criterion to determine I_{th}	25
A.7 Effects of reversible flux motion	27
Annex B (informative) Optional measurement systems	28
B.1 Overview	28
B.2 Harmonic noises arising from the power source and their reduction	29
Annex C (informative) Evaluation of the uncertainty	33
C.1 Evaluation of the uncertainty in the experimental coil coefficient	33
C.2 Uncertainty in the calculation of induced electric fields	34
C.3 Experimental results on the effect of the deviation of the coil-to-film distance	35

C.4	Examples of the Type-A uncertainties of J_C and n -values, originating from the experimental uncertainty in the U_3 measurement	35
C.5	Evaluation of the uncertainty in the obtained J_C	36
C.6	Experimental results that reveal the effect of the film edge	37
	Bibliography	39
Figure 1	– Diagram for an electric circuit used for inductive J_C measurement of HTS films	10
Figure 2	– Illustration showing techniques to press the sample coil to HTS films	11
Figure 3	– Example of a calibration wafer used to determine the coil coefficient	12
Figure 4	– Illustration of the sample coil and the magnetic field during measurement	13
Figure 5	– Illustration of the sample coil and its magnetic field generation	14
Figure 6	– E - J characteristics measured by a transport method and the U_3 inductive method	16
Figure 7	– Illustration of coils 1 and 3 in Table 2	17
Figure 8	– The coil-factor function $F(r) = 2H_0/I_0$ calculated for the three coils	18
Figure 9	– The coil-to-film distance Z_1 dependence of the theoretical coil coefficient k	19
Figure A.1	– Illustration of the sample coil and the magnetic field during measurement	24
Figure A.2	– U_3 and U_3/I_0 plotted against I_0 in a YBCO thin film measured in applied DC magnetic fields, and the scaling observed when normalized by I_{th} (insets)	26
Figure A.3	– Example of the normalized third-harmonic voltages (U_3/fI_0) measured with various frequencies	26
Figure B.1	– Schematic diagram for the variable- RL -cancel circuit	29
Figure B.2	– Diagram for an electrical circuit used for the two-coil method	29
Figure B.3	– Harmonic noises arising from the power source	30
Figure B.4	– Noise reduction using a cancel coil with a superconducting film	30
Figure B.5	– Normalized harmonic noises (U_3/fI_0) arising from the power source	31
Figure B.6	– Normalized noise voltages after the reduction using a cancel coil with a superconducting film	31
Figure B.7	– Normalized noise voltages after the reduction using a cancel coil without a superconducting film	32
Figure B.8	– Normalized noise voltages with the two-coil system shown in Figure B.2	32
Figure C.1	– Effect of the coil position against a superconducting thin film on the measured J_C values	38
Table 1	– Specifications and theoretical coil coefficients k of sample coils	14
Table 2	– Specifications and coil coefficients of typical sample coils	17
Table C.1	– Uncertainty budget table for the experimental coil coefficient k'	34
Table C.2	– Examples of repeated measurements of J_C and n -values	36

INTERNATIONAL ELECTROTECHNICAL COMMISSION

SUPERCONDUCTIVITY –

**Part 17: Electronic characteristic measurements –
Local critical current density and its distribution
in large-area superconducting films**

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as “IEC Publication(s)”). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use, and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, accept IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the informative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

IEC 61788-17 has been prepared by IEC technical committee 90: Superconductivity. It is an International Standard.

This second edition cancels and replaces the first edition published in 2013. This edition constitutes a technical revision.

This edition includes the following a significant technical change with respect to the previous edition:

- a) A simple method to calculate theoretical coil coefficient k is described in 6.2.1.

The text of this International Standard is based on the following documents:

FDIS	Report on voting
90/462/FDIS	90/464/RVD

Full information on the voting for the approval of this International Standard can be found in the report on voting indicated in the above table.

The language used for the development of this International Standard is English.

This document was drafted in accordance with ISO/IEC Directives, Part 2, and developed in accordance with ISO/IEC Directives, Part 1 and ISO/IEC Directives, IEC Supplement, available at www.iec.ch/members_experts/refdocs. The main document types developed by IEC are described in greater detail at www.iec.ch/standardsdev/publications.

A list of all the parts of the IEC 61788 series, published under the general title *Superconductivity*, can be found on the IEC website.

The committee has decided that the contents of this document will remain unchanged until the stability date indicated on the IEC website under "<http://webstore.iec.ch>" in the data related to the specific document. At this date, the document will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

IMPORTANT – The 'colour inside' logo on the cover page of this publication indicates that it contains colours which are considered to be useful for the correct understanding of its contents. Users should therefore print this document using a colour printer.

INTRODUCTION

Over thirty years after their discovery in 1986, high-temperature superconductors are now finding their way into products and technologies that will revolutionize information transmission, transportation, and energy. Among them, high-temperature superconducting (HTS) microwave filters, which exploit the extremely low surface resistance of superconductors, have already been commercialized. They have two major advantages over conventional non-superconducting filters, namely: low insertion loss (low noise characteristics) and high frequency selectivity (sharp cut) [1]¹. These advantages enable a reduced number of base stations, improved speech quality, more efficient use of frequency bandwidths, and reduced unnecessary radio wave noise.

Large-area superconducting thin films have been developed for use in microwave devices [2]. They are also considered for use in emerging superconducting power devices, such as resistive-type superconducting fault-current limiters (SFCLs) [3] [4] [5], superconducting fault detectors used for superconductor-triggered fault current limiters [6] [7] and persistent-current switches used for persistent-current HTS magnets [8] [9]. The critical current density J_c is one of the key parameters that describe the quality of large-area HTS films. Nondestructive, AC inductive methods are widely used to measure J_c and its distribution for large-area HTS films [10] [11] [12] [13], among which the method utilizing third-harmonic voltages $U_3 \cos(\omega t + \theta)$ is the most popular [10] [11], where ω , t and θ denote the angular frequency, time, and initial phase, respectively. However, these conventional methods are not accurate because they have not considered the electric-field E criterion of the J_c measurement [14] [15] and sometimes use an inappropriate criterion to determine the threshold current I_{th} from which J_c is calculated [16]. A conventional method can obtain J_c values that differ from the accurate values by 10 % to 20 % [15]. It is thus important to establish standard test methods to precisely measure the local critical current density and its distribution, to which will be referred in the HTS filter industry can refer for quality control of the HTS films. Background knowledge on the inductive J_c measurements of HTS thin films is summarized in Annex A.

In these inductive methods, AC magnetic fields are generated with AC currents $I_0 \cos \omega t$ in a small coil mounted just above the film, and J_c is calculated from the threshold coil current I_{th} , at which full penetration of the magnetic field to the film is achieved [17]. For the inductive method using third-harmonic voltage U_3 , U_3 is measured as a function of I_0 , and the I_{th} is determined as the coil current I_0 at which U_3 starts to emerge. The induced electric fields E in the superconducting film at $I_c = I_{th}$ which are proportional to the frequency f of the AC current, can be estimated by a simple Bean model [14]. A standard method has been proposed to precisely measure J_c with an electric-field criterion by detecting U_3 and obtaining the n -value (index of the power-law E - J characteristics) by measuring I_{th} precisely at various frequencies [14] [15] [18] [19]. This method not only obtains precise J_c values, but also facilitates the detection of degraded parts in inhomogeneous specimens, because the decline of n -value is more noticeable than the decrease of J_c in such parts [15]. It is noted that this standard method is excellent for assessing homogeneity in large-area HTS films, although the relevant parameter for designing microwave devices is not J_c , but the surface resistance. For application of large-area superconducting thin films to SFCLs, knowledge on J_c distribution is vital, because J_c distribution significantly affects quench distribution in SFCLs during faults.

The International Electrotechnical Commission (IEC) draws attention to the fact that it is claimed that compliance with this document may involve the use of a patent. IEC takes no position concerning the evidence, validity, and scope of this patent right.

¹ Numbers in square brackets refer to the Bibliography.

The holder of this patent right has assured IEC that s/he is willing to negotiate licences under reasonable and non-discriminatory terms and conditions with applicants throughout the world. In this respect, the statement of the holder of this patent right is registered with IEC. Information may be obtained from the patent database available at <http://patents.iec.ch>.

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights other than those in the patent database. IEC shall not be held responsible for identifying any or all such patent rights.

Currently in preview, click buy full version

SUPERCONDUCTIVITY –

Part 17: Electronic characteristic measurements – Local critical current density and its distribution in large-area superconducting films

1 Scope

This part of IEC 61788 specifies the measurements of the local critical current density (J_c) and its distribution in large-area high-temperature superconducting (HTS) films by an inductive method using third-harmonic voltages. The most important consideration for precise measurements is to determine J_c at liquid nitrogen temperatures by an electric-field criterion and obtain current-voltage characteristics from its frequency dependence. Although it is possible to measure J_c in applied DC magnetic fields [20] [21], the scope of this document is limited to the measurement without DC magnetic fields.

This technique intrinsically measures the critical sheet current that is the product of J_c and the film thickness d . The range and measurement resolution for $J_c d$ of HTS films are as follows.

- $J_c d$: from 200 A/m to 32 kA/m (based on results, not limitation).
- Measurement resolution: 100 A/m (based on results, not limitation).

2 Normative references

The following documents are referred to in this text in such a way that some or all of their content constitutes requirements of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60050-815, *International Electrotechnical Vocabulary – Part 815: Superconductivity* (available at <<http://www.electropedia.org>>)

3 Terms and definitions

For the purposes of this document, the terms and definitions given in IEC 60050-815 apply, some of which are repeated here for convenience.

ISO and IEC maintain terminological databases for use in standardization at the following addresses:

- IEC Electropedia: available at <http://www.electropedia.org/>
- ISO Online browsing platform: available at <http://www.iso.org/obp>

3.1 critical current

J_c
maximum direct current that can be regarded as flowing without resistance practically

Note 1 to entry: J_c is a function of magnetic field strength, temperature and strain.

[SOURCE: IEC 60050-815:2015, 815-12-01]