



IEC 61970-301

Edition 2.0 2009-04

INTERNATIONAL STANDARD

**Energy management system application program interface (EMS-API) –
Part 301: Common information model (CIM) base**

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

PRICE CODE **XK**

ICS 33.200

ISBN 2-8318-1036-8

CONTENTS

FOREWORD.....	11
INTRODUCTION.....	13
1 Scope.....	15
2 Normative references.....	15
3 Terms, definitions and abbreviations.....	16
4 CIM specification.....	16
4.1 CIM modeling notation.....	16
4.2 CIM packages.....	16
4.2.1 Core.....	18
4.2.2 Topology.....	18
4.2.3 Wires.....	18
4.2.4 Outage.....	18
4.2.5 Protection.....	18
4.2.6 Meas.....	18
4.2.7 LoadModel.....	18
4.2.8 Generation.....	18
4.2.9 SCADA.....	19
4.2.10 Domain.....	19
4.3 CIM classes and relationships.....	19
4.3.1 Generalization.....	20
4.3.2 Simple association.....	20
4.3.3 Aggregation.....	21
4.4 CIM Model concepts and examples.....	21
4.4.1 Containment, equipment hierarchies and naming.....	21
4.4.2 Connectivity model.....	24
4.4.3 Inheritance hierarchy.....	26
4.4.4 Transformer model.....	28
4.4.5 Measurements and controls.....	29
4.5 Modeling guidelines.....	33
4.5.1 Amendments to the CIM.....	33
4.5.2 CIM profiles.....	34
4.6 Modeling tools.....	34
4.7 Use implementation conventions.....	34
4.7.1 Number of terminals for ConductingEquipment objects.....	34
4.8 CIM modeling examples.....	34
5 Detailed model (normative).....	35
5.1 Overview.....	35
5.2 Context.....	35
6 Package architecture (normative).....	37
6.1 IEC 61970.....	37
6.1.1 IEC 61970CIMVersion.....	37
6.2 Core.....	38
6.2.1 BasePower.....	40
6.2.2 BaseVoltage.....	40
6.2.3 BasicIntervalSchedule.....	40
6.2.4 Bay.....	41

6.2.5	Company	41
6.2.6	ConductingEquipment	42
6.2.7	ControlHouseEquipment	43
6.2.8	CoreVersion	43
6.2.9	Curve	43
6.2.10	CurveData	44
6.2.11	Equipment	44
6.2.12	EquipmentContainer	44
6.2.13	GeographicalRegion	45
6.2.14	IdentifiedObject	45
6.2.15	IrregularIntervalSchedule	46
6.2.16	IrregularTimePoint	46
6.2.17	ModelingAuthority	47
6.2.18	ModelingAuthoritySet	47
6.2.19	PowerSystemResource	47
6.2.20	PSRType	48
6.2.21	RegularIntervalSchedule	48
6.2.22	RegularTimePoint	49
6.2.23	SubControlArea	49
6.2.24	SubGeographicalRegion	50
6.2.25	Substation	50
6.2.26	Terminal	51
6.2.27	Unit	51
6.2.28	VoltageLevel	52
6.3	Domain	52
6.3.1	AbsoluteDateTimePrimitive	57
6.3.2	ActivePowerPrimitive	57
6.3.3	AdmittancePrimitive	57
6.3.4	AngleDegreesPrimitive	57
6.3.5	AngleRadiansPrimitive	57
6.3.6	ApparentPowerPrimitive	57
6.3.7	AreaControlModeEnumeration	58
6.3.8	BoilerControlModeEnumeration	58
6.3.9	BooleanPrimitive	58
6.3.10	BreakerConfigurationEnumeration	58
6.3.11	BusbarConfigurationEnumeration	58
6.3.12	ClassificationPrimitive	58
6.3.13	ClearanceTagTypeEnumeration	59
6.3.14	CompanyTypeEnumeration	59
6.3.15	ComplexPrimitive	59
6.3.16	CompositeSwitchTypePrimitive	59
6.3.17	ConductancePrimitive	59
6.3.18	ControlHouseEquipmentTypeEnumeration	59
6.3.19	ControlModePrimitive	59
6.3.20	CoolantTypeEnumeration	60
6.3.21	CostPerEnergyUnitPrimitive	60
6.3.22	CostPerHeatUnitPrimitive	60
6.3.23	CostPerHourPrimitive	60
6.3.24	CounterPrimitive	60

6.3.25	<i>CurrentFlowPrimitive</i>	60
6.3.26	<i>CurveStyleEnumeration</i>	61
6.3.27	<i>DampingPrimitive</i>	61
6.3.28	<i>DayTypeNameEnumeration</i>	61
6.3.29	<i>DomainVersion</i>	61
6.3.30	<i>EmissionPrimitive</i>	61
6.3.31	<i>EmissionTypeEnumeration</i>	62
6.3.32	<i>EmissionValueSourceEnumeration</i>	62
6.3.33	<i>EnergyAsMWhPrimitive</i>	62
6.3.34	<i>ExcitingCurrentPrimitive</i>	62
6.3.35	<i>ExponentPrimitive</i>	62
6.3.36	<i>FloatPrimitive</i>	62
6.3.37	<i>FractionPrimitive</i>	63
6.3.38	<i>FreqBiasFactorPrimitive</i>	63
6.3.39	<i>FrequencyPrimitive</i>	63
6.3.40	<i>FuelTypeEnumeration</i>	63
6.3.41	<i>GeneratorControlModeEnumeration</i>	63
6.3.42	<i>GeneratorControlSourceEnumeration</i>	63
6.3.43	<i>GeneratorOperatingModeEnumeration</i>	64
6.3.44	<i>HeatPerHourPrimitive</i>	64
6.3.45	<i>HoursPrimitive</i>	64
6.3.46	<i>HydroPlantTypeEnumeration</i>	64
6.3.47	<i>ImpedancePrimitive</i>	64
6.3.48	<i>InductancePrimitive</i>	65
6.3.49	<i>InertiaPrimitive</i>	65
6.3.50	<i>IntegerPrimitive</i>	65
6.3.51	<i>LoadPrimitive</i>	65
6.3.52	<i>LoadLossPrimitive</i>	65
6.3.53	<i>LongDoublePrimitive</i>	65
6.3.54	<i>LongLengthPrimitive</i>	65
6.3.55	<i>LongLongPrimitive</i>	66
6.3.56	<i>MoneyPrimitive</i>	66
6.3.57	<i>NoLoadLossPrimitive</i>	66
6.3.58	<i>NumericUnion</i>	66
6.3.59	<i>NumericTypeEnumeration</i>	67
6.3.60	<i>OctetPrimitive</i>	67
6.3.61	<i>OperatingModePrimitive</i>	67
6.3.62	<i>ParticipationFactorPrimitive</i>	67
6.3.63	<i>PenaltyFactorPrimitive</i>	67
6.3.64	<i>PenstockTypeEnumeration</i>	67
6.3.65	<i>PerCentPrimitive</i>	67
6.3.66	<i>PhaseCodePrimitive</i>	68
6.3.67	<i>PowerFactorPrimitive</i>	68
6.3.68	<i>PowerROCPeMinPrimitive</i>	68
6.3.69	<i>PowerROCPeSecPrimitive</i>	68
6.3.70	<i>PowerVersusFrequencyPrimitive</i>	68
6.3.71	<i>PowerVersusVoltagePrimitive</i>	69
6.3.72	<i>PressurePrimitive</i>	69
6.3.73	<i>PriorityPrimitive</i>	69

6.3.74	<i>PUPrimitive</i>	69
6.3.75	<i>PUkVPerMVArPrimitive</i>	69
6.3.76	<i>QuantityEnumeration</i>	70
6.3.77	<i>RampMethodEnumeration</i>	70
6.3.78	<i>RampStartMethodEnumeration</i>	70
6.3.79	<i>RampUnitsEnumeration</i>	70
6.3.80	<i>RateOfChangePrimitive</i>	70
6.3.81	<i>RatioPrimitive</i>	71
6.3.82	<i>ReactancePrimitive</i>	71
6.3.83	<i>ReactivePowerPrimitive</i>	71
6.3.84	<i>ReferencePrimitive</i>	71
6.3.85	<i>RemoteUnitTypeEnumeration</i>	71
6.3.86	<i>ResistancePrimitive</i>	71
6.3.87	<i>SeasonNameEnumeration</i>	72
6.3.88	<i>SecondsPrimitive</i>	72
6.3.89	<i>ShortPrimitive</i>	72
6.3.90	<i>ShortLengthPrimitive</i>	72
6.3.91	<i>SourceEnumeration</i>	72
6.3.92	<i>SpillwayGateTypeEnumeration</i>	72
6.3.93	<i>StringPrimitive</i>	72
6.3.94	<i>SurgeTankCodeEnumeration</i>	73
6.3.95	<i>SusceptancePrimitive</i>	73
6.3.96	<i>SwitchStateEnumeration</i>	73
6.3.97	<i>SynchronousMachineOperating ModeEnumeration</i>	73
6.3.98	<i>SynchronousMachineTypeEnumeration</i>	73
6.3.99	<i>TapStepPrimitive</i>	73
6.3.100	<i>TemperaturePrimitive</i>	73
6.3.101	<i>TemperatureUnitsEnumeration</i>	74
6.3.102	<i>TerminalCountPrimitive</i>	74
6.3.103	<i>TerminalTypePrimitive</i>	74
6.3.104	<i>TimeStampPrimitive</i>	74
6.3.105	<i>TransformerControlModeEnumeration</i>	74
6.3.106	<i>TransformerCoolingTypeEnumeration</i>	74
6.3.107	<i>TransformerTypeEnumeration</i>	74
6.3.108	<i>TurbineTypeEnumeration</i>	75
6.3.109	<i>ULongPrimitive</i>	75
6.3.110	<i>ULongLongPrimitive</i>	75
6.3.111	<i>ValidityEnumeration</i>	75
6.3.112	<i>WaterLevelPrimitive</i>	76
6.3.113	<i>WindingConnectionEnumeration</i>	76
6.3.114	<i>WindingTypeEnumeration</i>	76
6.3.115	<i>VoltagePrimitive</i>	76
6.3.116	<i>VoltagePerReactivePowerPrimitive</i>	76
6.3.117	<i>VolumePrimitive</i>	76
6.3.118	<i>YAxisTypeEnumeration</i>	77
6.4	<i>LoadModel</i>	77
6.4.1	<i>AreaLoadCurve</i>	78
6.4.2	<i>AreaLossCurve</i>	78
6.4.3	<i>CustomerLoad</i>	79

6.4.4	DayType	80
6.4.5	EquivalentLoad	80
6.4.6	InductionMotorLoad	82
6.4.7	LoadArea	83
6.4.8	LoadDemandModel	83
6.4.9	LoadModelVersion	84
6.4.10	NonConformLoadSchedule	84
6.4.11	PowerCutZone	85
6.4.12	Season	85
6.4.13	StationSupply	86
6.5	Meas	87
6.5.1	Accumulator	90
6.5.2	AccumulatorLimit	91
6.5.3	AccumulatorLimitSet	91
6.5.4	AccumulatorValue	92
6.5.5	Analog	92
6.5.6	AnalogLimit	93
6.5.7	AnalogLimitSet	93
6.5.8	AnalogValue	94
6.5.9	Command	94
6.5.10	Control	95
6.5.11	ControlType	95
6.5.12	Discrete	96
6.5.13	DiscreteValue	96
6.5.14	Limit	97
6.5.15	LimitSet	97
6.5.16	Measurement	97
6.5.17	MeasurementType	99
6.5.18	MeasurementValue	99
6.5.19	MeasurementValueQuality	100
6.5.20	MeasurementValueSource	100
6.5.21	MeasVersion	101
6.5.22	Quality 1850	101
6.5.23	SetPoint	102
6.5.24	StringMeasurement	103
6.5.25	StringMeasurementValue	103
6.5.26	ValueAliasSet	104
6.5.27	ValueToAlias	104
6.6	Outage	105
6.6.1	ClearanceTag	105
6.6.2	OutageSchedule	106
6.6.3	OutageVersion	107
6.6.4	SwitchingOperation	107
6.7	Topology	107
6.7.1	ConnectivityNode	108
6.7.2	TopologicalIsland	109
6.7.3	TopologicalNode	109
6.7.4	TopologyVersion	110
6.8	Wires	110

6.8.1	ACLineSegment.....	118
6.8.2	Breaker	118
6.8.3	BusbarSection	119
6.8.4	CompositeSwitch	120
6.8.5	Conductor.....	121
6.8.6	ConductorType	122
6.8.7	Connector.....	123
6.8.8	DCLineSegment	123
6.8.9	Disconnecter	125
6.8.10	EnergyConsumer	126
6.8.11	EquivalentSource	127
6.8.12	FrequencyConverter	128
6.8.13	Fuse.....	129
6.8.14	Ground	130
6.8.15	GroundDisconnecter	131
6.8.16	HeatExchanger	132
6.8.17	Jumper	132
6.8.18	Junction.....	133
6.8.19	Line	134
6.8.20	LoadBreakSwitch.....	135
6.8.21	MVARCapabilityCurve	136
6.8.22	Plant.....	136
6.8.23	PowerTransformer	137
6.8.24	ProtectedSwitch	138
6.8.25	RectifierInverter	139
6.8.26	RegulatingCondEq.....	140
6.8.27	RegulationSchedule.....	141
6.8.28	SeriesCompensator	141
6.8.29	ShuntCompensator	142
6.8.30	StaticVarCompensator	144
6.8.31	Switch	145
6.8.32	SynchronousMachine	146
6.8.33	TapChanger	148
6.8.34	TransformerWinding	149
6.8.35	WindingTest	151
6.8.36	WireArrangement	152
6.8.37	WiresVersion	152
6.8.38	WireType.....	152
6.8.39	VoltageControlZone.....	153
6.9	Generation	154
6.9.1	GenerationVersion.....	154
6.10	Production.....	154
6.10.1	AccountBalance	157
6.10.2	AirCompressor	158
6.10.3	CAESPlant.....	158
6.10.4	CogenerationPlant.....	159
6.10.5	CombinedCyclePlant	160
6.10.6	EmissionAccount.....	160
6.10.7	EmissionCurve	161

6.10.8	FossilFuel	162
6.10.9	FuelAllocationSchedule	163
6.10.10	GeneratingUnit	164
6.10.11	GenUnitOpCostCurve	166
6.10.12	GenUnitOpSchedule	167
6.10.13	GrossToNetMWCurve	167
6.10.14	HeatInputCurve	168
6.10.15	HeatRateCurve	169
6.10.16	HydroGeneratingEfficiencyCurve	169
6.10.17	HydroGeneratingUnit	170
6.10.18	HydroPowerPlant	171
6.10.19	HydroPump	173
6.10.20	HydroPumpOpSchedule	173
6.10.21	IncrementalHeatRateCurve	174
6.10.22	InflowForecast	175
6.10.23	LevelVsVolumeCurve	175
6.10.24	PenstockLossCurve	176
6.10.25	Reservoir	176
6.10.26	ShutdownCurve	177
6.10.27	StartIgnFuelCurve	178
6.10.28	StartMainFuelCurve	179
6.10.29	StartRampCurve	179
6.10.30	StartupModel	180
6.10.31	SteamSendoutSchedule	181
6.10.32	TailbayLossCurve	181
6.10.33	TargetLevelSchedule	182
6.10.34	ThermalGeneratingUnit	182
6.11	GenerationDynamics	184
6.11.1	BWRSteamSupply	185
6.11.2	CombustionTurbine	186
6.11.3	CTTempMWCurve	187
6.11.4	DrumBoiler	188
6.11.5	FossilSteamSupply	189
6.11.6	HeatRecoveryBoiler	190
6.11.7	HydroTurbine	191
6.11.8	PrimeMover	192
6.11.9	PWRSteamSupply	192
6.11.10	SteamSupply	193
6.11.11	SteamTurbine	194
6.11.12	Subcritical	195
6.11.13	Supercritical	196
6.12	SCADA	197
6.12.1	CommunicationLink	197
6.12.2	RemoteControl	198
6.12.3	RemotePoint	198
6.12.4	RemoteSource	199
6.12.5	RemoteUnit	199
6.12.6	SCADAVersion	200
6.13	Protection	200

6.13.1 CurrentRelay	201
6.13.2 ProtectionEquipment	202
6.13.3 ProtectionVersion	203
6.13.4 RecloseSequence	203
6.13.5 SynchrocheckRelay	204
Annex A (informative) Model of a circuit breaker in the CIM	205
Bibliography	211
Figure 1 – CIM Part 301 package diagram	17
Figure 2 – Example of generalization	20
Figure 3 – Example of simple association	21
Figure 4 – Example of aggregation	21
Figure 5 – Equipment containers	23
Figure 6 – Connectivity model	24
Figure 7 – Simple network example	25
Figure 8 – Simple network connectivity modeled with CIM topology	26
Figure 9 – Equipment inheritance hierarchy	27
Figure 10 – Transformer model	28
Figure 11 – Navigating from PSR to MeasurementValue	30
Figure 12 – Measurement placement	32
Figure 13 – CIM Top level packages	35
Figure 14 – Main	37
Figure 15 – CurveSchedule	38
Figure 16 – Main	39
Figure 17 – Main	53
Figure 18 – Integer Datatypes	53
Figure 19 – Float Datatypes	54
Figure 20 – String Datatypes	55
Figure 21 – Primitive Datatypes	55
Figure 22 – Enumeration Datatypes	56
Figure 23 – Main	77
Figure 24 – Inheritance structure	87
Figure 25 – Measurement	88
Figure 26 – Control	89
Figure 27 – Quality	90
Figure 28 – Main	105
Figure 29 – Main	108
Figure 30 – Main	110
Figure 31 – NamingHierarchyPart2	111
Figure 32 – Transformer model	112
Figure 33 – InheritanceHierarchy	113
Figure 34 – LineModel	114
Figure 35 – RegulatingEquipment	115
Figure 36 – VoltageControl	116

Figure 37 – NamingHierarchyPart1	117
Figure 38 – Main.....	154
Figure 39 – Main.....	155
Figure 40 – Hydro	156
Figure 41 – Thermal	157
Figure 42 – Main.....	184
Figure 43 – Main.....	197
Figure 44 – Main.....	201
Figure A.1 – IEC 61970 CIM model for a circuit breaker.....	206
Figure A.2 – CIM model for location of breaker as electrical device and the physical asset performing the device’s role.....	207
Figure A.3 – Top of asset hierarchy	208
Figure A.4 – Types of document relationships inherited by all assets.....	209
Figure A.5 – Activity Records Associated with a Circuit Breaker	210
Table 1 – MeasurementType naming conventions.....	31
Table 2 – MeasurementValueSource naming conventions.....	31

Currently in preview, click buy full version

INTERNATIONAL ELECTROTECHNICAL COMMISSION

**ENERGY MANAGEMENT SYSTEM APPLICATION
PROGRAM INTERFACE (EMS-API) –****Part 301: Common information model (CIM) base**

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC provides no marking procedure to indicate its approval and cannot be rendered responsible for any equipment declared to be in conformity with an IEC Publication.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.

International Standard IEC 61970-301 has been prepared by IEC technical committee 57: Power systems management and associated information exchange.

This second edition cancels and replaces the first edition published in 2005. This edition constitutes a technical revision ¹⁾.

The second edition contains the following changes from the first edition:

- First edition Annex A which contained the description of the CIM UML model is now a part of the main body of the standard – Clauses 5 and 6.

¹⁾ Note that the third edition with the updates made to the CIM UML model in 2007 will be available shortly after publication of this second edition. For the third edition of this publication the units will be based on the "International System of Units" (SI).

- A new Annex A was added providing a model of a circuit breaker in the CIM as an example of how the CIM can be used to model network devices.
- Significantly reorganized and expanded Subclause 4.4 Examples to explain:
 - Containment, equipment hierarchies, connectivity, and naming
 - Measurements and controls
 - Role of the new IdentifiedObject class, which replaces the old Naming class.
- The naming hierarchy was changed. New classes GeographicalRegion and SubGeographicalRegion replaced HostControlArea and SubControlArea.
- ModelingAuthority and ModelingAuthoritySet classes were added to represent ownership of models. A ModelingAuthority is a role responsible for a model and is used to break down a large model in manageable pieces with clear ownership.
- A new schedules data model was added to replace the use of the curve model for time series data. New base classes IrregularSchedule and RegularSchedule replaced the class CurveSchedule.
- The measurement value attributes were sub-typed into classes Analog, Discrete and Accumulator.
- The class naming was renamed to IdentifiedObject.
- The Line class was changed to be a specialization of the classes Equipment and EquipmentContainer, so that Line is now a container able to contain all necessary objects to model multiple interconnected ACLineSegments as found in the real world.
- Many editorial corrections, including several cardinality and attribute changes to resolve issues submitted on the first edition.

The text of this standard is based on the following documents:

FDIS	Report on voting
57/986/FDIS	57/995/RVD

Full information on the voting for the approval of this standard can be found in the report on voting indicated in the above table.

A list of all parts of the IEC 61970 series, under the general title: *Energy management system application program interface (EMS-API)*, can be found on the IEC website.

The committee has decided that the contents of this publication will remain unchanged until the maintenance result date indicated on the IEC web site under "<http://webstore.iec.ch>" in the data related to the specific publication. At this date, the publication will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

A bilingual version of this publication may be issued at a later date.

INTRODUCTION

This standard is one of the IEC 61970 series which define an application program interface (API) for an energy management system (EMS). This standard was originally based upon the work of the EPRI control center API (CCAPI) research project (RP-3654-1). The principle objectives of the EPRI CCAPI project were to:

- reduce the cost and time needed to add new applications to an EMS,
- protect the investment of existing applications or systems that are working effectively with an EMS.

The principal objective of the IEC 61970 series of standards is to produce standards which facilitate the integration of EMS applications developed independently by different vendors, between entire EMS systems developed independently, or between an EMS system and other systems concerned with different aspects of power system operations, such as generation or distribution management systems (DMS). This is accomplished by defining application program interfaces to enable these applications or systems access to public data and exchange information independent of how such information is represented internally.

The common information model (CIM) specifies the semantics for this API. The component interface specifications (CIS), which are contained in other parts of the IEC 61970 standards, specify the content of the messages exchanged.

The CIM is an abstract model that represents all the major objects in an electric utility enterprise typically needed to model the operational aspects of a utility. This model includes public classes and attributes for these objects, as well as the relationships between them.

The objects represented in the CIM are abstract in nature and may be used in a wide variety of applications. The use of the CIM goes far beyond its application in an EMS. This standard should be understood as a tool to enable integration in any domain where a common power system model is needed to facilitate interoperability and plug compatibility between applications and systems independent of any particular implementation.

IEC 61970-301 defines the CIM base set of packages which provide a logical view of the physical aspects of an energy management system including SCADA (Supervisory Control and Data Acquisition). IEC 61968 series of standards describes additional parts of the CIM that deal with other logical views of utility operations including assets, location, activities, documentation, and work management. However, while there are multiple IEC standards dealing with different parts of the CIM, there is a single, unified normalized information model comprising the CIM behind all these individual standards documents.

International Electrotechnical Commission (IEC) draws attention to the fact that it is claimed that compliance with this document may involve the use of a patent concerning a computer-based implementation of an object-oriented power system model in a relational database. As such, it does not conflict with the development of any logical power system model including the Common Information Model (CIM), where implementation of the model is not defined.

IEC takes no position concerning the evidence, validity and scope of this patent right.

The holder of this patent right has assured IEC that it is willing to negotiate licences under reasonable and non-discriminatory terms and conditions with applicants throughout the world. In this respect, the statement of the holders of these patent rights is registered with IEC. Information may be obtained from:

ICL

Wenlock Way

West Gorton

Manchester

M12 5DR

United Kingdom (U.K.)

Attention is drawn to the possibility that some of the elements of this standard may be the subject of patent rights other than those identified above. IEC shall not be held responsible for identifying any or all such patent rights.

ENERGY MANAGEMENT SYSTEM APPLICATION PROGRAM INTERFACE (EMS-API) –

Part 301: Common information model (CIM) base

1 Scope

The common information model (CIM) is an abstract model that represents all the major objects in an electric utility enterprise typically involved in utility operations. By providing a standard way of representing power system resources as object classes and attributes, along with their relationships, the CIM facilitates the integration of energy management system (EMS) applications developed independently by different vendors, between entire EMS systems developed independently, or between an EMS system and other systems concerned with different aspects of power system operations, such as generation or distribution management. SCADA is modeled to the extent necessary to support power system simulation and inter-control center communication. The CIM facilitates integration by defining a common language (i.e. semantics and syntax) based on the CIM to enable these applications or systems to access public data and exchange information independent of how such information is represented internally.

The object classes represented in the CIM are abstract in nature and may be used in a wide variety of applications. The use of the CIM goes far beyond its application in an EMS. This standard should be understood as a tool to enable integration in any domain where a common power system model is needed to facilitate interoperability and plug compatibility between applications and systems independent of any particular implementation.

Due to the size of the complete CIM, the object classes contained in the CIM are grouped into a number of logical packages, each of which represents a certain part of the overall power system being modeled. Collections of these packages are progressed as separate International Standards. This particular International Standard specifies a base set of packages which provide a logical view of the physical aspects of energy management system (EMS) information within the electric utility enterprise that is shared between all applications. Other standards specify more specific parts of the model that are needed by only certain applications. Subclause 4.2 below provides the current grouping of packages into standards documents.

2 Normative references

The following referenced documents are indispensable for the application of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60870 (all parts), *Telecontrol equipment and systems*

IEC 61850 (all parts), *Communication networks and systems in substations*

IEC 61850-7-3, *Communication networks and systems in substations – Part 7-3: Basic communication structure for substation and feeder equipment – Common data classes*

IEC 61968 (all parts), *Application integration at electric utilities – System interfaces for distribution management*

ISO 8601:2004, *Data elements and interchange formats – Information interchange – Representation of dates and times*

IEEE 754-1985, Standard for Binary Floating-Point Arithmetic