



ANSI/NEMA AB 4-2023

*Guidelines for Inspection and Preventive Maintenance of Molded Case Circuit Breakers
Used in Commercial and Industrial Applications*

Secretariat

National Electrical Manufacturers Association

1300 North 17th Street, Suite 900
Rosslyn, Virginia 22209

www.nema.org

© 2023 by the National Electrical Manufacturers Association. All rights including translation into other languages, reserved under the Universal Copyright Convention, the Berne Convention for the Protection of Literary and Artistic Works, and the International and Pan American Copyright Conventions.

NOTICE AND DISCLAIMER

The information in this publication was considered technically sound by the consensus of persons engaged in the development and approval of the document at the time it was developed. Consensus does not necessarily mean that there is unanimous agreement among every person participating in the development of this document.

The National Electrical Manufacturers Association (NEMA) standards and guideline publications, of which the document contained herein is one, are developed through a voluntary consensus standards development process. This process brings together volunteers and/or seeks out the views of persons who have an interest in the topic covered by this publication. While NEMA administers the process and establishes rules to promote fairness in the development of consensus, it does not write the document and it does not independently test, evaluate, or verify the accuracy or completeness of any information or the soundness of any judgments contained in its standards and guideline publications.

NEMA disclaims liability for any personal injury, property, or other damages of any nature whatsoever, whether special, indirect, consequential, or compensatory, directly or indirectly resulting from the publication, use of, application, or reliance on this document. NEMA disclaims and makes no guaranty or warranty, expressed or implied, as to the accuracy or completeness of any information published herein, and disclaims and makes no warranty that the information in this document will fulfill any of your particular purposes or needs. NEMA does not undertake to guarantee the performance of any individual manufacturer or seller's products or services by virtue of this standard or guide.

In publishing and making this document available, NEMA is not undertaking to render professional or other services for or on behalf of any person or entity, nor is NEMA undertaking to perform any duty owed by any person or entity to someone else. Anyone using this document should rely on his or her own independent judgment or, as appropriate, seek the advice of a competent professional in determining the exercise of reasonable care in any given circumstances. Information and other standards on the topic covered by this publication may be available from other sources, which the user may wish to consult for additional views or information not covered by this publication.

NEMA has no power, nor does it undertake to police or enforce compliance with the contents of this document. NEMA does not certify, test, or inspect products, designs, or installations for safety or health purposes. Any certification or other statement of compliance with any health or safety-related information in this document shall not be attributable to NEMA and is solely the responsibility of the certifier or maker of the statement.

AMERICAN NATIONAL STANDARD

Approval of an American National Standard requires verification by The American National Standards Institute, Inc. (ANSI) that the requirements for due process, consensus, and other criteria for approval have been met by the Standards developer. An American National Standard implies a consensus of those substantially concerned with its scope and provisions. Consensus is established when, in the judgment of the ANSI Board of Standards Review, substantial agreement has been reached by directly, and materially affected interests. Substantial agreement means much more than a simple majority, but not necessarily unanimity. Consensus requires that all views and objections be considered and that a concerted effort be made toward their resolution.

The existence of an American National Standard does not in any respect preclude anyone, whether s/he has approved the Standard or not, from manufacturing, marketing, purchasing, or using products, processes, or procedures not conforming to the Standards. It is intended as a guide to aid the manufacturer, the consumer, and the general public.

The American National Standards Institute, Inc., does not develop Standards and will in no circumstances give an interpretation of any American National Standard. Moreover, no person shall have the right or authority to issue an interpretation of an American National Standard in the name of the American National Standards Institute, Inc. Requests for interpretations should be addressed to the secretariat or sponsor whose name appears on this title page.

CAUTION NOTICE: This American National Standard may be revised or withdrawn at any time. The procedures of the American National Standards Institute, Inc. require that action be taken periodically to reaffirm, revise, or withdraw this Standard. Purchasers of American National Standards may receive current information on all Standards by calling or writing the American National Standards Institute, Inc.

CONTENTS

1	General	1
1.1	Scope.....	1
1.2	Referenced Standards.....	1
2	Safety Procedures	2
2.1	Warning	2
2.2	Safety Procedure.....	3
2.3	Reinstallation Safety Procedure	3
3	Guidelines	3
3.1	The <i>National Electrical Code</i> ®	3
3.2	Molded Case Circuit Breaker.....	3
3.3	Insulated Case Circuit Breaker.....	4
3.4	To Avoid Damaged or Otherwise Inoperable Circuit Breakers Being Inadvertently Returned to Service	4
3.5	Guidance Regarding Inspection and Preventive Maintenance Procedures.....	4
3.6	For Information Regarding Molded Case Circuit Breaker Performance and Application.....	4
3.7	Water-damaged Molded Case Circuit Breakers.....	4
3.8	Heat-damaged Molded Case Circuit Breakers.....	4
4	Inspection Procedures	4
4.1	General.....	4
4.2	Exposed Face Temperature Check.....	5
4.3	Inspection of Enclosure Interior	5
4.4	Electronic Trip Unit Check	9
5	Preventive Maintenance	10
5.1	General	10
5.2	Environmental Evaluation.....	10
5.3	Interchangeable Trip Units	11
5.4	Wire Connectors.....	12
5.5	Reinstallation Procedure	13
6	Test Procedures.....	13
6.1	General.....	13
6.2	Mechanical Operation Tests.....	13
6.3	Insulation Resistance Test	14
6.4	Individual Pole Resistance Test (Millivolt Drop)	16
6.5	Inverse-Time Over Current Trip Test	19
6.6	Instantaneous Over Current Trip Test.....	22
6.7	Rated Hold-In Test	26
7	Accessory Device Test Procedures	27
7.1	General.....	27
7.2	Shunt Trip Release Tests.....	27
7.3	Under-voltage Trip Release Tests.....	29
7.4	Electrical Operator Tests	30

7.5	Auxiliary Switch Tests.....	32
7.6	Alarm Switch Tests.....	33
8	ICCB Inspection and Test Procedures.....	34
8.1	General.....	34
8.2	Primary Connector Check.....	35
8.3	Cradle Check.....	35
8.4	Arc Chute Check.....	36
8.5	Main Contact Check.....	36
8.6	Mechanism Check.....	36
9	Electronic Trip Unit Secondary Injection Test Procedures.....	37
9.1	General.....	37
9.2	Sensor Check.....	37
9.3	Tripping Check.....	37

FIGURES

Figure 1	Improperly Sealed Enclosure.....	6
Figure 2	Front View of Circuit Breaker with Cracked Molded Case.....	6
Figure 3	Side View of Circuit Breaker with Cracked Molded Case.....	7
Figure 4	Faulty Wire Connection.....	7
Figure 5	Arc Gas Exhaust Area.....	8
Figure 6	Line and/or Load Terminals.....	8
Figure 7	Molded Housing (Base and/or Cover).....	9
Figure 8	Improper Wire Connections.....	13
Figure 9	Insulation Resistance Test Setup.....	15
Figure 10	Individual Pole Resistance Test Setup—1.....	16
Figure 11	Individual Pole Resistance Test Setup—2.....	17
Figure 12	Current Wave Shapes.....	25
Figure 13	Sample Shunt Trip Release.....	27
Figure 14	Sample Under-voltage Release.....	29
Figure 15	Sample Electrical Operator/Circuit Breaker Assembly.....	30
Figure 16	Sample Auxiliary Switch.....	32

TABLES

Table 1	Copper Test Conductor Selection.....	21
Table 2	Size of Copper Busbar Connection.....	22
Table 3	Values for Inverse Time Trip Test.....	22
Table 4	Instantaneous Trip Tolerance for Field Testing of Circuit Breakers.....	25

Foreword

This NEMA standards publication supersedes and fully replaces NEMA AB 4-2003. To ensure that a meaningful publication was being developed, draft copies were sent to a number of individuals and organizations in the public sector having an interest in or responsibility for the purchase, testing, application, use, and preventive maintenance of these products. Their resulting comments and suggestions provided a vital user and general interest input prior to final NEMA approval and resulted in a number of substantive changes in this publication. This publication will be periodically reviewed by the Molded Case Circuit Breaker Voting Classification of NEMA for any revisions necessary to keep it up to date with advancing technology. Proposed or recommended revisions should be submitted to:

Senior Technical Director, Operations
National Electrical Manufacturers Association
1300 North 17th Street, Suite 900
Rosslyn, Virginia 22209

This standards publication was developed by the Molded Case Circuit Breaker Voting Classification of NEMA. Approval of this standard does not necessarily imply that all voting classification members voted for its approval or participated in its development. At the time it was approved, the Molded Case Circuit Breaker Voting Classification had the following members:

Eaton Corporation—Pittsburgh, PA
General Electric—Plainville, CT
Siemens Industry, Inc.—Norcross, GA
Schneider Electric USA—Andover, MA
ABB Inc.—Memphis, TN

Introduction

ANSI/NEMA AB 4 includes guidelines for inspection and preventive maintenance of molded case circuit breakers used in commercial and industrial applications. These guidelines are to be used to identify circuit breakers requiring maintenance or replacement. Good practice includes periodic circuit breaker maintenance during plant shutdown or during a regular maintenance period as specified (in NFPA 70B, for example). When a circuit breaker operates automatically, good practice dictates that the source of the overcurrent should be located, and if it is suspected that the operation was at or near the interrupting rating, the circuit breaker's condition should be checked prior to circuit re-energization.

When appropriately maintained, molded case circuit breakers provide reliable protection for many years. It would be impractical for any manufacturer to test their products' life cycles in each and every application. The exact lifetime of the breaker, however, is determined by the circuit breaker's operational duty and by its environment.

With respect to operational duty, for some circuits there will be occasional overload conditions or low-current fault conditions. Here, the operating life will be tens of years. In other circuits, there may be high short-circuit-current faults but it should be noted that bolted faults at the interrupting rating of the breaker are rarely encountered. These will reduce the circuit breaker's operating life and may necessitate circuit breaker replacement. Molded case circuit breakers are evaluated to UL 489 (NEMA AB 1), *Molded-Case Circuit Breakers, Molded-Case Switches and Circuit-Breaker Enclosures*. They are subjected to thousands of endurance test operations (UL 489, Table 7.1.5.1); 50 overload test operations for circuit breakers rated up to 1600A and 25 operations for circuit breakers rated 2000A and higher (UL 489, Table 7.1.3.1); 3 to 7 interrupting tests, depending on breaker type, at limited fault current (UL 489, Table 7.1.7.1, 7.1.7.2, and 7.1.7.3); and two interrupting tests at maximum short-circuit-current rating. Thus, circuit breakers have an extensive but finite interrupting capability, and breakers that experience multiple high short-circuit-current faults should receive a thorough inspection (with replacement, if necessary).

With respect to environmental effects, circuit breakers are sometimes exposed to high ambient temperatures, high humidity, and other conditions that are hostile to long-term performance. For example, industries may have corrosive or dusty environments that could affect operating parts.

It is not intended that molded case circuit breakers be disassembled for inspection. Rather, NEMA AB 4 should be referenced during periodic maintenance or during specific inspection following a high short-circuit-current fault. This document is intended to ensure that molded case circuit breakers are well maintained, and it provides guidelines for circuit breaker replacement.

This document is divided into the following clauses:

Clause 1 presents the scope and reference standards.

Clause 2 details the safety procedures to be followed.

Clause 3 deals with general guidance.

Clause 4 covers inspection procedures and describes thermal checks (4.2) and visual checks (4.3) of the enclosure and circuit breaker condition. Overheating of the circuit breaker would necessitate further investigation, and cracks in the molded case would certainly necessitate circuit breaker replacement.

Clause 5 covers preventive maintenance and ensures that the circuit breaker's life is not compromised by external conditions. The objectives are that the circuit breaker operates in a clean environment and that the terminals are in good condition (5.2), that interchangeable trip units are connected properly (5.3), and that wire connectors are in good condition and are correctly torqued (5.4).

Clause 6 covers nondestructive test procedures that can be used to verify specific operating characteristics of molded case circuit breakers. These include mechanical operation test (6.2), insulation resistance test (6.3), individual pole resistance test (millivolt drop test) (6.4), inverse time overcurrent test (6.5),

instantaneous overcurrent trip test (6.6), and rated hold-in test (6.7). Noncompliance to one or more of these tests could lead to circuit breaker replacement.

Clause 7 covers the operation of accessory devices. Failure of an accessory would lead to replacement of that accessory or circuit breaker replacement if accessories are not removable.

Clause 8 covers inspection and test procedures for insulated case circuit breakers, including checking and servicing the primary connectors and cradle (chassis) if so equipped, and checking and servicing the arc chutes, contacts, and mechanism (if accessible).

Clause 9 covers testing electronic trip units using secondary injection.

In summary, following an automatic overcurrent interruption at or near its interrupting rating, the condition of any protective devices should be checked prior to circuit re-energization. For molded case circuit breakers, the condition of the circuit breaker is assessed without opening or disassembling the breaker. Circuit breakers that have experienced multiple high short-circuit-current faults, as evidenced by conditions at the source of the faults, should require a thorough inspection per the guidelines of NEMA AB 4. This document should also be used for recommended, periodic, preventive maintenance.

<This page is intentionally left blank.>

Currently in preview, click buy full version

1 General

1.1 Scope

NEMA AB 4 sets forth, for use by qualified personnel,¹ a number of basic procedures that may be used for the inspection and preventive maintenance of molded case circuit breakers used in industrial and commercial applications rated up to and including 1000 V 50/60 Hz AC or AC/DC (consult the manufacturer for DC-only or 400 Hz circuit breakers).

The methods outlined may be used to verify specific characteristics of a molded case circuit breaker that was originally built and tested in compliance with the requirements of NEMA standards publication AB 1 (UL 489). These methods are intended for field application and are, therefore, nondestructive in nature. Accordingly, these methods cannot be used to verify all performance capabilities of a molded case circuit breaker since verification of some capabilities requires tests of a destructive nature.

Many tests, including those of a destructive nature, as defined in AB 1 (UL 489), are performed on representative samples of circuit breakers by the manufacturer as part of a routine program of factory inspection.

This publication is not intended, nor is it adequate, to verify proper electrical performance of a molded case circuit breaker that has been disassembled (broken factory seal or removal of rivets), modified, rebuilt, refurbished, or handled in any manner not intended or authorized by the original circuit breaker manufacturer. Such breakers should be removed from service.

1.2 Referenced Standards

In this publication, reference is made to the latest edition of the standards listed below. Copies are available from the indicated sources:

National Fire Protection Association

Batterymarch Park
Quincy, MA 02269

NFPA 70	<i>National Electrical Code®</i>
NFPA 70B	<i>Recommended Practice for Electrical Equipment Maintenance</i>
NFPA 70E	<i>Standard for Electrical Safety Requirements for Employee Workplace®</i>

¹ For purposes of these guidelines, a qualified person is one who has skills and knowledge related to the construction and operation of the electrical equipment and installation and has received safety training to recognize and avoid the hazards involved. In addition, the person is trained:

- and authorized to test, energize, clear, ground, tag, and lockout circuits and equipment in accordance with established safety practices;
- in the proper care and use of protective equipment, such as rubber gloves, hard hats, safety glasses or face shields, and arc-resistant clothing, in accordance with established safety practices;
- in first aid.

Refer to NFPA 70E, *Standard for Electrical Safety in the Workplace*, for electrical safety training requirements.