

NEMA BS 31005-2024

Training Manual on Fire Alarm Systems

Published by:

National Electrical Manufacturers Association

1300 North 17th Street, Suite 900

Rosslyn, Virginia 22209

www.nema.org

© 2024 National Electrical Manufacturers Association. All rights, including translation into other languages, are reserved under the Universal Copyright Convention, the Berne Convention for the Protection of Literary and Artistic Works, and the International and Pan American copyright conventions.

NOTICE AND DISCLAIMER

The information in this publication was considered technically sound by the consensus of persons engaged in the development and approval of the document at the time it was developed. Consensus does not necessarily mean that there is unanimous agreement among every person participating in the development of this document.

The National Electrical Manufacturers Association (NEMA) standards and guideline publications, of which the document contained herein is one, are developed through a voluntary consensus standards development process. This process brings together volunteers and/or seeks out the views of persons who have an interest in the topic covered by this publication. While NEMA administers the process and establishes rules to promote fairness in the development of consensus, it does not write the document and it does not independently test, evaluate, or verify the accuracy or completeness of any information or the soundness of any judgments contained in its standards and guideline publications.

NEMA disclaims liability for any personal injury, property, or other damages of any nature whatsoever, whether special, indirect, consequential, or compensatory, directly or indirectly resulting from the publication, use of, application, or reliance on this document. NEMA disclaims and makes no warranty or warranty, express or implied, as to the accuracy or completeness of any information published herein, and disclaims and makes no warranty that the information in this document will fulfill any of your particular purposes or needs. NEMA does not undertake to guarantee the performance of any individual manufacturer or seller's products or services by virtue of this standard or guide.

In publishing and making this document available, NEMA is not undertaking to render professional or other services for or on behalf of any person or entity, nor is NEMA undertaking to perform any duty owed by any person or entity to someone else. Anyone using this document should rely on his or her own independent judgment or, as appropriate, seek the advice of a competent professional in determining the exercise of reasonable care in any given circumstances. Information and other standards on the topic covered by this publication may be available from other sources, which the user may wish to consult for additional views or information not covered by this publication.

NEMA has no power, nor does it undertake to police or enforce compliance with the contents of this document. NEMA does not certify, test, or inspect products, designs, or installations for safety or health purposes. Any certification or other statement of compliance with any health- or safety-related information in this document shall not be attributable to NEMA and is solely the responsibility of the certifier or maker of the statement.

Contents

- Section 1 General 1
 - 1.1 Scope 1
 - 1.2 Referenced Standards 1
 - 1.3 General Definitions 2
- Section 2 Basic Fire Alarm Systems 16
 - 2.1 General 16
 - 2.2 Control Unit 18
 - 2.3 Notification Methods 18
 - 2.3.1 Non-Coded System 18
 - 2.3.2 Zoned Non-Coded System 18
 - 2.3.3 Coded System 18
 - 2.3.4 Master Coded System 19
 - 2.3.5 March-Time Coded System 19
 - 2.3.6 Selective Coded System 19
 - 2.3.7 Signaling Pattern 19
 - 2.3.8 Zoned Coded System 20
 - 2.4 Emergency Communications Systems (ECS) 20
 - 2.4.1 Other Types of Emergency Communications Systems 20
 - 2.5 Control Unit Operation 21
 - 2.6 Circuits and Pathways 22
 - 2.7 Initiating Device Circuits (IDCs) 23
 - 2.7.1 Two-Wire, Class B Circuit, Using Initiating Devices and an End-of-Line Device 23
 - 2.7.2 Four-Wire, Class A Circuit, Using Initiating Devices 23
 - 2.8 Notification Appliance Circuits (NACs) 24
 - 2.8.1 Two-Wire, Class B, Direct Current Notification Appliance Circuits 24
 - 2.8.2 Two-Wire, Class B, Audio Notification Appliance Circuits 24
 - 2.8.3 Four-Wire, Class A, Notification Appliance Circuits 25
 - 2.9 Signaling Line Circuits (SLCs) 25
 - 2.10 Power Supplies 27
 - 2.11 Supplementary Circuits and Devices 27
 - 2.12 Types of Life Safety Systems 27
 - 2.12.1 Protected Premises (Local) Fire Alarm System (Chapter 23, NFPA 72) 27
 - 2.12.2 Dedicated Function Fire Alarm Systems and Emergency Control Functions 28
 - 2.12.3 In-Building Fire Emergency Voice/Alarm Communications Systems (Chapter 24, NFPA 72) 28
 - 2.12.4 Combination Systems 29
 - 2.12.5 Interconnected Fire Alarm Control Units 30
 - 2.12.6 Emergency Communications Systems 30
 - 2.12.7 Supervising Station Alarm Systems (Chapter 26, NFPA 72) 33
 - 2.12.8 Central Station Service Alarm Systems (Chapter 26, NFPA 72) 33
 - 2.12.9 Proprietary Supervising Station Alarm Systems (Chapter 26, NFPA 72) 34
 - 2.12.10 Remote Supervising Station Alarm Systems (Chapter 26, NFPA 72) 34
 - 2.12.11 Public Emergency Alarm Reporting Systems (Chapter 27, NFPA 72) 36

Section 3 Fire Alarm System Concepts	38
3.1 General.....	38
3.2 Multiplexing or Networking	38
3.3 Circuit Interfaces (Transponders, Data Gathering Panels)	39
3.4 Multiplexed or Networked Outputs	39
3.5 Addressability	41
3.6 Intelligent (Smart) Circuit Interfaces	42
3.7 Programming.....	42
3.8 Addressable Devices.....	42
3.9 Multiplexing Technology.....	43
3.10 Active Multiplex.....	43
3.11 Digital Signaling.....	44
3.12 Analog Sensors	44
3.13 Intelligent Systems	44
3.14 Displays.....	46
3.15 Digital Alarm Communicator Systems (DACs)	46
Section 4 Initiating Devices	47
4.1 Manual and Automatic Alarm Initiating Devices.....	47
4.2 Manual Fire Alarm Boxes	47
4.2.1 Non-Coded Fire Alarm Boxes	47
4.2.2 Coded Fire Alarm Boxes	47
4.2.3 Pre-Signal Fire Alarm Boxes.....	47
4.2.4 General Alarm Fire Alarm Boxes	47
4.2.5 Breakglass Fire Alarm Boxes.....	47
4.2.6 Single-Action Fire Alarm Boxes	48
4.2.7 Double-Action Fire Alarm Boxes	48
4.3 Automatic Alarm Initiating Devices.....	49
4.3.1 Classification of Automatic Fire Detectors	49
4.3.2 Heat-Sensing Fire Detectors.....	51
4.3.3 Smoke-Sensing Fire Detectors	52
4.4 Switches on Automatic Fire Suppression Systems.....	54
4.4.1 Waterflow Switch on Sprinkler Systems	54
4.4.2 Alarm Switches on Fire Suppression Systems	55
4.4.3 Supervisory Monitoring for Sprinkler Systems.....	55
4.5 Installation Wiring	56
4.6 Pathway Class—Circuit Classes for Conventional Initiating Device Circuit (IDC)	59
Section 5 Notification Appliances.....	61
5.1 General.....	61
5.2 Alarm Notification Appliances.....	61
5.3 Audible Alarm Notification Appliances	61
5.3.1 Bells	61
5.3.2 Horns.....	61
5.3.3 Chimes	62
5.3.4 Buzzers	62

5.3.5	Sirens	62
5.3.6	Speakers	62
5.3.7	Electronic Alarms	62
5.4	Visual Alarm Notification Appliances	63
5.5	Combination Audible/Visual Notification Appliances	63
5.6	Exit Marking Audible Notification Appliance	63
5.7	Textual Audible Notification Appliance	63
5.8	Visual Notification Appliance	64
5.9	Textual Visual Notification Appliance	64
5.9.1	Visual Annunciators	64
5.9.2	Lamp Annunciators	64
5.9.3	Drop-Type Annunciators	64
5.9.4	Incandescent Lamp	64
5.9.5	Solid-State Lamp	64
5.9.6	Fluorescent Lamp	64
5.10	Permanent Recorders	65
5.10.1	Punch Registers	65
5.10.2	Print Recorders	65
5.10.3	Time Stamps	65
5.11	Installation Wiring	65
Section 6 Installation Instructions for Life Safety Signaling Systems		68
6.1	General	68
6.2	Location of System Components	68
6.2.1	General	68
6.2.2	Control Units	68
6.2.3	Alarm Initiating Devices	68
6.2.4	Audible Alarm Notification Appliances	69
6.2.5	Visual Alarm Notification Appliances	69
6.2.6	Visual Alarm Signal Annunciators	70
6.2.7	Permanent Recorders	70
6.2.8	Trouble Signal Appliances	70
6.3	Power Supplies	70
6.3.1	Number of Sources Required	70
6.3.2	Primary Power Supplies	71
6.3.3	Secondary Power Supplies	71
6.3.4	Batteries	73
6.4	Requirements for Installation of Wiring and Equipment	73
6.5	Manufacturer's Published Instructions	73
6.6	Local Codes	73
6.7	Types of Circuits	74
6.8	Intermixing of Circuits	74
6.8.1	Non-Power-Limited Circuits and Conductors	74
6.8.2	Power-Limited Circuits and Conductors (NFPA 70, Article 760-136)	74
6.9	Enclosed Versus Exposed Wiring	76

6.10	Selecting Conductors and Cables	76
6.11	Cable Markings.....	77
6.12	Identification of Circuits	77
6.13	Monitoring for Integrity.....	77
6.14	Lightning/Surge Protection (Circuit Protection).....	78
6.15	Outside Wiring.....	78
Section 7 System Startup Procedure.....		79
7.1	General.....	79
7.2	Check of Installation Wiring.....	79
7.2.1	Preliminary	79
7.2.2	Test for Extraneous Voltages.....	79
7.2.3	Test for Shorts and Opens.....	79
7.2.4	Test for Grounds	82
7.2.5	Visual Inspection.....	82
7.2.6	Check of Power Sources	82
7.3	Normal Operation (Normal Monitoring Condition).....	82
7.4	Monitoring of Circuits for Integrity (Electrical Supervision)	83
7.4.1	General	83
7.4.2	Power Supply Circuits.....	83
7.4.3	Initiating Device and Notification Appliance Circuits.....	83
7.4.4	Overcurrent Protection Devices	83
7.4.5	Municipal Circuits.....	83
7.4.6	Supplementary Circuits.....	84
7.4.7	Annunciator Circuits.....	84
7.5	Alarm Operation	84
7.6	Authority Having Jurisdiction.....	85
Section 8 Proper Maintenance of Fire Alarm Systems.....		86
8.1	Periodic Maintenance.....	86
8.1.1	General	86
8.1.2	System Performance and Integrity.....	86
8.2	Fire Alarm Control Units.....	86
8.2.1	Printed Circuit Board Assemblies of Modules.....	86
8.2.2	Relay Maintenance	87
8.2.3	Battery Charger Maintenance.....	87
8.2.4	Factory Maintenance	87
8.2.5	Fuses	87
8.2.6	Circuit Breakers.....	87
8.2.7	Condition of Control Unit Cabinets (Dust and Dirt Removal).....	87
8.3	Non-Coded Manual Fire Alarm Boxes	88
8.4	Coded Manual Fire Alarm Boxes	88
8.4.1	General	88
8.4.2	Spring-Driven Fire Alarm Boxes	88
8.4.3	Motor-Driven Coded Fire Alarm Boxes.....	89
8.5	Automatic Transmitters	89

8.6	Automatic Heat Detectors	89
8.6.1	Fixed-Temperature Heat Detector	89
8.6.2	Rate-of-Rise Heat Detectors.....	89
8.6.3	Rate-Compensation Heat Detectors.....	90
8.6.4	Explosion-Proof Heat Detectors.....	90
8.7	Smoke Detectors.....	90
8.8	Sprinkler Waterflow Detectors.....	91
8.8.1	Pressure Operated.....	91
8.8.2	Vane Operated.....	91
8.9	Gate-Valve Supervisory Contacts	91
8.10	Open Outside Screw and Yoke (OS & Y) Valve Supervisory Contacts.....	91
8.11	Pressure Switches.....	91
8.12	Tank Switches for High and Low Alarm Service on Gravity Tanks.....	91
8.13	Differential Pressure Switches	92
8.14	Inspector's Test Valves	92
8.15	Notification Appliance—Alarm Horns	92
8.16	Notification Appliance—Alarm Bells	92
8.17	Strobe Notification Appliances	93
8.18	Trouble Bells and Buzzers	93
8.19	Remote Switches on Systems.....	93

Figures

Figure 2-1	Two-Wire, Class B Initiating Device Circuit with End-of-Line Resistor	23
Figure 2-2	Four-Wire, Class A Initiating Device Circuit with Return Run to Panel.....	24
Figure 2-3	Two-Wire, Class B Notification Appliance Circuit Using Polarized DC Notification Appliances.....	24
Figure 2-4	Two-Wire, Class B Audio Notification Appliance Circuit Using Capacitor-Coupled Speakers	25
Figure 2-5	Four-Wire, Class A Notification Appliance Circuit with Return Run to Panel	25
Figure 2-6	Two-Wire, Class B Signaling Line Circuit with T-Tap Connection	26
Figure 2-7	Four-Wire, Class A or Class X Signaling Line Circuit	27
Figure 2-8	Example of an In-Building Fire Emergency Voice/Alarm Communications System (Used with Permission from Honeywell)	29
Figure 2-9	Energy Communications Systems Classification.....	31
Figure 2-10	Remote Supervising Station Fire Alarm System Schematic Diagram	35
Figure 2-11	Remote Supervising Station Fire Alarm System Riser Diagram	35
Figure 2-12	Local Energy-Type Auxiliary Alarm System.....	36
Figure 2-13	Shunt Auxiliary Alarm System.....	37
Figure 3-1	Basic Multiplex System Block Diagram Showing Initiating Device Circuits Connected to Circuit Interfaces and to a Signaling Line Circuit	39
Figure 3-2	Basic Multiplex System Showing Notification Appliance Circuits Also Connected to Circuit Interfaces	40
Figure 3-3	Active Multiplex System Using T-Tapped Connections	41
Figure 3-4	Multiplex System Where Nonaddressable Initiating Devices Are Connected to an Addressable Initiating Device that Includes Circuit Interface.....	45

Figure 4-1	Breakglass Fire Alarm Box	48
Figure 4-2	Single-Action Fire Alarm	48
Figure 4-3	Double-Action Fire Alarm Box.....	49
Figure 4-4	An Example of a Current Multi-Criteria Detector	49
Figure 4-5	Spot-Type Example: Thermal Detector.....	50
Figure 4-6	Spot-Type Example: Smoke Detector.....	50
Figure 4-7	Duct Smoke Detector Housing.....	50
Figure 4-8	Current Flow-Through Ionization Detector Sensing Chamber.....	53
Figure 4-9	Projected Beam Smoke Detector.....	53
Figure 4-10	Photoelectric Light Scattering Detector.....	53
Figure 4-11	Waterflow Switch on Sprinkler System	55
Figure 4-12	Initiating Devices, Correctly Wired	57
Figure 4-13	Initiating Devices, Incorrectly Wired.....	57
Figure 4-14	Pigtail Connections, Incorrect Wiring Method.....	57
Figure 4-15	Pigtail Connections, Correct Wiring Method	58
Figure 4-16	Incorrect Wiring Method for Multiriser Initiating Device Circuit	58
Figure 4-17	Correct Wiring Method for Multiriser Initiating Device Circuit	59
Figure 4-18	Correct Wiring Method for Class A Circuit	60
Figure 5-1	Incorrect Installation Wiring Method for a Notification Appliance Circuit	66
Figure 5-2	Correct Installation Wiring Method for a Notification Appliance Circuit	66
Figure 5-3	Correct Installation Wiring Method for Single Notification Appliance Circuit with Two Risers	66
Figure 7-1	End-of-Line Device on Two-Wire, Class B Initiating Device Circuit.....	80
Figure 7-2	End-of-Line Device in Control Unit on Four-Wire, Class A Initiating Device Circuit	80
Figure 7-3	Polarized Diode-Type Notification Appliances Connected in Parallel	81
Figure 7-4	Speaker-Type Notification Appliances Connected in Parallel	81

Tables

Table 6-1	Operating Periods Required by NFPA Standards	72
Table 7-1	Resistance of Conductors.....	81

Foreword

The purpose of this training manual is to provide text material suitable for training persons in the proper physical installation of fire alarm signaling systems. To that end, this manual covers terminology, basic theory of operation, installation details, system startup techniques, and general maintenance.

While the manual may serve as a standalone text, it is best used as a source material for either apprentices or journeymen in a classroom environment using a qualified instructor.

The manual emphasizes installation of basic fire alarm signaling systems instead of how or when to apply the myriad system or equipment options available. Though the manual focuses on installation, the reader is cautioned to follow the specific published installation instructions provided by the manufacturer of systems or equipment being installed.

This information is a technical guide, distinct from mandatory requirements for compliance. It will be updated to keep current with requirements of referenced and/or quoted publications of other organizations. Comments, questions, or recommendations are invited and should be addressed to:

NEMA Technical Operations Department
National Electrical Manufacturers Association
1300 N. 17th Street, Suite 900
Rosslyn, VA 22209

This technical publication was developed by the NEMA Fire, Life Safety, Security, and Emergency Communications Section. At the time it was approved, the section was composed of the following members:

Bosch Security Systems, LLC
Construction Innovations, LLC
Eaton
Figaro USA, Inc.
Gentex Corporation
Google Nest
Honeywell Fire Safety
HSI Fire & Safety Group LLC
Johnson Controls
Keltron Corporation
New Cosmos USA, Inc.
Potter Electric Signal Company, LLC
SDi LLC
Siemens Industry, Inc.
Space Age Electronics, Inc.

< This page is intentionally left blank. >

Currently in preview, click buy full version

Section 1 General

1.1 Scope

This manual, developed by NEMA's Fire, Life Safety, Security and Emergency Communication Section, provides technical information on basic life safety systems in common usage.

This edition of the manual supersedes all prior versions.

Portions of this material are reprinted with permission from the 2022 edition of the National Fire Protection Association NFPA 72® *National Fire Alarm and Signaling Code*®, copyright 2021, National Fire Protection Association, Quincy, Massachusetts. This reprinted material is not the complete and official position of the NFPA on the referenced subject, which is represented only by the standard in its entirety.

1.2 Referenced Standards

Acoustical Society of America
ANSI/ASA S3.41

Audible Emergency Evacuation (E2) and Evacuation Signals with Relocation Instructions (ESRI)

International Code Council
IBC 2021
IFC-2021

International Building Code
International Fire Code

National Electrical Manufacturers Association
NEMA SB 50-2021

Emergency Communications Audio Intelligibility Applications Guide

National Fire Protection Association

NFPA 13-2022

Standard for the Installation of Sprinkler Systems

NFPA 70-2020

National Electrical Code®

NFPA 72-2022

National Fire Alarm and Signaling Code

NFPA 101-2021

Life Safety Code

NFPA 1221-2016

Standard for the Installation, Maintenance, and Use of Emergency Services Communications Systems

NFPA 5000-2021

Building Construction and Safety Code

Underwriters Laboratories
UL 1971

Signaling Devices for the Hearing Impaired

Note: Since NFPA standards and codes are periodically revised, the year of the desired edition of the particular standard or code should be used when referencing the NFPA document involved. Two methods are in common use. One is to reference the code by stating NFPA 72-2013. The other is to refer to the 2013 edition of NFPA 72. If a particular question comes up regarding a standard or code, be sure to correctly identify which edition of the code may be at issue. All states or municipalities that have adopted NFPA codes or standards by reference do not always refer to the latest edition available. Each state or municipality may adopt the NFPA codes in whole or in part. The user should check for local amendments to the codes.